

SONY®

COLOR VIDEO CAMERA

DXC-D35
DXC-D35P
DXC-D35WS
DXC-D35WSP

SERVICE MANUAL

Volume 1 1st Edition

Power HAD
Power HAD WS

⚠ 警告

このマニュアルは、サービス専用です。

お客様が、このマニュアルに記載された設置や保守、点検、修理などを行うと感電や火災、人身事故につながる可能性があります。

危険をさけるため、サービストレーニングを受けた技術者のみご使用ください。

⚠ WARNING

This manual is intended for qualified service personnel only.

To reduce the risk of electric shock, fire or injury, do not perform any servicing other than that contained in the operating instructions unless you are qualified to do so. Refer all servicing to qualified service personnel.

⚠ WARNUNG

Die Anleitung ist nur für qualifiziertes Fachpersonal bestimmt.

Alle Wartungsarbeiten dürfen nur von qualifiziertem Fachpersonal ausgeführt werden. Um die Gefahr eines elektrischen Schlages, Feuergefahr und Verletzungen zu vermeiden, sind bei Wartungsarbeiten strikt die Angaben in der Anleitung zu befolgen. Andere als die angegebenen Wartungsarbeiten dürfen nur von Personen ausgeführt werden, die eine spezielle Befähigung dazu besitzen.

⚠ AVERTISSEMENT

Ce manuel est destiné uniquement aux personnes compétentes en charge de l'entretien. Afin de réduire les risques de décharge électrique, d'incendie ou de blessure n'effectuer que les réparations indiquées dans le mode d'emploi à moins d'être qualifié pour en effectuer d'autres. Pour toute réparation faire appel à une personne compétente uniquement.

CAUTION

Danger of explosion if battery is incorrectly replaced.

Replace only with the same or equivalent type recommended by the manufacturer.

Dispose of used batteries according to the manufacturer's instructions.

ADVARSEL

Lithiumbatteri - Eksplosjonsfare.
Ved utskifting benyttes kun batteri som anbefalt av apparatfabrikanten.
Brukt batteri returneres apparatleverandøren.

Vorsicht!

Explosionsgefahr bei unsachgemäßem Austausch der Batterie.

Ersatz nur durch denselben oder einen vom Hersteller empfohlenen ähnlichen Typ. Entsorgung gebrauchter Batterien nach Angaben des Herstellers.

VARNING

Explosionsfara vid felaktigt batteribyte.
Använd samma batterityp eller en likvärdig typ som rekommenderas av apparattillverkaren.
Kassera använt batteri enligt gällande föreskrifter.

ATTENTION

Il y a danger d'explosion s'il y a remplacement incorrect de la batterie.

Remplacer uniquement avec une batterie du même type ou d'un type équivalent recommandé par le constructeur.

Mettre au rebut les batteries usagées conformément aux instructions du fabricant.

VAROITUS

Paristo voi räjähtää jos se on virheellisesti asennettu.
Vaihda paristo ainoastaan laitevalmistajan suosittelemaan tyyppiin.
Hävitä käytetty paristo valmistajan ohjeiden mukaisesti.

ADVARSEL!

Lithiumbatteri-Eksplosionsfare ved fejlagtig håndtering.

Udskiftning må kun ske med batteri af samme fabrikat og type.

Levér det brugte batteri tilbage til leverandøren.

For the customers in the U.S.A. and Canada

RECYCLING NICKEL-CADMIUM BATTERIES

Nickel Cadmium batteries are recyclable. You can help preserve our environment by returning your unwanted batteries to your nearest point for collection, recycling or proper disposal.

Note: In some areas the disposal of nickel cadmium batteries in household or business trash may be prohibited.



RBRC (Rechargeable Battery Recycling Corporation) advises you about spent battery collection by the following phone number.

**Call toll free number: 1-800-822-8837
(United States and Canada only)**


Caution: Do not handle damaged or leaking nickel-cadmium batteries.

**For the customers in the Netherlands
Voor de klanten in Nederland**

Dit apparaat bevat een MnO₂-Li en Li-ion batterij voor memory back-up.

Raadpleeg uw leverancier over de verwijdering van de batterij op het moment dat u het apparaat bij einde levensduur afdankt.

Gooi de batterij niet weg, maar lever hem in als KCA.



Bij dit produkt zijn batterijen geleverd. Wanneer deze leeg zijn, moet u ze niet weggooien maar inleveren als KCA.

Für Kunden in Deutschland

Entsorgungshinweis: Bitte werfen Sie nur entladene Batterien in die Sammelboxen beim Handel oder den Kommunen. Entladen sind Batterien in der Regel dann, wenn das Gerät abschaltet und signalisiert "Batterie leer" oder nach längerer Gebrauchsdauer der Batterien "nicht mehr einwandfrei funktioniert". Um sicherzugehen, kleben Sie die Batteriepole z.B. mit einem Klebestreifen ab oder geben Sie die Batterien einzeln in einen Plastikbeutel.

X-RAY RADIATION WARNING

Be sure that parts replacement in the high voltage block and adjustments made to the high voltage circuits are carried out precisely in accordance with the procedures given in this manual.

Table of Contents

Manual Structure

Purpose of this manual	3
Related manuals	3

1. Operating Instructions

2. Service Overview

2-1. Board Layout	2-1
2-2. Removal/Attachment of Cabinet	2-2
2-2-1. Removal of Side Plate	2-2
2-2-2. Removal/Attachment of Top Chassis	2-3
2-3. Replacement of CCD Unit	2-5
2-4. Connectores and Cables	2-7
2-4-1. Connector Input/Output Signals	2-7
2-4-2. Connection Connector	2-11
2-5. How to Attach of the Extension Board EX-591	2-11
2-6. Replacement Way of ROM (IC102)	2-12
2-7. Switch Settings on Boards	2-12
2-8. DC-DC Converter Voltage	2-13
2-9. Recommended Replacement Parts	2-14
2-10. Attaching the 4-type or 5-type Viewfinder	2-15
2-11. Disconnecting/Connecting the Flexible Card Wire	2-16
2-12. Service Mode Operation	2-17
2-12-1. Service Menu	2-18
2-12-2. File Menu	2-30

3. Electrical Alignment

3-1.	Preparation	3-1
3-1-1.	Equipment Required	3-1
3-1-2.	Connection	3-1
3-1-3.	Setting Before Adjustment	3-2
3-1-4.	Notes on Adjustment	3-2
3-1-5.	Maintaining the Grayscale Chart	3-3
3-2.	Before Adjustment	3-5
3-2-1.	Color Bar Signal Confirmation	3-5
3-2-2.	Sensitivity Measurement Confirmation	3-5
3-3.	Camera Adjustment	3-6
3-3-1.	Sub-Carrier Frequency Adjustment	3-6
3-3-2.	INT SC-H Phase Adjustment	3-6
3-3-3.	Y/R-Y/B-Y CLP Level Adjustment	3-7
3-3-4.	Y/SYNC/R-Y/B-Y Level Adjustment	3-7
3-3-5.	Carrier Balance Adjustment	3-8
3-3-6.	Chroma (VBS) Level Adjustment	3-9
3-3-7.	Y (VBS) Level Adjustment	3-10
3-3-8.	Y (YC) Level Adjustment	3-10
3-3-9.	Chroma (YC) Level Adjustment	3-11
3-3-10.	VF SYNC/BLKG Level Adjustment	3-11
3-3-11.	CCD Output Level Adjustment	3-12
3-3-12.	Carrier Adjustment at DPR (Double Pixel Reading) ON	3-13
3-3-13.	Shading Adjustment	3-13
3-3-14.	Flare Adjustment	3-14
3-3-15.	MIC Level/MIC Level IND Adjustment	3-15
3-3-16.	Character Position Adjustment	3-16
3-3-17.	4 : 3 Title Adjustment (Only for DXC-D35WS/D35WSP)	3-17
3-4.	Changing the Standard Setting Values (Video Level)	3-18
3-4-1.	Setting Status before Changing the Setting.	3-18
3-4-2.	Changing the Setting Value of Black Level	3-18
3-4-3.	Changing the Flare Compensation Setting Value	3-19
3-4-4.	Changing the Gamma Correction Setting Value	3-19
3-4-5.	Changing the Manual Knee/White Clip Setting Value	3-20

Manual Structure

Purpose of this manual

This is the Service Manual Volume 1 of the color video camera DXC-D35/D35P and DXC-D35WS/D35WSP.

Contains the operation manual related to the operations of this equipment, the replacement of the parts and adjustments.

Related manuals

Besides this Service Manual Volume 1, the following manuals are available for color video camera DXC-D35/D35P and DXC-D35WS/D35WSP.

- **Service Manual Volume 2 (Available on request)**

Part No. 9-955-214-21

This manual describes parts list, semiconductor pin assignments, block diagrams, schematic diagrams and board layouts.

For obtaining, contact your local Sony Sales Office/Service Center.

- **Service Manual DXF-801/801CE (Available on request)**

Part No. 9-955-212-01

This manual describes the replacement of the parts, alignments, parts list, semiconductor pin assignments, block diagrams, schematic diagrams and board layouts of the viewfinder.

For obtaining, contact your local Sony Sales Office/Service Center.

- **Service Manual VCT-U14 (Available on request)**

Part No. 9-977-221-01

This manual describes exploded view and parts list of the tripod adaptor.

For obtaining, contact your local Sony Sales Office/Service Center.

- **Service Manual VCL-918BY (Available on request)**

Part No. 9-977-329-01

This manual describes exploded view and parts list of the zoom lens.

For obtaining, contact your local Sony Sales Office/Service Center.

- **“Semiconductor Pin Assignments” CD-ROM (Available on request)**

This “Semiconductor Pin Assignments” CD-ROM allows you to search for semiconductors used in Communication System Solutions Network Company equipment.

Semiconductors that cannot be searched for on this CD-ROM are listed in the service manual for the corresponding unit. The service manual contains a complete list of all semiconductors and their ID Nos., and thus should be used together with the CD-ROM.

Part number: 9-968-546-XX

SONY.

3-203-895-11(1)

Section 1 Operating Instructions

This section is extracted
from operation manual.

Color Video Camera

Operating Instructions

Before operating the unit, please read this manual
thoroughly and retain it for future reference.

**Power HAD
Power HAD WS**



**DXC-D35K/D35PK
DXC-D35L/D35PL
DXC-D35WSL/D35WSPL
DXC-D35H/D35PH**

© 2000 by Sony Corporation

WARNING

To prevent fire or shock hazard, do not expose the unit to rain or moisture.

To avoid electrical shock, do not open the cabinet. Refer servicing to qualified personnel only.



CAUTION
RISK OF ELECTRIC SHOCK
DO NOT OPEN

**CAUTION: TO REDUCE THE RISK OF ELECTRIC SHOCK,
DO NOT REMOVE COVER (OR BACK).
NO USER-SERVICEABLE PARTS INSIDE.
REFER SERVICING TO QUALIFIED SERVICE PERSONNEL.**

This symbol is intended to alert the user to the presence of uninsulated "dangerous voltage" within the product's enclosure that may be of sufficient magnitude to constitute a risk of electric shock to persons.



This symbol is intended to alert the user to the presence of important operating and maintenance (servicing) instructions in the literature accompanying the appliance.

Owner's Record

The model and serial numbers are located on the top. Record these numbers in the spaces provided below. Refer to them whenever you call upon your Sony dealer regarding this product.

Model No. _____ Serial No. _____

LITHIUM BATTERY

Replace the battery with a Sony CR2032 lithium battery. Use of another battery may present a risk of fire or explosion.

WARNING
Battery may explode if mistreated.
Do not recharge, disassemble or dispose of in fire.

Note
Keep the lithium battery out of the reach of children. Should the battery be swallowed, consult a doctor immediately.

ADVARSEL!
Lithiumbatteri - Eksplosionsfare ved fejlagtig h ndtering. Udskiftning m  kun ske med batteri af samme fabrikat og type.
Lev r det brugte batteri tilbage til leverand ren.

ADVARSEL
Lithiumbatteri - Eksplosionsfare.
Ved uskiftning benyttes kun batteri som anbefalt av apparatfabrikanten.
Brukt batteri returneres apparatleverand ren.

WARNING
Explosionsfara vid felaktigt batteribyte.
Anv nd samma batterityp eller en likv rdig typ som rekommenderas av apparat tverkaren.
K ssera anv nt batteri enligt g llande f reskrifter.

VAROITUS
Paristo voi r j ht   jos se on virheellisesti asennettu. Vaihda paristo ainoastaan laitevalmistajan suosittelemaan tyyppiin.
H vilt  k ytetty paristo valmistajan ohjeiden mukaisesti.



For the customers in the USA and Canada
RECYCLING NICKEL-CADMIUM BATTERIES

Nickel Cadmium batteries are recyclable. You can help preserve our environment by returning your unwanted batteries to your nearest point for collection, recycling or proper disposal.
Note: In some areas the disposal of nickel cadmium batteries in household or business trash may be prohibited.

BBRC (Rechargeable Battery Recycling Corporation) advises you about spent battery collection by the following phone number.

Call toll free number: 1-800-892-8837 (United States and Canada only)

Caution: Do not handle damaged or leaking nickel-cadmium batteries.

For safety reasons, be sure to discharge the battery before discarding it.

For customers in the USA (for DXC-D35K/D35L/D35WSL/D35H)
This equipment has been tested and found to comply with the limits for a Class A digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications. Operation of this equipment in a residential area is likely to cause harmful interference in which case the user will be required to correct the interference at his own expense.

You are cautioned that any changes or modifications not expressly approved in this manual could void your authority to operate this equipment.

The shielded interface cable recommended in this manual must be used with this equipment in order to comply with the limits for a digital device pursuant to Subpart B of Part 15 of FCC Rules.

For the customers in Europe (for DXC-D35PK/D35PL/D35WSP/D35PH)
This product with the CE marking complies with the EMC Directive (89/336/EEC) issued by the Commission of the European Community.
Compliance with this directive implies conformity to the following European standards:
• EN55103-1: Electromagnetic Interference (Emission)
• EN55103-2: Electromagnetic Susceptibility (Immunity)
This product is intended for use in the following Electromagnetic Environment(s):
E1 (residential), E2 (commercial and light industrial), E3 (urban outdoors) and E4 (controlled EMC environment, ex. TV studio).

Table of Contents

Chapter 1

Overview

Product Configurations	7
Features	9
Features on the DXC-D35/D35P/D35WSL/D35WSPL	9
Features on the DXC-D35WSL/D35WSPL	12
Location and function of Parts	13
Camera Head	13
VCL-918BY Zoom Lens	19
DXF-801/801CE Viewfinder	21

Chapter 2

Fitting and Connection

Replacing the Lithium Battery	23
Fitting a VTR	25
Using the Camcorder Grip	27
Fitting the Lens	30
Using Accessories	32
Using the Viewfinder	32
Using an Optional Microphone	33
Fitting to a Tripod	34
Using the Optional CAC-4 Chest Pad	34
Using the Carrying Case	35
Connections	36
Connecting a Portable VTR	36
Connecting a Number of Cameras (Using a Camera Control Unit)	37
Connecting a Number of Cameras (Without Using a Camera Control Unit)	39
Power Supply	40
Using Battery Packs	40
Camera Adaptor Power Supply	41

Chapter 3

Shooting

Basic Procedure for Shooting	43
Using the DynaLatitude Function	45
Shooting with the DSR-1/1P	46
Using the ClipLink Function	46
Using the Edit Search Function While Back Space Editing	48
Using the Freeze Mix Function	49

Chapter 4

Viewfinder Screen Indications and Menus

Viewfinder Screen Indications	51
Changing the Viewfinder Display	51
Viewfinder Normal Indications	54
Status Indications	57
Viewfinder Basic Menu	58
Basic Menu Operations	58
Contents and Settings of Each Page	58
Viewfinder Advanced Menu	64
Advanced Menu Operations	64
Contents and Settings of Each Page	64
Video Output and Viewfinder Picture (For DXC-D35WSL/D35WSPL)	70
Setup Files	71
Calling up a Setup File	71
Changing File Settings	73
Saving File Settings	73
Using SetupNavi and SetupLog with the DSR-1/1P	76
Setting up the Camera Using Data Recorded on Tape	76
Recording the Menu Settings onto a Tape	77
Viewing SetupLog Data	78

Table of Contents

Chapter 5

Adjustments and Settings

White Balance Adjustment	79
Saving an Appropriate White Balance Value in Memory	79
Using the Preset White Balance Settings	81
Light Sources and Color Temperatures	81
Using the ATW (Auto Tracing White Balance) Function	81
Black Balance Adjustment	83
Shutter Settings	84
Setting the Clock and Timestamping Recordings	86
Viewfinder Screen Adjustments	88
Adjusting the Lens	89
Flange Focal Length Adjustment	89
Iris Adjustments	90
Adjusting the Iris Sensitivity	91
Macrophotography	91
Settings for Special Cases	92
Skin Detail Correction	93
Adjusting Color in the Specified Area	93

Appendix

Important Notes on Operation	95
Characteristics of CCD Sensors	96
Warning Indications	97
Specifications	98
Related Products	99
Chart of Optional Components and Accessories	101
What Is ClipLink?	102
How ClipLink Changes Video Production Techniques ...	102
ClipLink Operation Flow	103
Example System Configuration	103
Data Generated When Shooting	104


1
Chapter

Overview

Product Configurations

The eight models, DXC-D35K, DXC-D35L/D35WSL, DXC-D35H, DXC-D35PK, DXC-D35PL/D35WSPL, and DXC-D35PH, comprise both NTSC and PAL versions and the components as shown in the figure on next page. The operation of the basic camera unit is the same in all cases.

Product Configurations



Camera adaptor

The product kit does not include a camera adaptor: to use a camera adaptor, you will need to purchase a model CA-337/537P or CA-327/527P.

Features

Features on the DXC-D35/D35P/D35WSL/D35WSPL

The DXC-D35WSL/D35WSPL is a 1/69 wide-screen type (4:3-16:9 switchable) digital video camera while the DXC-D35/D35P is a 4:3 standard-screen type digital video camera. Common features on both types are described in this section. See also "Features on the DXC-D35WSL/D35WSPL" (page 12) for using the DXC-D35WSL/D35WSPL.

2 1/2-inch IT type Power HAD (WS) CCD

The DXC-D35/D35P Color Video Camera uses 2 1/2-inch IT type Power HAD CCDs. (For the DXC-D35WSL/D35WSPL, Power HAD WS CCDs are used.) It outperforms most of the existing FIT type CCD cameras for high-end use, in both picture quality and sensitivity.

- Smeared: -125 dB (DXC-D35/D35P) or -120 dB (DXC-D35WSL/D35WSPL)
- Sensitivity: F11.0 (at 3200 K, 2000 lux)
- S/N: 63 dB (DXC-D35/D35WSL) or 61 dB (DXC-D35P/D35WSPL)

Sophisticated image processing

TruEye™ processing makes possible the following performance features. This new digital signal processing has brought reproduction of natural colors to the level achieved by the human eye.

Dynal-Attitude™

Enables detailed adjustment of contrast control in each pixel in accordance with a histogram of luminance signal levels (see page 45).

DCC+ (dynamic contrast control plus)

Prevents white breakup when shooting a high intensity subject, and also prevents color faults in high intensity subject.

Black stretch and compress

Enables control of luminance signal levels in black areas without changing the hue.

Variety of detail corrections

- Skin detail function: this function gives a slightly softer appearance to the subject's face. The target skin color can be automatically set.
- Black halo correction
- Red/green vertical detail correction: this function performs vertical detail compensation for both red and green signals.
- Horizontal detail frequency control

Recording and managing setup data

In addition to the setup menu that is displayed in the viewfinder screen, the DXC-D35/D35P/D35WSL/D35WSPL is equipped with the following functions to facilitate camera head setup.

Setup file system

You can use setup files when making adjustments or settings. The DXC-D35/D35P/D35WSL/D35WSPL comes with factory preset files that contain shipped settings and you can freely create user files as well.

Automatic recording of setup data (when using DSR-1/1P)

When the DXC-D35/D35P/D35WSL/D35WSPL is connected to the DSR-1/1P VTR, two types of setup data can be recorded.

SetupLog™: Shooting-related environment settings are recorded onto the tape at intervals of a few seconds. This recorded data can then be used to reproduce the same shooting conditions in subsequent shots. It also makes it easier to identify the causes of problems in previous shots.

SetupNav™: The setup conditions selected with the setup menu and setup files are recorded onto the tape. The recorded setup data can be copied to other camera heads so that the same setup can be shared among several camera heads.



Features



Chapter 1 Overview

ClipLink™ Function (when using DSR-1/1P)

The ClipLink function can be used at every step from acquisition to editing. Information necessary for editing is recorded when shooting to ensure fast and efficient editing operations.

When you set a recording start (Rec IN) point or when you press the TAKE button to set a Mark IN point, the video image at that point is recorded on the tape in compressed form as an Index Picture. In addition, the time codes for such editing points (Mark IN/Mark OUT points or cue points) are recorded along with other editing point data (such as the cassette number and scene number) into cassette memory (as ClipLink log data). Unsuccessful scenes containing faults can also be marked in cassette memory as "NG", so that only the good scenes are taken up from cassette memory when editing.

Dockable with various types of VTRs

The DXC-D35/D35P/D35WSL/D35WSPL docks with the DSR-1/1P DVCCAM VTR to configure a digital camcorder. It also docks with the PVV-3/3P Betacam SP VTR to configure a Betacam SP camcorder. In addition, the DXC-D35/D35P/D35WSL/D35WSPL docks with the EVV-9000/9000P Hi-8 VTR. Using an adaptor (not supplied), it is also able to dock with a variety of existing S-VHS VTRs.

New Functions boost operability

EZ (easy) mode function

When there isn't time to check the camera head settings, simply press the EZ mode button to start the auto adjustment function using standard settings. There is no need to lose a shot for lack of setup time.

EZ (easy) focus

Press the EZ focus button before shooting to ensure a quick and accurate focus.

Programmable gain

The amount of gain relative to the GAIN switch setting (H, M, or L) can be programmed as -3 dB, 0 dB, 3 dB, 6 dB, 9 dB, 12 dB, 18 dB, 18 dB+DPR¹⁾, 24 dB, 24 dB+DPR and hyper gain.

Hyper gain

Hyper gain (36 dB or 42dB, i.e. about 60 times or 120 times greater than 0 dB) can be easily set via one switch setting. This can also be done from remote equipment.

Auto tracing white balance

This function automatically traces the white balance, which constantly changes as lighting conditions change. Auto tracing white balance is especially useful when there is no time to manually adjust the white balance or when shooting moves between indoor and outdoor locations.

Total level control system (TLCS)

Even if the incoming light exceeds the range in which the standard auto iris can control exposure, the auto gain control (AGC) or auto exposure (AE) backs up to ensure proper exposure.

Dual pixel readout (DPR)

When the gain is set to either 18 dB or 24 dB, the gain setting can be doubled (6 dB up) without increasing the noise level.

Recording time display

Recording time can be displayed in either of the following modes.

- Total recording time for all cuts
- Total recording time for current cut

Viewfinder super detail

Video signals for the viewfinder are mixed with DTL signals to make focusing easier.

Dual zebra pattern display

Two types of zebra patterns, zebra 1 and zebra 2 can be displayed simultaneously or independently. The zebra 1 can be set to the levels ranging from 70 to 90 IRE on the DXC-D35/D35WSL (or from 70 to 90% on the DXC-D35P/D35WSPL) and the zebra 2 indicates the levels of 100 IRE for the DXC-D35/D35WSL or more (or the levels of 100% or more for the DXC-D35P/D35WSPL).

Color temperature display

When reading the white balance, the color temperature is displayed on the viewfinder screen.

Switching the color temperatures for the preset white balance

You can select the preset white balance at 3200 K (default) or 5600 K (default) by setting the FILTER control. The preset white balance can be changed to other value through menu setting (see page 59).

Video monitor output with text

The video signal with text superimposed that is shown in the viewfinder can also be output to an external video monitor.

Camera head microphone output indicator

An indication β appears in the viewfinder whenever a signal is being output from the camera head's microphone.

1-kHz reference signal output

Along with a color bar, a 1-kHz reference signal can also be output.

Freeze mix function (when using DSR-1/1P)

The freeze mix function superimposes any previously recorded still picture on the viewfinder screen to facilitate framing the subject when reshooting the scene.

Edit Search Function (when using DSR-1/1P)

When using the DXC-D35/D35P/D35WSL/D35WSPL with the DSR-1/1P, pressing the EDIT SEARCH buttons allow the tape to play back in search mode. Set either of two playback speeds.



Chapter 1 Overview

Designed for ease of operation

Dynafit Pad

Thanks to the Dynafit Pad which fits well to the shoulder, the camera is stable on the shoulder.

Slide cover

The slide cover can hide the switches and buttons that are seldom used during shooting. The cover can be locked so as not to open during shooting.

High-performance viewfinder (DXF-801/801CE)

- High resolution (600 TV lines of horizontal resolution)
- Large-diameter eye cup for easier viewing and focusing
- PEAKING potentiometer for vertical and horizontal detail control
- Two indicators can be used as TALLY indicators.
- Tough die-cast aluminum body
- DISPLAY switch that can turn the character display on and off
- Light that can light the lens control elements
- Switching the aspect ratio automatically between 16:9 (wide screen) and 4:3 (standard screen) when used with the DXC-D35WSL/D35WSPL.

VTR data display

When connected to a VTR, the DXC-D35/D35P/D35WSL/D35WSPL is able to display the following data on the viewfinder screen.

- Time values (counter, time code, or user bit vales)
- VTR audio levels
- Remaining tape time
- VTR operation mode
- Remaining battery capacity (when using an Anton Bauer Intelligent Battery System)
- ClipLink information (when using the DSR-1/1P)

1) DPR = Dual Pixel Readout

Features

Features on the DXC-D35WSL/D35WSP

Features only on the DXC-D35WSL/D35WSP is described in this section. See "Features on the DXC-D35/D35P/D35WSL/D35WSP" (page 9) for common features on a 4:3 standard-screen type digital video camera and 16:9 wide-screen type digital video camera.

Switchable between 16:9 and 4:3 aspect ratios

A simple menu operation provides instant switching between the 16:9 and 4:3 aspect ratios. In 4:3 mode, a screen equivalent to a 4:3 screen is obtained through digital processing of the 16:9 video signals produced by the WS CCD. (See page 68.)

Wide-aspect ID signals

A menu setting is available to add wide-aspect ID signals¹⁾ to 16:9-mode video signals.²⁾ (See page 68.)

Selection of the safety zone size in 16:9 mode

When the aspect ratio is 16:9, you can change the safety zone size through menu setting (see page 65.)

- 1) ID signals complying with EIAJ CPR-1204 (DXC-D35WSL) or complying with ETS WSS (DXC-D35WSP).
- 2) Video signals refer to the following:
 - Video signals output from the VIDEO OUT connector and MONITOR OUT connector.
 - The Y component of Y/C separate signals and the Y component of component signals output from the VTR connector.

Location and Function of Parts

Camera Head

Right side view




Illustration: DXC-D35WS/D35WSP

Location and Function of Parts

④ EZ ("easy") MODE button and indicator
Depress this button (EZ mode on) when you want to be able to shoot immediately, with automatic adjustment of the camera settings to standard values. (See page 68.) When this function is used, the iris and the white balance are adjusted automatically. (The total level control system functions.) Press this button again to return the camera to the previous settings (EZ mode off).

Note
When connecting the CCU-M5/M7 (or CCU-M5P/ M7P) Camera Control Unit or the RM-M7G Remote Control Unit, the "easy mode" function is disabled.

⑤ EZ FOCUS button
Press this button to turn the "easy focus" function on. This opens the iris, to make it easier to focus before beginning shooting. The indication "EZ FOCUS" appears in the viewfinder while the function is on; to turn it off, press the EZ FOCUS button again. If left on, the function automatically turns off after ten seconds.


Note
If the "easy focus" function is still on when you press the VTR button, it turns off automatically and recording starts about one second later.

⑥ EDIT SEARCH buttons (for operation with DSR-1/IP)

When using the DSR-1/IP to record, you can see the search playback while pressing either of these buttons at recording pause mode to quickly find the next recording start point. Two playback speeds are available, and press either of the buttons to the inner position to increase the speed.

⑦ Slide cover lock

This lock keeps the slide cover closed.
Pull the upper panel forward and then lift it up.



⑤ A.IRIS (auto iris) MODE switch and indicator
When you use the auto iris function (by setting the iris selector on the lens to A), set this switch to suit the shooting conditions. Selecting BACK L gives more light to back-lit subjects, and selecting SPOT L adjusts for high contrast in spot-lit subjects. For normal shooting, set this switch to STD.

⑥ ATW (auto tracing white balance) button and indicator

Press this button, turning the indicator on, when you want the white balance to be adjusted automatically to follow changes in lighting conditions. (See page 81.)

⑦ POWER switch

This powers the camera on and off. There are two different ON settings as follows.

ON STBY: This puts the VTR on standby. In this state, pressing the VTR button on the camera head, the lens or a camera adaptor starts recording immediately.

ON SAVE: This puts the VTR in the power-saving state, with the video head drum stationary. In this state, it takes a few seconds to start recording after pressing the VTR button.

Note

The VTR state when this switch is in the ON STBY or ON SAVE position may depend on the VTR model.

⑧ MENU/STATUS switch

When you press this switch to the MENU position, the basic menu is displayed. Keep pressing it to the MENU position to cycle through the various menu displays. When you press the switch to the STATUS position, the DXC-D35/D35P/D35WSI/D35WSPL's status (of current settings) is displayed.

⑨ W. BAL. (white balance) switch

This selects the white balance setting from the preset value, the value in memory A or the value in memory B. (See page 79.)

⑩ OUTPUT/DL/DCC+ (DynaLatitude/dynamic contrast control plus) switch

Use this switch to select the DCC+ function, the DynaLatitude function, or color bar output.

Select the CAM/DCC+ position in most cases.

CAM/DCC+: This activates the DCC+ function. This prevents color faults when shooting high-intensity subjects.

CAM/DL: This setting uses the DynaLatitude function, which finely adjusts the contrast of each pixel according to a histogram of luminance signal levels. Access advanced menu page 2 to set the DynaLatitude function ON or OFF. The DynaLatitude effect can be set to any of three levels, Low, STD (standard), and High with basic menu page 2.

BARS: This setting displays color bars.

For details of menu operation, see Chapter 4 "Viewfinder Screen Displays and Menus" (page 51).

⑪ GAIN switch

This selects one of the three gain settings, high, medium or low. You can choose the gain values assigned to the H, M and L settings from values from -3 dB to 24 dB + DPR and HYPER GAIN. (See page 64.) The factory default selections are 18 dB (H), 9 dB (M) and 0 dB (L).

Note

When the HYPER GAIN switch ⑬ is in the ON position, the GAIN switch has no effect.

⑫ NG button

When using the ClipLink function during shooting, you can designate a particular scene as "NG" (No Good) by pressing this button before shooting the next scene. Press the button again to cancel the NG setting.

⑬ Breaker switch

If there is a fault in the camera power supply, the breaker trips, and the camera power supply is disconnected. Correct the fault in the power supply, then press this switch.

⑭ REC (recording) TIME switch

This selects the recording time indication in the viewfinder.

TTI: Displays the total recording time.

The total recording time is not reset even when you stop the VTR and power off the camera, for example, to replace the battery pack.

DUR: Displays the recording time of the current cut.

OFF/TC: Switches off the recording time display. If, however, a PVV-3/P is connected, and in the advanced menus you set the time code display item (TC IND) to ON (see page 67), then the VTR time data (time code, CTL count, or user bit value) is displayed.

Note
The recording time displayed when this switch is set to the TTI or DUR position is obtained by counting the duration of the internal reference signal input to the camera.

The value may not agree exactly with the value derived from the time code values. Furthermore, the value displayed may not be correct when another manufacturer's VTR is connected to the camera.

⑮ TTL (total) RESET button

Pressing this button resets the total recording time (TTL selection) to zero.

⑯ SKIN DTL (skin detail) switch

Set this switch to ON to use the skin detail correction function.

For details, see "Skin Detail Correction" (page 93).

⑰ SKIN DTL (skin detail set) SET button

Press this button with the SKIN DTL button ⑯ to display the area detect cursor on the viewfinder screen. Place the cursor on the target and press this button to perform skin detail correction.

For details, see "Skin Detail Correction" (page 93).

⑱ SET UP switch

Use this switch to select the camera head setup method.

STD: Set up using the setup menu. Setup file data is not displayed.

FILE: Set up using setup files and the setup menu.

⑲ HYPER GAIN switch

Setting this switch to the ON position increases the gain by a factor of about 60 or 120 with respect to 0 dB (a 30 or 36 dB increase by electronic amplification and a 6 dB increase for DPR, bringing about a total gain increase of 36 or 42 dB).

When this switch is in the ON position, the indication "HYPER" appears in the viewfinder, and the GAIN UP indicator in the viewfinder also lights.

When finished shooting, return this switch to the OFF position. The "HYPER" indication disappears and the GAIN UP indicator goes out.

Note

Increasing the gain with this switch reduces the horizontal resolution by 50%.



Location and Function of Parts



Chapter 1 Overview

① ZEBRA switch

Set this switch to the ON position to display a zebra pattern (diagonal stripes) in the viewfinder. Depending on the zebra setting in advanced menu page 4 (page 65), the zebra 1 for video levels between 70 to 90 IRE (or 70 to 90%) and the zebra 2 for video levels 100 IRE or more (or 100% or more) can be displayed independently or simultaneously.


② UP/ON button

Use this button to open displays and to make "ON" settings. When using the advanced menus, use this button to change menu pages or to switch to the ordinary screen display.

③ DOWN/OFF button

Use this button to close displays and to make "OFF" settings. You can also use this button to change menu pages when using the advanced menus.

Front view



① MIC (microphone) IN +48 V connector (XLR 3-pin, female)

Connect the supplied microphone or an optional microphone (operable with a 48 V supply).

② VF (viewfinder) connector (20-pin)

This is the connector for the DXF-801/801CE viewfinder.

Note

When using this connector, do not connect a DXF-41/51 viewfinder to the VF connector on the left side.

③ MIC LOW CUT switch

Set this switch to the ON position to insert a high-pass filter in the microphone circuit, reducing wind noise. Normally leave the switch in the OFF position.

④ FILTER control

Select the color temperature conversion filter appropriate to the lighting conditions. (See page 43.)

⑤ Lens mount

Attach the zoom lens here.

⑥ SHUTTER switch

Use this switch to set the shutter speed, CLS (clear scan), or EVS setting (see page 84). Usually, set this switch to OFF.

⑦ TAKE button

Press this button to specify an editing point (Mark IN/OUT or cue point) at the current tape position during shooting.

⑧ AUDIO LEVEL knob

When the DSR-1/1P is attached, you can use this knob to manually adjust the channel 1 audio recording level.


⑨ WHT/BLK (white/black) switch

This switch is used for automatic adjustment of the white balance and black balance. (See pages 79 to 83.)

⑩ VTR button

Pressing this button starts and stops recording on the VTR.

Left and upper view



① Fitting for optional microphone holder

You can fit an optional CAC-12 Microphone Holder here. (See page 33.)

② Accessory fitting shoe and screw hole

Attach optional video lights or other accessories here.

③ Shoulder strap fixture

To use the supplied shoulder strap, fix one end here and the other end to the VTR.

④ Viewfinder fitting shoe

Fix the DXF-801/801CE Viewfinder here.

⑤ Viewfinder left-to-right position fixing ring

Loosen this ring to adjust the left-to-right position of the viewfinder. (See page 32.)

⑥ Viewfinder front-to-back position locking catch

Release this catch to adjust the front-to-back position of the viewfinder. (See page 32.)

Location and Function of Parts

① REMOTE connector 1 (mini-jack)
Connect the RM-LG1 Remote Control Unit to enable remote operation of the ClipLink function.

② MONITOR OUT connector (BNC)
Outputs both the camera video and the character information as displayed on the viewfinder screen. You can connect an optional LCD color monitor to this connector.

③ VIDEO OUT connector (BNC)
This outputs the video signal captured by the camera.

④ REMOTE connector 2 (10-pin)
Connect the optional RM-M7G Remote Control Unit to this connector. Set the CAMERA HEAD SELECT switch on the bottom of RM-M7G to 1.

Note

- When using the RM-M7G, note the following points.
- When operating the camera head from the camera control unit, connect the RM-M7G to the camera control unit.
 - EZ mode cannot be used if the RM-M7G is connected to the camera head.

⑤ LENS connector (12-pin, for 7/8-inch lens)
Connect the lens connector.


⑥ VF (viewfinder) connector (8-pin)
This is the connector for the DXF-41/51 viewfinder.

Note

When using this connector, do not connect a DXF-801/801CE viewfinder to the VF connector on the front of the camera head.

⑦ VTR connectors (PRO 76-pin DIGITAL and PRO 50-pin)
Connect a dockable VTR. A PRO 76-pin DIGITAL connector is for the DSR-1/IP and a PRO 50-pin connector is for the PVV-3/P or a camera adaptor.

VCL-918BY Zoom Lens



Location and Function of Parts


- ① **Iris ring**
For manual iris control, set the IRIS selector ⑬ to the "M" position, and turn this ring.
- ② **Zoom ring**
For direct manual zoom control, set the ZOOM selector ⑦ to the "MANU" position, and turn this ring.
- ③ **Focus ring**
Turn this ring to focus the lens on the subject.
- ④ **M (close-up) button**
For close-up work, turn the MACRO ring ⑤ while holding this button down. (See page 91.)
- ⑤ **F.B (flange focal length) adjustment ring and F.B fixing knob**
F.B adjustment ring : To adjust the flange focal length, loosen the F.B fixing knob, then turn the ring. (See page 89.)
F.B fixing knob: Fixes the F.B adjustment ring.
- ⑥ **MACRO (close-up) ring**
For close-up, turn this ring while holding the M button ④ down. (See page 91.)
- ⑦ **ZOOM selector**
This selects the mode of zoom operation.
SERVO: power zoom
MANU: (manual); manual zoom
- ⑧ **Zoom remote control connector (8-pin)**
Connect the optional LO-26 lens remote control unit for remote control of zooming.
- ⑨ **Lens connector (12-pin)**
Connect to the LENS connector (⑪ on page 18) of the Camera Head.

1) **E-E video signal:** "electric-to-electric" video signal.
This is the input video signal which has passed through internal electrical circuits, but has not been converted to a magnetic signal.

- ⑩ **RET (return) button**
This allows you to check the video signal as follows.
When operating with a portable VTR connected via other equipment: when the VTR is in recording, pressing this button connects the E-B video signal from the VTR to the viewfinder.
When operating with a DSK-1/1P or PVV-3/3P mounted on the camera head: when the VTR is in recording pause mode, press this button to review the last few seconds of the recording in the viewfinder (recording review).
- ⑪ **When operating with a CCU-M5/M5P/M7/M7P Camera Control Unit connected:** pressing this button connects the return video signal from the camera control unit to the viewfinder.
When this button is not pressed, the viewfinder displays the video signal captured by the camera.
- ⑫ **VTR button**
When operating with a VTR: this button starts and stops recording, and once more to stop.
When operating with a CCU-M5/M5P/M7/M7P Camera Control Unit connected: pressing this button connects the return video signal from the camera control unit to the viewfinder.
(Starting and stopping recording is controlled on the VTR.)
- ⑬ **Instant automatic iris adjustment button**
While using manual iris control, press this button to switch temporarily to the automatic iris control setting. The automatic setting is maintained as long as you hold the button down.
- ⑭ **IRIS selector**
This selects the mode of iris operation. (See page 14.)
A (automatic): automatic iris
M (manual): manual iris
- ⑮ **Motorized zoom lever**
Use this to carry out a power zoom. Pressing the lever harder increases the zoom speed.
W end: zoom toward wide angle
T end: zoom toward telephoto

DXF-801/801CE Viewfinder

You can switch the scan size of the DXF-801/801CE in accordance with the aspect ratio selected on the camera or camcorder.



- ① **Eyepiece focusing knob**
Turn this to adjust the viewfinder focus to match your eyesight. (See page 88.)
- ② **Stopper**
Lift up when detaching the viewfinder (See page 32).
- ③ **LIGHT switch and light**
The light lights the lens and the switch controls the light as follows.
HIGH/LOW: Turn the light on and control the brightness.
OFF: Turns the lights off.
- ④ **TAKE/TALLY indicator (orange)**
When using the ClipLink function while shooting, this indicator lights when the TAKE button (⑦ on page 17) has been pressed to set a Mark IN point and goes out when a Mark OUT point is set.
- ⑤ **BATT (battery) indicator (red)**
This lights when the battery capacity is low.

Note

When using a camera control unit, this indicator flashes when you operate the controls, but this is not a malfunction.



Chapter 1 Overview

- ④ RECTALLY (recording/tally) indicators (red)**
• This flashes from the time when you press the VTR button (④ on page 17 and ④ on page 20) on the lens or camcorder until recording starts, then stays on continuously during recording.
• When using a camera control unit, this lights when the video from the camera is selected.
• This is also used to indicate a fault. (See page 97.)
• The lower indicator can be disabled by menu setting. (See page 66.)
- ⑦ GAIN UP indicator (orange)**
This lights when the gain is 3 dB or more.
- ⑤ SHUTTER indicator (red)**
This lights when the SHUTTER switch (⑤ on page 17) is in the ON position. (If the EVS is selected, the indicator will not light.)
- ⑥ PEAKING control**
This adjusts the outline intensity of the viewfinder image. (See page 88.)
- ④ CONTRAST control**
This adjusts the contrast of the viewfinder image. (See page 88.)
- ④ Tally lamp**
When the TALLY switch (④) is in the ON position, this operates in the same way as the RECTALLY indicators ④.
- ④ BRIGHT (brightness) control**
This adjusts the brightness of the viewfinder image. (See page 88.)
- ⑥ Eyepiece release catch**
To view the viewfinder screen directly, press this catch, and hinge up the eyepiece.
- ④ TALLY switch**
Set this switch to the ON position to use the tally lamp ④.

Fitting and Connections

Replacing the Lithium Battery

The camera head uses a lithium battery (CR2032) to retain date and time data.
When the lithium battery's voltage falls, the clock indication does not appear. Replace the lithium battery and set the clock (see page 86).


Notes

- Carefully read the instructions for replacing the lithium battery. **Lithium batteries may explode if misused.**
- Use only CR2032-type lithium batteries. Other types of lithium batteries may come loose when the camcorder is moved. If you have difficulty finding CR2032-type lithium batteries, contact your Sony dealer.


Replacing the Lithium Battery

- 1 Pull the upper part of the battery cover (on the rear of the camera head) forward and turn the cover clockwise.

For detaching the VTR or camera adaptor, see "Fitting a VTR" next page.



- 2 Take out the lithium battery.



Press down and pull out toward you.

- 3 Reverse step 2 to insert a replacement lithium battery. Make sure that the + symbol on the battery is facing you.

- 4 Close the battery cover.


Fitting a VTR

This section explains how to attach the DSR-1/IP to the camera head. The method for attaching a PVV-3/3P is similar.


When replacing the camera head grip with a camcorder grip, see "Using the Camcorder Grip" (page 27).

- 1 Set the PRO 76-pin DIGITAL connector on the DSR-1/IP. (The camera connector on the PVV-3/3P is PRO 50-pin.)


For details, see the operating instructions for the DSR-1/IP.



- 2 Loosen the two screws and remove the shoulder pad.




- 3 Align the projection on the bottom of the DSR-1/IP with the slot on the camera head.




(continued)

Fitting a VTR

- 4 Slide the DSR-1/IP and the camera head together in the groove as far as possible.



- 5 Tighten the two screws in the grip connector and the two screws in the shoulder pad section.



- 6 Attach the shoulder pad.

To remove the VTR
Reverse the fitting procedure.

To fit a camera adaptor
Follow the same procedure as when fitting a VTR.



Using the Camcorder Grip


When using the camera head with a VTR as a camcorder, you can replace the camera head's grip with a camcorder grip (not supplied). The type of camcorder grip and the method for attaching it differ slightly depending on the type of VTR.

Attaching a camcorder grip to the DSR-1/IP


- 1 If the viewfinder is attached, adjust the viewfinder to the full-forward position.

For details, see "Adjusting the viewfinder position" on page 32.


- 2 Remove the camera head grip's three screws, then pull up the grip to remove it.



- 3 Remove the VTR connection plate.



- 4 Remove the DSR-1/IP's shoulder strap fitting and the camera head connection plate.



(continued)


Fitting a VTR

5 Perform the first three steps in "Fitting a VTR".


6 Screw the connection plate (supplied with the grip for the DVCAM camcorder) which straddles the connection between the camera head and the DSR-1/IP. Also, tighten the two screws in the shoulder pad section. (See step 5 on page 26.)

7 Screw the grip for the DVCAM camcorder.


3 Remove the grip's three screws, then pull up the grip to remove it.



4 Remove the PVV-3/3P's shoulder strap fitting.



5 Screw the grip for the Betacam camcorder.



Attaching a camcorder grip to the PVV-3/3P

1 Perform steps 2 to 4 in "Fitting a VTR".

2 If the viewfinder is attached, adjust the viewfinder to the full-forward position.

For details, see "Adjusting the viewfinder position" on page 32.

Fitting the Lens

In the case of the DXC-D35K/D35PK model, the lens is already fitted. In other cases, use the following procedure to fit the lens.


- Remove the retaining rubber which prevents the lens mount from coming loose, then raise the lens fixing lever, and remove the lens mount cap.
- With the lens fixing lever turned fully counterclockwise, push in the lens, aligning the projection on the lens with the cutout on the camera.
- Supporting the lens, turn the lens fixing lever fully clockwise. Replace the retaining rubber on the lens mount.



- Using the triangular mark as a guide, push the lens connector into the LENS connector on the camera head, until it clicks into place. Fasten the cable with the clamps.

Fitting optional filters

Loosen the lens hood fixing screw to remove the lens hood, then attach the filter.




Using Accessories

Using the Viewfinder


Removing the Viewfinder

Remove any microphone from the viewfinder before beginning.

- 1 Pull the viewfinder connector out of the VF connector on the front of the camera head.



- 2 Loosen the viewfinder left-to-right position fixing ring, then pulling up the retaining catch, slide the viewfinder out.




To fit the viewfinder

Reverse the removal procedure.

Adjusting the viewfinder position

To adjust the viewfinder left-to-right position, loosen the left-to-right fixing ring, and to adjust the front-to-back position loosen the front-to-back position locking catch.



Left eye adaptor

By fitting a left eye adaptor, you can use the camera with your left eye to the viewfinder.

Note

You cannot stow the camera attached with a left eye adaptor in the LC-421 Carrying Case.


For details, consult your Sony dealer.

Using an Optional Microphone

To use a long microphone such as the optional ECM-670/672, fit an optional CAC-12 Microphone Holder to the camera, then mount the microphone in this holder.

Fitting the optional CAC-12 Microphone Holder


Remove the two retaining screws (M3 x 8) for the optional microphone holder, then use these screws to attach the CAC-12 Microphone Holder.




Fitting an optional microphone

Use the following procedure to attach an optional ECM-670 Microphone.

- 1 Loosen the screw of the CAC-12 Microphone Holder, then open the holder and replace the microphone adaptor with the one supplied with the ECM-670 Microphone.



- 2 Insert the microphone in the microphone holder, close the holder, and tighten the screw. Connect the microphone cable to the MIC IN +48 V connector.




Using Accessories


Fitting optional microphones (operable with a 48 V supply) other than the ECM-670
Use the same fitting procedure as for the ECM-670, but note the following differences with respect to the microphone adaptor.
ECM-672: no microphone adaptor required.
Slender microphones (19 mm (3/4 inch) diameter):
use the microphone adaptor supplied with the CAC-12.

Fitting to a Tripod

First fit the VCT-U14 Tripod Adaptor to the tripod, then mount the camera on the tripod adaptor.




Removal



Note

After removing the camera, if the tripod adaptor pin has not returned to its original position, hold down the red button and move the lever in the direction of the arrow to return the pin to its original position. It is not possible to mount a camera with the pin left out.



Using the Optional CAC-4 Chest Pad

When using the camera on your shoulder, attaching the optional CAC-4 Chest Pad reduces the load on your right hand supporting the zoom lens, and makes operation easier.

For details see the instructions provided with the CAC-4.


Using the Carrying Case

Stowing the camera


Align the camera with the base of the case, and slide the camera in forward.
Checking that the pin at the rear engages correctly, push forward until it locks into place.

Notes

- Bring the viewfinder into the horizontal position, slide it fully rearward and to the left, then fix before stowing.
- When an optional microphone (ECM-670/672, C-74, etc.) is attached, loosen the microphone fixing screws, move the microphone to the lowest position, and fix before stowing.



Example of fully-stowed carrying case



Connections

Connecting a Portable VTR

Using the optional CA-537/537P or CA-327/327P Camera Adaptor and a camera cable, you can connect a portable VTR. Set the VTR selector switch on the camera adaptor according to the VTR connected.


If using a VTR from another manufacturer, consult your Sony dealer.

Checks before making connections

Check first that the video camera, camera adaptor, VTR, and other devices are all powered off.

Making connections

Using a camera cable, connect the VTR/CCU/CMA connector on the camera adaptor to the camera input connector of the VTR.



Camera cable

- Select a camera cable to fit the camera input connector on the VTR you are using.
- The maximum camera cable extent is 10 m (33 ft).


For details, consult your Sony dealer.

Video monitor

- If using an S-VHS VTR, using a video monitor with an S-video input connector and connecting it to the S-video connector of the VTR will allow you to monitor a clear picture, with no flicking.
- The output video signal from the VIDEO OUT connector of this unit is a composite video signal. Connect the VIDEO OUT connector of this unit to a composite video signal input connector of the monitor.

Setting the VTR selector switch on the camera adaptor

When using the camera with a CA-537/537P/327/327P Camera Adaptor, it is essential to correctly set the VTR selector switch on the camera adaptor according to the VTR connected. This switch determines the type of video signal output from the VTR/CCU/CMA connector and the audio output signal level.



VTR selector settings on the CA-537/537P

Connected VTR	VTR selector switch setting	Video output signal	Audio output signal level
Sony broadcast and professional VTRs: BVU-150/VO-6800/6800PS*, BVW-50/50P and BVV-5/5FS*	1	Composite (BVU-150/VO-6800/6800PS) or component (BVW-50/50P and BVV-5/5FS)	-60 dB
Sony professional VTRs: VO-8800/8800P and EVV-9000/9000P	3	Y/C	-60 dB
Panasonic AG-6400 VHS VTR	2	Composite	-20 dB
Panasonic AG-7400 S-VHS VTR and JVC BR-S40S S-VHS VTR	3	Y/C	-20 dB

- Set the audio input level on the VO-6800/6800PS to -60 dB.
- When the BVV-5/5FS is used as a portable VTR, a V-A-53P VTR Composite/Component Adaptor is required.
- Set the input selector switch on the AG-7400 to Y/C.

Connecting a Number of Cameras (Using a Camera Control Unit)

When using a number of cameras in the studio, it may be necessary to use a CCU-M5/M5P/M7/M7P Camera Control Unit to provide video and color sync between cameras, and special effects and other devices to allow switching, wipes and so forth.

In the studio it may also be convenient to use a DXF-41/51 Viewfinder.

The figure in the next page shows an example studio configuration.

For details, consult your Sony dealer.

Notes


- When using a camera control unit, put the camera head into the EZ mode off state beforehand (see page 14). (Otherwise, it is impossible to access the advanced menu.)
- With the DXC-D35/D35P/D35WS/D35WSP, color matrix switching on the CCU-M5/M5P is invalid.
- When the DL in advanced menu page 2 is set to ON (see page 64) and the OUTPUT/DL/DCC+ switch is set to DL, knee adjustment does not function on the CCU-M7/M7P.



VTR selector settings on the CA-327/327P


Connected VTR	VTR selector switch setting	Video output signal	Audio output signal level
Sony broadcast and professional VTRs: BVU-150/VO-6800/6800PS*	1	Composite	-60 dB
Sony professional VTRs: VO-8800/8800P and EVV-9000/9000P	3	Y/C	-60 dB
Panasonic AG-6400 VHS VTR	2	Composite	-20 dB
Panasonic AG-7400 S-VHS VTR	4	Y/C	-20 dB

- Set the audio input level on the VO-6800/6800PS to -60 dB.
- Set the input selector switch on the AG-7400 to Y/C.



Connecting a Number of Cameras (Without Using a Camera Control Unit)

When using two or more synchronized cameras without a camera control unit, connect an external sync signal to the GEN LOCK IN connector on the camera adaptor (CA-537/537P etc.), supplying a VBS or BS menus. (See page 59.)



Power Supply

This unit operates on either a battery pack or an AC supply (using the optional CMA-8A/8ACE AC Adaptor).

For details of the power supplies which can be used, refer to the documentation supplied with the VTR connected to this unit or the camera adaptor.

Using an Anton Bauer Intelligent Battery System and Ultralight System
Fitting the special battery mount made by Anton Bauer Corporation to this unit allows you to use their Intelligent Battery System and Ultralight System.

For details, consult your Anton Bauer products supplier or Sony dealer.

Using Battery Packs


Always fully charge a battery pack before using it.

Notes

- Be careful that other metal objects do not come in contact with the metal parts of the battery pack, as this could cause a short.
- Do not leave the battery pack in the camera if it is not going to be used for a long time.
- If the battery pack is recharged after use while still hot, it may not be possible to obtain a full charge.

Fitting a battery pack (NP-1B)

Open the lid of the battery case, insert a fully-charged battery pack, and close the lid.



Battery pack operating times

The following table shows approximate continuous operating times, when operating the camera and 1.5-inch viewfinder at normal temperatures, with a camera adaptor and an DSR-1/1P or PVV-3/3P connected.

Approximate operating times with a fully-charged battery pack

DXC-D35/D35P			
Battery pack	With camera adaptor	With DSR-1/1P	With PVV-3/3P
NP-1B	110 minutes	60 minutes	60 minutes
NP-1A	85 minutes	45 minutes	50 minutes
BP-90A*	—	130 minutes	140 minutes

DXC-35WSL/D35WSPL

Battery pack	With camera adaptor	With DSR-1/1P or PVV-3/3P
NP-1B	95 minutes	50 minutes
NP-1A	70 minutes	35 minutes
BP-90A*	—	105 minutes

a) Requires the special-purpose DC-500 Battery Case. Cannot be used with a camera adaptor.

Battery low indications

When the voltage of the supply to the camera head lowers to or below 11.0 V, the battery voltage indication appears in the viewfinder. At this time, the BATT indicator in the viewfinder flashes when operating with the DSR-1/1P or PVV-3/3P. If you continue using the camera head, the BATT indicator lights up.
When the battery pack is low, replace it with a fully-charged battery pack.

Battery pack charging

Before using a battery pack, charge it as shown in the following table.

Battery pack	Battery charger	Approximate charging time (normal temperature)
NP-1A	BC-1WD/1WDCE, BC-410/410CE	70 minutes
NP-1B	BC-1WD/1WDCE, BC-410/410CE	95 minutes
BP-90A	BC-410/410CE	160 minutes

For details of battery charger operation, refer to the instructions provided with the battery charger to be used.

Camera Adaptor Power Supply

The camera adaptor automatically operates on power supplied to the VTR/CCU/CMA connector from the portable VTR, CCU-M7/M7P Camera Control Unit, CMA-8A/8ACE AC Adaptor or other connected device.

Note

Before use, check that the device connected to the VTR/CCU/CMA connector is able to provide the power required by the camera.
If it is not able to provide the necessary power, or when it is necessary to prolong the operating time, use the camera with a separate power supply.




3

Chapter

Shooting

Basic Procedure for Shooting



- 1** Attach the VTR or camera adaptor to the camera head, then turn each device's power on.
- 2** Set the FILTER control appropriately for the lighting conditions.

(continued)

Basic Procedure for Shooting

Filter setting	Lighting conditions
1 (3200K)	Studio halogen lighting (incandescent), sunrise and sunset.
2 (5600K + 1/8 ND)	Sunlight. This setting includes a 1/8 neutral density filter (reducing the exposure by the equivalent of three stops). Use it to prevent "burning" or to reduce the depth of field.
3 (5600K)	Cloudy or rainy outdoor shooting, and fluorescent lighting.
4 (5600K + 1/4 ND)	Sunlight. This setting includes a 1/4 neutral density filter (reducing the exposure by the equivalent of six stops). Use it to prevent "burning" or to reduce the depth of field.

- 3 Check the switch settings on the camera head.
(See pages 13 to 18.)
If there is not sufficient time to check the camera settings, you can use "easy mode" by setting the EZ MODE switch to the ON position. The camera is automatically adjusted to standard settings, and the iris and the white balance are adjusted automatically. (See page 68.)
 - 4 Check the settings in the basic menu (page 58) and advanced menu (page 64).
 - 5 Check the lens settings (pages 30 and 31) and flange focal length adjustment (page 89).
 - 6 Adjust the eyepiece focus, and the contrast and brightness of the viewfinder image (page 88).
 - 7 Check the sound system settings.
 - Microphone connections
 - Settings on the VTR (refer to the VTR instructions)
 - 8 If required, switch on the center marker and/or safety zone (basic menu page 5 and advanced menu page 4) and zebra pattern (ZEBRA switch) in the viewfinder image.
 - 9 Adjust the white balance (page 79) and black balance (page 83).
- 1) **Hunting:** This occurs if the automatic iris function is not able to reach a stable state, and as a result the image brightness keeps changing, alternately lighter and darker.

2) **Depth of field:** This is the range over which the subject is sharply in focus.

- 10 Turn the focusing ring so that the subject is sharply in focus. It may be convenient to use the EZ FOCUS button for the "easy focus" function (see page 14).
- 11 Set up the VTR according to your shooting objectives, then start recording.
If a camera control unit is not connected: Press the VTR button on the camera head or on the lens.
If a camera control unit is connected: Press the VTR's record button to begin recording.

For details of VTR setup and operations, see your VTR's operating instructions.

- During recording, the REC/TALLY indicator(s) in the viewfinder light(s), and "REC" appears on the viewfinder screen.
- Depending on the setting of the REC TIME switch (See page 15), you can display the total recording time or the length of the camera cut on the viewfinder screen.
- When recording on the DSR-1/1P, you can use the AUDIO LEVEL knob on the front of the camera head to manually adjust the channel 1 audio level. To do this, you must first set up the DSR-1/1P to enable manual adjustment of the audio recording level.

For details of this operation, see the operating instructions for the DSR-1/1P.

- 12 To pause recording, press the VTR button again.

Reviewing the recording


It is possible to review the last few seconds of the recording on the tape (recording review). Press the VTR button to pause recording, then press the RET button on the lens. Depending on how long the button is pressed, the tape is automatically rewound over the last two to ten seconds from the paused position, and then this part is played back in the viewfinder. If the RET button is kept pressing, about ten seconds of the recording review is possible. The VTR then returns to the paused state.

Note

This function may not be provided by some VTRs. Refer to the instructions for the VTR.

Using the DynaLatitude Function

This function detects the bright and dark parts of the subject and automatically adjusts for the appropriate contrast. The DynaLatitude function enables fine-grained contrast adjustment according to the luminance level of each pixel. It is effective when shooting scenes with mixed light and dark parts.



However, the brightness of the subject on the screen may change if the subject moves during shooting. Also, for some subjects, there may be increased noise in dark sections of the picture.

For information on turning this function on and off, see page 64. For information on setting effect levels, see page 59.

Shooting with the DSR-1/IP

The DXC-D35/D35P/D35WS/D35WSP docks with the DSR-1/IP to configure a DVCAM Camcorder. The following describes how to shoot using a DVCAM camcorder.

Using the ClipLink Function

The ClipLink function can be used at all stages from shooting to editing. This function makes editing operations more efficient by automatically recording index pictures (Mark IN point images) that provide a searchable index of recorded scenes, along with other data such as time code and scene numbers.


For concept of the ClipLink function, see the section "What Is ClipLink" (page 102).

1 Dock the DSR-1/IP to the camera head and turn on the power, then perform steps **2** to **10** from "Basic Procedure for Shooting" (page 43).

2 Insert a cassette into the DSR-1/IP and set ClipLink mode to ON by menu setting.

For details of this operation, see the operating instructions for the DSR-1/IP.

The following display appears on the viewfinder screen.



a) For details, see "Basic menu page 6" (page 60).

To record the cassette name/number
Access basic menu page 6 to specify a name or number for the inserted cassette.

For details, see "Basic menu page 6" (page 60).

3 Press the VTR button on the camera head or the lens.

The DSR-1/IP starts recording, and the REC/TALLY indicator lights in the viewfinder. Meanwhile, the time code at the recording start point (Rec IN) is recorded (HH:MM:SS) in the DSR-1/IP's internal memory.

4 When a shooting of the scene completes, press the VTR button on the camera head or the lens.

This pauses recording.

To continue recording the next scene, repeat steps **3** and **4**. The scene number will be automatically incremented.

To set/clear NG (No Good)

If you press the NG button before you start shooting the next scene, the previous scene will be designated as "NG" (the "NG" display appears in the viewfinder).

Once NG has been set, you can cancel it by pressing the NG button again before you start shooting the next scene (the "NG" display in the viewfinder disappears, which means that the previous scene has been re-designated as "OK"). Each time you press the NG button before starting shooting the next scene, the status of the previous scene toggles between "NG" and "OK". It is always the last selected status that will take effect and be stored in the cassette memory.

5 To finish recording, press the STOP button on the DSR-1/IP.

This stops recording.

Note

When using the ClipLink function while shooting, if you continue shooting after stopping or if you change the tape's recording position, your subsequent shots may overwrite and erase the previously recorded ClipLink log data (time codes, scene number, etc.) or index pictures.

To avoid this problem, press the DSR-1/IP's ClipLink CONTINUE button before restart of shooting.

For details, see the operating instructions for the DSR-1/IP.

Setting Mark IN/OUT points as you shoot

Instead of continuing shots from scene to scene, you can specify Mark IN and Mark OUT points as you shoot and set scene numbers (ranging from 001 to 198).

1 Perform steps **1** and **2** from "Using the ClipLink Function" (page 46).

2 Access basic menu page 6 and perform the following operations.

1) Set MARK/CUE to MARK.
The ClipLink mode indication "CLIP M" appears on the viewfinder screen.


2) Set the cassette name or number if necessary.

For details of menu operations, see "Basic Menu Operations" (page 58).

3 Press the VTR button on the camera head or the lens.

The DSR-1/IP starts recording, and the REC/TALLY indicator(s) light(s) in the viewfinder.

4 Press the TAKE button when you find a shot where you would like to set a Mark IN point.



The TAKE/TALLY indicator (orange) lights in the viewfinder and "TAKE" appears on the screen.

5 Press the TAKE button when you find a shot where you would like to set a Mark OUT point.

The TAKE/TALLY indicator (orange) goes out in the viewfinder and the "TAKE" disappears from the screen.

At this time, the time code (HH:MM:SS) at the Mark IN/OUT point for scene 001 is recorded to the DSR-1/IP's internal memory, and then recorded to the cassette memory.

To set/clear NG

If you press the NG button before you set the next Mark IN point, the previous scene will be designated as "NG" (the "NG" display appears in the viewfinder).

Once NG has been set, you can cancel it by pressing the NG button again before you set the next Mark IN point (the "NG" display in the viewfinder disappears).

6 Repeat steps **4** and **5** as needed to record (to cassette memory) time codes at Mark IN/OUT points, scene numbers, and NG designations to the cassette memory.

The scene number is automatically incremented each time you specify a Mark OUT point.

7 To finish shooting, press the VTR button on the camera head or the lens, then press the DSR-1/IP's STOP button.

This stops the recording operation.
The index pictures of each Mark IN point are recorded onto the tape.

Shooting with the DSR-1/IP

Setting cue points as you shoot

You can make edit search operations easier by specifying cue points to highlight scenes.

- 1 Perform steps 1 and 2 in "Using the ClipLink Function" (page 46).
- 2 Access basic menu page 6 and perform the following operations.
 - 1) Set MARK/CUE to CUE.
 The ClipLink mode indication "CLIP C" appears on the viewfinder screen.

- 2) Set the cassette name or number if necessary. For details of menu operations, see "Basic Menu Operations" (page 38).

- 3 Press the VTR button on the camera head or the lens.

The DSR-1/IP starts recording, and the REC/TALLY indicator lights in the viewfinder. Meanwhile, the recording start point (Rec IN) is recorded in the DSR-1/IP's internal memory.

- 4 Press the TAKE button when you find a shot where you would like to set a cue point.

The "CUE" indication appears (for about 1 second) on the viewfinder screen. At this point, the time code (HH:MM:SS:frame) at the cue point is recorded into the cassette memory.

- 5 Repeat step 4 to specify more cue points.

- 6 To finish shooting, press the VTR button on the camera head or the lens, then press the DSR-1/IP's STOP button.


This stops recording operation.

Time codes (HH:MM:SS) and scene number (scene 001) are recorded to the cassette memory and the index picture of the Rec IN point is recorded onto the tape.

Using the Edit Search Function While Back Space Editing

While the DSR-1/IP is in recording pause mode, press and hold the EDIT SEARCH buttons to activate the search playback function for as long as you hold down the button. You can use the edit search function to find the desired tape location after a recording stop during back space editing or when continuing to record from any other location on the tape.

- 1 Dock the DSR-1/IP to the camera head and turn on the power, then insert a cassette into the DSR-1/IP.
- 2 Perform steps 2 to 12 in "Basic Procedure for Shooting" (page 43).
- 3 Press and hold either of the EDIT SEARCH buttons (REV or FWD)



The tape is moved in reverse or forward search mode for as long as you hold down the REV or FWD button, and the image is shown in the viewfinder.

To change the playback speed

Press the REV or FWD button down firmly into the inner position to make the tape move at the faster speed. Press the button down lightly to make the tape move at the slower speed.

Note

Do not shut off the camera head's power while using the edit search function. The DSR-1/IP may not be able to find the continue point.

- 4 Release the REV or FWD button when you find the tape location where you wish to continue shooting.

The DSR-1/IP enters recording pause mode.

- 5 Press the VTR button on the camera head or the lens.

The DSR-1/IP starts recording.

Using the Freeze Mix Function

The freeze mix function superimposes a freeze-frame image of a previously recorded shot on the shooting image displayed on the viewfinder screen. You can use this function to easily frame a subject within the same framework from a previous shot.

Note

When the camera head is in EZ mode, the freeze mix function is disabled. Release the EZ mode beforehand. (See page 14.)


- 1 Dock the DSR-1/IP to the camera head and connect a color monitor to the MONITOR OUT connector.
- 2 Perform steps 2 to 10 from "Basic Procedure for Shooting" (page 43).

- 3 Play back the tape on which the image to be used for framework alignment has been recorded.

For playback operation, refer to the operating instructions for the DSR-1/IP.


- 4 Press the MENU/STATUS switch down.

The following indication appears on the screen.



- 5 Press the UP/ON button when you see the image you want to freeze.

The frozen playback image is displayed, mixed with the shooting image, in monochrome. The indication "FREEZE MIX ON" appears on the screen.



To release the freeze mix mode, press the UP/ON button again.

To change the freeze-frame image

Press the DSR-1/IP's PLAY button. This returns to the screen shown in step 3 above, and color playback mode begins.

Use the DSR-1/IP's tape transport buttons to find the desired image and then perform steps 4 and 5 again.

- 6 Once you have framed your subject, press the UP/ON button to cancel the freeze function.

- 7 Find the recording start point or insert a new cassette for recording, then begin recording.

Note

If you use the DSR-1/IP's tape transport buttons during back space editing, the back space editing mode will be stopped. When you were using the ClipLink function when shooting, if you simply restart the recording you will lose any ClipLink data that was recorded. To avoid this, press the DSR-1/IP's ClipLink CONTINUE button before restarting recording.

For details, see the operating instructions for the DSR-1/IP.



Viewfinder Screen Indications and Menus

Viewfinder Screen Indications


There are four types of indication screen which appear in the viewfinder, as follows.

- **Normal indications**
These show the operating state of the camera and connected VTR. (See page 54.)

- **Status indications**
Pressing the MENU/STATUS switch up while the normal indications are present calls a display of current settings. (See page 57.)

- **Basic menu**
These provide settings for the lens iris, shutter speed and so forth, and also a tilting screen. (See the section "Viewfinder Basic Menu" page 58.)

- **Advanced menu**
These provide settings for the center marker, zebra pattern, viewfinder screen indications, and so forth. (See the section "Viewfinder Advanced Menu" page 64.)



Displaying the normal indications and switching to the basic menu

To display the normal indications, move the POWER switch to the ON position.
To switch to and from the basic menu, use the MENU/STATUS switch.

Changing the Viewfinder Display



Use the buttons and switches shown in the following figure to switch the viewfinder display among the normal indications, basic menu pages and advanced menu pages.

Use the following procedure to display the advanced menu.

- ① Move the POWER switch to the ON position while holding down the UP/ON button to display the advanced menu selection screen.
- ② To display advanced menu page 2 immediately, move the cursor to the menu number and then press the DOWN/OFF button.


- ① Align the cursor to **ALL RESET** and press the UP/ON button.
(The indication changes to "ALL RESET SURE".)
- ② Press the UP/ON button again. (The indication changes to "ALL RESET OK" and reinitialization completes.)

To cancel the reinitialization, move the cursor instead of pressing the UP/ON button.



Viewfinder Normal Indications

During normal operation, the following items can be indicated in the viewfinder.



The significance of each of the indications shown in the figure is as follows.

1 VTR operation status indication

This indicates the VTR's current operation status (REC, PLAY, etc.).

2 TAKE/CUE indication

This displays a TAKE or CUE indicator when using the ClipLink function and recording with the DSR-1/1P.
TAKE: When recording in Mark mode, this indication appears when a Mark IN point is set and disappears when the next Mark OUT point is set.
CUE: When recording in Cue mode, this indication appears for about 1 second when a cue point is set.

3 Recording time or time data indication

This shows the following values.
• When the REC TIME switch on the camera is in the TTL position: The total recording time
• When the REC TIME switch on the camera is in the DUR position: The duration of the current recording cut

5 Clip mode indication

A "CLIP M" or "CLIP C" indication appears when you use the ClipLink function and record using the DSR-1/1P.

CLIP M: Indicates shooting in Mark mode
CLIP C: Indicates shooting in Cue mode

6 Clip remaining indication

The number of available index pictures remaining is displayed when you use the ClipLink function with the DSR-1/1P.

7 Status display area

One of the following values or messages is displayed to indicate the camera head's current status or its operation status.

- New values when changing camera head's settings
- Messages indicating progress or results of adjustments
- The camera head's current settings
- SetupLog data recorded to tape during shooting (see page 78)

Note

The status indication is not shown while the EZ FOCUS indication 8 appears.

8 EZ FOCUS indication

This appears when the EZ FOCUS button is pressed, enabling the "easy focus" function.

9 LOW LIGHT indication

This warning appears if the lighting level is inadequate.

10 Camera microphone output indication


This appears when there is an input from the camera microphone.

Note

This indication serves as a check on whether the camera microphone is operating correctly, but it does not provide confirmation that the VTR is recording sound. Check that the audio recording levels on the VTR are set correctly.

11 Audio recording level indicators

These show the recording levels of audio channels 1 and 2 on the VTR.



12 Tape remaining indication

This shows the tape remaining in the VTR as follows.

Indication	Tape remaining
F-30	At least 30 minutes
30-25	25 - 30 minutes
25-20	20 - 25 minutes
20-15	15 - 20 minutes
15-10	10 - 15 minutes
10-5	5 - 10 minutes
5-0	2 - 5 minutes
5-0 (flashing)	0 - 2 minutes

13 VTR warning indication

This shows warning indications about operation or status of the connected VTR.

When connecting the DSR-1/1P or PVV-3/3P

Indication	Meaning
NO TAPE	There is no tape loaded.
REC INHIBIT	The tape is in the recording inhibited state.
LOW BATT.	The battery is almost exhausted.
BATT. END	The battery is exhausted.
TAPE NEAR END	The tape is near the end.
TAPE END	The tape is at the end.
CHECK REMOTE (PVV-3/3P only)	A device other than a remote control unit (e.g. headphones) is connected to the REMOTE connector.
SERVO	The servo lock has been lost.
HUMID	There is condensation.
RF	The video heads are clogged, or there is some other fault in the recording system.
SLACK	The tape is not wound properly.
OXIDE TAPE (PVV-3/3P only)	An oxide tape has been loaded. (The tape is automatically ejected.)

Viewfinder Normal Indications

Only when connecting the DSR-1/1P

Indication	Meaning
50P CONNECT	Connection with the PRO 50-pin connector on the DSR-1/1P. (Freeze mix function is disabled.)
MP TAPE	An incorrect type of cassette has been loaded. (The cassette is automatically ejected and the indication disappears in about two seconds.)
CLIP DATA ERR	Abnormality of the cassette memory data.
AUDIO 48kHz?	At back space editing, audio recording mode has changed from 32 kHz mode (4-channel mode) to 48 kHz mode (2-channel mode).
AUDIO 32kHz?	At back space editing, audio recording mode has changed from 48 kHz mode (2-channel mode) to 32 kHz mode (4-channel mode).
ERROR:91-13F	Failure in loading or saving the cassette memory data. When other indication appears, refer to the operating instructions for the DSR-1/1P.
CLIP CONT?	Asking whether you will continue shooting in ClipLink mode or not when a cassette contains ClipLink data. (The indicator disappears when you press the ClipLink CONTINUE button on the DSR-1/1P or start the next shooting without pressing it.)
CLIP NEAR END	At back space editing in ClipLink mode, capacity for only 1 to 3 index pictures remains.
CLIP END	Impossible to record any more clip shots.

White balance indication

The following indications appear.

Indication	Meaning
EZ	Operating in EZ mode (The ATW function is selected.)
ATW	The ATW function is selected. (The ATW button was pressed and the indicator is lit.)
W/A	White balance memory A is selected.
W/B	White balance memory B is selected.
W/P	Preset white balance is selected.
W/M	Manual adjustment is performed remotely.

SKIN DTL indication

This appears when the skin detail function is activated (The SKIN DTL switch is set ON.)

EVS indication

This appears when the EVS (Enhanced Vertical definition System) function is enabled. (See page 84.)

Lens f-stop indication

This shows the f-stop of the lens.

Note

Depending on the lens being used, this indication may differ slightly from the actual f-stop on the lens.

Gain indication

This shows the gain value, and the settings of the HYPER GAIN switch and the DPR (Dual Pixel Readout) function (see page 64) as shown in the following table.

Example indication	Meaning
18dB	Gain setting is 18 dB.
DPR 18dB	The DPR function is enabled. In this case the DPR function approximately doubles the gain (an increase of 6 dB) over the current gain setting (in this case 18 dB).
HYPER	The HYPER GAIN switch is in the ON position. In this case the hyper gain function increases the gain by a factor of about 60 or 120 with respect to 0 dB regardless of the current gain setting (that is, increased to 36 or 42 dB).

Filter setting indication

This shows the setting of the FILTER control.

Indication	Filter setting
3200	1 (3200K)
56ND	2 (5600K + 1/2ND)
5600	3 (5600K)
56ND	4 (5600K + 1/2ND)

Clock indication

The clock indication is shown in one of the following ways (according to the CLOCK IND setting of CAM, BARS, or OFF in advanced menu page 8).

CAM: Always displayed.

BARS: Displayed whenever color bars are displayed.

OFF: Not displayed.

If the clock indication is displayed during recording, it is recorded onto the image.

Voltage/error indication

The current voltage is displayed whenever the camera head's power supply voltage dips below 11.0 V DC. However, you can also display the current voltage at any time by pressing and holding the MENU/STATUS switch in the upward position (the display is shown for as long as you hold the switch upward).

An error message is displayed when an abnormality has been detected by the auto diagnostic function (page 62).

If an error message appears, contact your Sony dealer.

If using a VTR and an Anton Bauer Intelligent Battery System

The remaining battery capacity is shown as a percentage.

Shutter setting indication

When the SHUTTER switch has been set to ON, the shutter speed, CLS frequency or EVS set in basic menu page 1 is displayed here.

Status Indications

If you set the MENU/STATUS switch to STATUS while a menu is being displayed, the camera head's current setting status will be shown in this display area.

WHITE	: 0 3200K
FILE	: STD
DCC+	: OFF
SS	: OFF
BATT	: 13.0V

a) When both the DCC+ and DYNALatitude functions are set to OFF

Display	Description
WHITE	White balance adjustment method selection (PRE/AB) and color temperature during auto white balance adjustment
A.IRIS	Iris adjustment method selection (STD/SPOT/LBACK L)
FILE	STD (when not using the setup files), or a selected file name (when using the setup files) (see page 71).
DCC+ or DL	For DCC+ Indication: ON with the OUTPUT/DL/DCC+ switch set to CAM/DCC+ (DCC+ ON), and OFF with the switch set to CAM/DL and DL in advanced menu page 2 (page 64) set to OFF (both DCC+ and DYNALatitude OFF). For DL Indication: When setting the OUTPUT/DL/DCC+ switch to DL and DL in advanced menu page 2 to OFF (DYNALatitude OFF), LOW, STD or HIGH is displayed according to DL LEV setting in basic menu page 2 (page 59).

Viewfinder Basic Menu

To display the basic menu pages, press the MENU/STATUS switch downward while the normal indications are being shown in the viewfinder. The basic menu configuration can include up to eight pages (the configuration depends on the switch settings and the type of connected VTR).

Basic Menu Operations

The common operations on all basic menu pages are described below.

To change the page or item

The cursor is moved downward each time you press the MENU/STATUS switch down. Once the cursor has reached the last item on a page, pressing down the MENU/STATUS switch to go to the next page. When the last page is being displayed, pressing down the MENU/STATUS switch returns the display to the normal indications.

The cursor is moved upward each time you press up the MENU/STATUS switch. Once the cursor has reached the first item on a page, pressing up the MENU/STATUS switch returns the display to the normal indications.

To change settings

After using the MENU/STATUS switch to move the cursor to the item on which you will change the setting, press either the UP/ON button or the DOWN/OFF button to select the desired value.

To reset any item to its shipped settings, press the UP/ON button and the DOWN/OFF button at the same time.

Contents and Settings of Each Page

Each page's contents and settings are described below. On the DXC-D35WSJ/D35WSPL, when the MENU/MODE is set to 2 in advanced menu page 9, a page for aspect ratio settings (16:9/4:3) is added before basic menu page 1.

Basic menu page 1

<p>→A. IRIS : ± 0 DTL LEU : ± 0 STRETCH : ± 0 SHUTTER : OFF</p>

Item	Settings
A. IRIS Sets a base value for auto adjustment of lens iris.	-1.0, -0.5, ±0 (normal value), +0.5, +1.0 Negative adjustment values set a narrower lens iris and positive values set a wider lens iris.
DTL LEU Sets the detail (edge) emphasis.	-99 to ±0 (normal value) to +99 Negative adjustment values soften the image's edges and positive values sharpen them.
M. BLACK Sets the master pedestal level.	-99 to ±0 (normal value) to +99 Negative adjustment values make dark areas of the picture darker and increase the contrast. Positive adjustment values make dark areas of the picture lighter and reduce the contrast.
STRETCH Sets black stretch/compress value.	-16 to ±0 (normal value) to +15 This function adjusts the intensity of dark areas of the screen. Negative values make these areas darker (black compress) and positive values make these areas brighter (black stretch).
SHUTTER Sets shutter speed or CLS/EVS setting (see page 84).	DXC-D35/D35WSL: 1/100 (normal value), 1/250, 1/500, 1/1000, 1/2000, EVS, CLS (60.4 Hz to 200.3 Hz) DXC-D35P/D35WSPL: 1/60 (normal value), 1/250, 1/500, 1/1000, 1/2000, EVS, CLS (60.3 Hz to 201.4 Hz) This selects either the shutter speed or the scan frequency or EVS for the clear scan function.

Basic menu page 2

<p>→SKIN DTL : 0.0 DL LEV : STD PRE-WHT : 3200</p>
--

Item	Settings
SKIN DTL Sets the amount of skin detail correction.	0.0 (normal value) to 1.0 Smaller values set a softer skin detail.
DL LEV Sets the DynaLatitude level.	LOW, STD (normal value), HIGH Set the amount of DynaLatitude effects as high level, standard level (STD), or low level.
PRE-WHT Sets the color temperature of the preset white balance.	When the FILTER control is set to 1 (3200K): 2200 to 3200 (normal value) to 4300 When the FILTER control is set to 2 (5600K + 1/4 ND), 3 (5600K) or 4 (5600K + 1/4 ND): 4600 to 5600 (normal value) to 12000

Basic menu page 3

This is displayed when the SET UP switch has been set to FILE.

<p>FILE : #FL →SELECT FILE HISAT DATE (YES/NO)</p>
--

For details of this operation, see "Setup Files" (page 71).

Basic menu page 4

This menu is displayed only when an external sync signal is input to the camera adaptor or VTR connected to the camera head.

<p>→SC PHASE : 000 H PHASE : 135</p>
--

Item	Settings
SC PHASE Sub carrier phase adjustment for when camera is genlocked.*	000 (normal value) to 999
H PHASE Horizontal phase adjustment for when camera is genlocked.*	000 to 135 (normal value) to 199

a) This applies when using an external sync signal to synchronize operation of several cameras (see page 39).

Basic menu page 5

<p>MARKER : ON →HOUR TIME : DATE : 00:00</p>
--




Viewfinder Basic Menu

Item	Settings
MARKER Sets MARKER display ON/OFF.	ON (normal value), OFF MARKER is displayed when the setting is ON and is not displayed when it is OFF. When the setting is ON, go to Advanced Menu 4 to select the type of marker (see page 65).
DUR TIME Sets the recording time before shooting helps you with making scenes of equal duration. When shooting with displaying the recording time of the current cut in the viewfinder (with the REC TIME switch set to DUR), the recording time indication flashes to remind you that the recording time has passed.	00:00 to 59:59 (minute to second) See "Setting the recording time in seconds" below.


Setting the recording time in seconds
Move the cursor to DUR TIME, then press the UP/ON button or DOWN/OFF button.

A value of seconds is displayed under "SS".



Basic menu page 6


The following display is shown when the DSR-1/IP is connected.




Item	Settings
MARK/CUE Selects MARK mode or CUE mode (page 46).	MARK (normal value), CUE See "Using the ClipLink Function"
CHG REEL NO Sets the cassette name/number	See "To set the cassette name/number" below.

To set the cassette name/number (when using DSR-1/IP)

- 1 Connect the DSR-1/IP and load a cassette.
- 2 Press the MENU/STATUS switch to move the cursor to CHG REEL NO, then press the UP/ON button.




The cursor (→) changes to the text entry arrow (↓) and the current cassette name/number is displayed. ("NO TAPE" is displayed if you neglected to load a cassette.)



- 3 Press the MENU/STATUS switch to move the text entry arrow.

Press the MENU/STATUS switch upward to move the cursor to the right or downward to move it to the left.
The character cycles through the following sequence.




- 4 Press the UP/ON button or DOWN/OFF button to enter the desired characters.

The displayed character changes each time the UP/ON button is pressed. It changes in reverse order each time the DOWN/OFF button is pressed.

- 5 Return to step 2 and repeat the text entry procedure.


- 6 After completing text entry, move the text entry cursor to the parenthesis position.

The display changes as follows.



- 7 Check your cassette name/number setting, and press the UP/ON button if no more changes are required. (To make changes or to abort the procedure for this setting, return to step 2.)

This writes the new cassette name/number to the cassette memory, after which the display changes as follows.




Basic menu pages 7 and 8

You can create a title of up to four lines, each of twelve alphanumeric or punctuation characters, and then save it. It is then possible to record the title over the picture while shooting.

Entering the title (page 7)


- 1 Press the MENU/STATUS switch as necessary to display basic menu page 7 (title setting display) in the viewfinder.



If a title is already present, it appears on this screen. To delete the displayed title, press the UP/ON and DOWN/OFF buttons simultaneously.

- 2 Press the UP/ON button.

This brings up the cursor on the screen (flashing), and switches to title editing mode.



- 3 Press the DOWN/OFF button to move the cursor to the position where you wish to insert a character.

To move the cursor back

With the DOWN/OFF button held down, press the UP/ON button.

(continued)

Viewfinder Basic Menu


- 4 Press the UP/ON button to select the required character.
Each time you press the UP/ON button, the character cycles through the following sequence.

RECIEFSH.KJLWNPQRSTUVMXYZ*0123456789<>-./□ (Space)
To reverse the character sequence
With the UP/ON button held down, press the DOWN/OFF button.

- 5 Press the DOWN/OFF button to confirm the character selection.
The cursor advances to the next character position.

To change a character after confirming it
Return to step 3, and input the character again.


- 6 Repeat steps 4 and 5 until the title is complete.




- 7 When the title is complete, press the MENU/STATUS switch as necessary to return to the normal viewfinder indications.
The title created is retained, even when you power the camera off.

To record a title (page 8)

- 1 Press the MENU/STATUS switch as necessary to access basic menu page 8 (title display).



Example: If an abnormality is detected in the DSP circuit.




The error message "DIAG ERROR" appears when the normal indications are displayed. If this message appears, contact your Sony dealer.

Note on using the CCU-M5MSP Camera Control Unit
When the CCU-M5MSP has a function switch setting of "TITLE ON", the title display takes precedence, and the status display (see page 57) do not appear in the normal indications. However, when you press the MENU/STATUS switch up, for as long as you hold it up the status indications appear in place of the title.

When "CHECK DIAG" is displayed

The "CHECK DIAG" indication appears in the status display area whenever the camcorder's automatic self diagnostic function detects an abnormality. Access this page and perform error checking. (This page is displayed as basic menu page 1.)
"CHECK DIAG" will also be displayed if there is a problem on the sync signal input to the GEN LOCK IN connector. Input a proper sync signal and then perform error checking.



To perform error checking

Press the UP/ON button.

The error checking performs on the digital signal processing (DSP) and memory circuits and the results are displayed.
When no error is detected, "OK" appears.



Viewfinder Advanced Menu

Bring up the advanced menu pages by setting the POWER switch to ON while pressing the UP/ON button up (see page 52).

There are up to 15 advanced menu pages (the number displayed depends on the switch settings and the type of connected VTR).

Note on EZ mode

When the camera is in EZ mode, the advanced menu does not appear. Release the EZ mode beforehand. (See page 14.)

Advanced Menu Operations

To change the page

Move the cursor to the menu number, then press the UP/ON button or the DOWN/OFF button.

Pressing the UP/ON button displays the previous page and pressing the DOWN/OFF button displays the next page. Pressing the DOWN/OFF button when the last page is being displayed returns the display to the first page.

To select items in a page

Press the MENU/STATUS switch to move the cursor among the menu items.

To change settings

This operation is the same as for the basic menus.

For a description of basic menu operations, see page 58.

To return to the normal indications

Move the cursor to EXIT MENU, then press the UP/ON button.

Contents and Settings of Each Page

Each page's contents and settings are described below.

Advanced menu page 1

Use this page to return all advanced menu settings to their factory preset values.

For details of this operation, see "Displaying the advanced menu and switching to the normal indications" (page 52).

<p>→PAGE 1 (NEXT→ PREVIOUS←)</p> <p>ALL RESET (YES→)</p> <p>EXIT MENU (YES→)</p>
--

Advanced menu page 2

<p>→PAGE 2 (NEXT→ PREVIOUS←)</p> <p>SEL : ON</p> <p>SEL : OFF</p> <p>EXIT MENU (YES→)</p>

Advanced menu page 3

<p>→PAGE 3 (NEXT→ PREVIOUS←)</p> <p>AUD MEN : 2</p> <p>TONE : OFF</p> <p>BARS : SHITE</p> <p>REMO1 : MARK</p> <p>REMO2 : MARK</p> <p>BAUD RATE : 38400</p> <p>EXIT MENU (YES→)</p>
--

a) For DXC-D35P/D35WSPL/EBU75

Item	Settings
AUD MEN Selects whether or not to make the FILTER knob settings (1 to 4) correspond to separate white balance adjustment values stored in memory.	2 (normal value): No correspondence with FILTER knob settings. Only two adjustment values (A and B) are stored in memory. 2 x 4 FL: Correspondence with FILTER knob settings. Each of the four knob settings can be used to set A and B adjustment values, for a total of eight settings.
TONE Selects whether or not to output a 1-kHz audio signal with the color bars when the OUTPUT/DJ/DOCC has been set to BARS.	ON (normal value): Output audio signal. OFF: Do not output audio signal.
BARS Selects normal width or narrower width for color bars.	SHITE (normal value for DXC-D35/D35WSPL): Normal width. EBU75 (normal value for DXC-D35P/D35WSPL): EBU 75% EBU100 (for DXC-D35P/D35WSPL): EBU 100% SPLIT (for DXC-D35P/D35WSPL): Not for normal operation SNG: Narrower than normal (used for satellite communications, etc.)
REMO1 Sets a function for position 1 of a switch connected to the REMOTE1 connector.	REC (normal value): Specifies recording start/stop. MARK: Specifies a Mark IN/OUT point. CUE: Specifies a cue point. NG: Specifies NG/OK.
REMO2 Sets a function for position 2 of a switch connected to the REMOTE1 connector.	REC: Specifies recording start/stop. MARK (normal value): Specifies a Mark IN/OUT point. CUE: Specifies a cue point. NG: Specifies NG/OK.
BAUD RATE Sets a baud rate for a computer connected to the REMOTE connector 2 (to be supported in future version).	9600, 38400 (normal value)

Advanced menu page 4

<p>→PAGE 4 (NEXT→ PREVIOUS←)</p> <p>MARKER : OFF</p> <p>LIMITS : ZEBRA</p> <p>VF S DTL : 70 IRE</p> <p>VF S DTL : 90 IRE</p> <p>VF S DTL : 99 IRE</p> <p>EXIT MENU (YES→)</p>

a) For DXC-D35P/D35WSPL/70%.

Item	Settings
MARKER Selects ON/OFF setting for center marker, size setting (center marker, zebra, zebra area), and display ON/OFF setting.	CENT90% (normal value): Displays center marker and safety zone marker at 90% size. CENT80%: Displays center marker and safety zone marker at 80% size. 90%: Displays only safety zone marker at 90% size. 80%: Displays only safety zone marker at 80% size. CENT: Displays only center marker.
LIMITS (For DXC-D35WSPL) Selects the safety zone size when the scan size is 16:9.	OFF (normal value): Depends on the scan size. 4:3, 13:9, 14:9, 16:9
ZEBRA Selects type of zebra pattern display.	1 (normal value): Displays the zebra pattern over parts having a video level between 70 and 90 IRE (or 70 and 90%). Use the next item (ZEBRA1) to select the base level. 2: Displays the zebra pattern over parts having video levels of 100 IRE or above (or 100% or above). 1/2: Dual display (both 1 and 2).
ZEBRA1 Sets base level for zebra pattern 1.	70 IRE (normal value) to 90 IRE or 70% (normal value) to 90%: Can be set for each IRE step or 1% step.
VF S DTL Sets the detail level of images on the viewfinder screen (displayed only when a viewfinder other than the DXF-701/70ICE/701WS/701WSE/801/801CE is attached).	-99 to +99 (normal value) to +99: Negative values set softer edges and positive values set sharper edges.

(continued)

Viewfinder Advanced Menu

Item	Settings
VF TALLY Selects whether or not to use more than one RECTALLY indicator, (displayed only when the DXF-701/701CE/701WS/701WSP/701WSPCE/701WSPCE/701WSPCE is attached).	x1: Uses only the upper RECTALLY indicator. x2 (normal value): Uses two RECTALLY indicators.
VF PLAY Selects the video signal displayed in the viewfinder during playback of the DSR-1/1P (displayed only when the DSR-1/1P is connected).	Y (normal value): Y signal VBS: Composite video signal
LENS SEL Selects the types of the lens. F-number is set to the lens on page 90.	1 (normal value), 2, 3, 4 F-number is set to the lens on page 90.

Advanced menu page 5

→PAGE 5(NEXT→) PREVIOUS←
SS IND: ALWAYS
MIC IND: ON
IRIS IND: ON
TAPE IND: ON
TC IND: ON
WHITE IND: ON
SKIN IND: ON
EXIT MENU (YES→)A



Item	Settings
SS IND^a Selects the mode for showing the shutter setting when displaying the normal indications.	3SEC: Displays shutter setting for three seconds only when the setting has been changed. ALWAYS (normal value): Displays the shutter setting at all times.
LL IND^a Selects whether or not to show the LOW LIGHT indication on the normal indications when inadequate lighting is detected.	ON (normal value): Displays. OFF: Not display.
MIC IND^a Selects whether or not to show the camera microphone output indication on the normal indications.	ON (normal value): Displays. OFF: Not display.
IRIS IND^a Selects whether or not to show the lens's F-stop value (iris indication) on the normal indications. The F-stop value is always displayed when in EZ mode.	ON (normal value): Displays. OFF: Not display.

Item	Settings
TC IND^a Selects whether or not to show the time data indication on the normal indications (valid only when the DSR-1/1P or PVV-323P is connected).	ON (normal value): Displays. OFF: Not display.
ID IND Selects whether or not to display the camera ID when displaying color bars.	ON (normal value): Displays. OFF: Not display.
ID SET Sets the camera ID (up to eight characters, including alphanumerics, symbols, and spaces).	See "To set the camera ID" below.

a) When the viewfinder's DISPLAY switch is set to OFF, indications related to these items are not displayed even when menu settings are set to ON.

To set the camera ID

1 Press the MENU/STATUS switch to move the cursor to ID SET.

The cursor (→) changes to the text entry arrow (↓).

→PAGE 6(NEXT→) PREVIOUS←
AUDIO IND: ON
TAPE IND: ON
TC IND: ON
ID IND: OFF
ID SET: ↓
EXIT MENU (YES→)A

2 Press the MENU/STATUS switch to move the text entry arrow.

Press the MENU/STATUS switch upward to move the cursor to the right or downward to move it to the left.

3 Press the UP/ON button or DOWN/OFF button to enter the desired characters.

The displayed character changes each time the UP/OFF button is pressed. It changes in reverse order each time the DOWN/OFF button is pressed.

4 Return to step 2 and repeat the text entry procedure.

5 When you have finished entering the text, move the cursor to the parenthesis position.

This clears the displayed menu and returns to the normal indications.

Advanced menu page 7

→PAGE 7(NEXT→) PREVIOUS←
EZ MODE : CUSTOM ^a
A. IRIS-AE : F2.8
A. IRIS-AE : F5.6
AE LIMIT : 1dB
EXIT MENU (YES→)A

a) At shipping, the EZ MODE is set to STD.

Item	Settings
EZ MODE When the EZ MODE button is pressed, the EZ MODE is set to STD or CUSTOM. Changes only not to change the settings of other settings to standard settings. (The EZ mode function cannot be used during remote operation.)	STD (normal value): Changes settings to standard settings. CUSTOM: Changes only not to change the settings of other settings to standard settings. (The EZ mode function cannot be used during remote operation.)
A. IRIS-AE Selects auto iris adjustment which sets an F-stop value that can be switched to AGC (displayed only when the EZ MODE is set to CUSTOM).	F1.8, F2.8 (normal value), F4, F5.6
A. IRIS-AE Selects auto iris adjustment which sets an F-stop value that can be switched to AE (displayed only when the EZ MODE is set to CUSTOM).	F5.6, F8, F11, F16 (normal value)
AGC LIMIT Sets an upper limit value for AGC adjustment (displayed only when the EZ MODE is set to CUSTOM).	0 dB, 3 dB, 6 dB, 9 dB, 12 dB (normal value)



Viewfinder Advanced Menu

EZ mode settings

The following settings are set for the camera head when EZ mode has been selected.

Item	Setting	CUSTOM
Setup file	STD	Selectable
Detail level	STD	Selectable
Master black	±0	Selectable
Black stretch	±0	Selectable
Skin detail	OFF	OFF
Shutter	OFF (AE mode)	OFF (AE mode)
Freeze mix	OFF	OFF
Gain	AGC mode	AGC mode
Hyper gain	OFF	OFF
iris control method	Automatic	Automatic
Auto iris control mode	STD	STD
Iris override	±0	Selectable
Color bar output	Not output	Not output
AGC upper limit	12dB	Selectable
AGC's F stop value	F2.8	Selectable
AE's F stop value	F16	Selectable
ATW	ON	ON
DynaLatitide	OFF	OFF
DCC+	ON	ON
F-stop value indication	ON	ON
Filter indication	ON	ON
Clock indication	OFF	OFF

→PAGE 8 (NEXT→ PREVIOUS) CLOCK IND: OFF CLOCK SET: (START→) YY MM DD 00 00 00 EXIT MENU (YES→)

Advanced menu page 8



→PAGE 9 (NEXT→ PREVIOUS) 16:9/4:3 : 16:9 WIDE ID : ON SCENE : AUTO MENU MODE : 1 EXIT MENU (YES→)
--

Advanced menu page 9

Item	Setting
CLOCK IND	OFF (normal value): Not display. CAM: Displays color bars only when normal indications.
CLOCK SET	See "Setting the Clock and Sets date/time." See "Stamping Recordings" (page 86).

Item	Setting
16:9/4:3	16:9 (normal value) Selects whether to put the camera in 16:9 mode or 4:3 mode.
WIDE ID	ON (normal value): Adds signal to video output to add a wide aspect ID signals in 16:9 mode.
VF SCAN	AUTO (normal value): Automatically switch to 16:9 size when the camera is in 16:9 mode, and automatically switch to 4:3 size when the camera is in 4:3 mode. FULL: Regardless of camera's mode (16:9 or 4:3), the viewfinder picture completely fills the display area.
MENU MODE	1 (normal value): Selects the 16:9 or 4:3 mode only with the advanced menu. 2: Selects the 16:9 or 4:3 mode with both the basic and advanced menus.

- a) Compared to 16:9 mode, the 4:3 mode video appears as if a zoom lens has been adjusted slightly toward the telephoto end (see figure on page 70).
- b) When the camera is in 16:9 mode, the viewfinder picture appears stretched vertically (see figure on page 70).

Advanced menu pages 10 to 13

These pages are displayed only when the SET UP switch has been set to FILE.

For details of this operation, see "Setup Files" (page 71).

Advanced menu pages 14 and 15


These pages are displayed only when a DSR-1/P has been connected and the SET UP switch is set to FILE.

For details of this operation, see "Using SetupNav and SetupLog with the DSR-1/P" (page 76).



Video Output and Viewfinder Picture (For DXC-D35WSL/D35WSP/L)

The video output and viewfinder picture of this camera vary as shown below according to the settings of the 16:9/4:3 item and the VF SCAN item of the advanced menu page 9.




Setup Files

You can use setup files to reproduce a particular configuration of settings. You can also revise the contents of setup files. There are eight types of setup files, of which five are factory preset setup files and the other three are user files.

Calling up a Setup File


This describes how to call up a setup file and use it to replace the current menu settings.

- 1 Set the SET UP switch to FILE.



The camera head is set according to the currently-selected file data.

- 2 Access basic menu page 3.



a) An asterisk (*) appears in front of any factory preset file whose contents have been revised at least once.

- 3 Move the cursor to SELECT FILE and use the UP/ON button or the DOWN/OFF button to select the desired file.


Press the UP/ON button or DOWN/OFF button repeatedly until the desired file name is displayed.



File	Description
STD	Settings for shooting under standard conditions
HI SAT	Settings for making pictures vivid
FL	Settings for shooting under fluorescent lighting
FILM LIKE	Settings for making pictures like ones shot by film camera
SVHS/VHS	Settings to optimize camera image for recording and playback characteristics of S-VHS, VHS, or Hi-8 tape
USER1 to USER3	User setup files (set to STD at shipping)

- 4 Move the cursor to CHG FILE and press the UP/ON button.

The display changes as shown below and the selected file is called up.



You can also call up these files via a similar operation in advanced menu page 10. In this page, a file recorded onto a tape can also be called up (when using the DSR-1/1P).

For details, see "To call up files recorded onto a tape (when using the DSR-1/1P)" (page 72).

Setup Files

To call up files recorded onto a tape (when using the DSR-1/1P)

First, connect the DSR-1/1P to the camera head and load the cassette that contains the recorded files.

1 Set the SET UP switch to FILE.

2 Access advanced menu page 10.

→PAGE 10 (NEXT→ PREV←)
FILE RECALL
FILE: #FL
SELECT FILE
CHG FILE
(YES→)
EXIT MENU (YES→)

3 Move the cursor to SELECT FILE and use the UP/ON button or the DOWN/OFF button to select TAPE.

→PAGE 10 (NEXT→ PREV←)
FILE RECALL
FILE: #FL
SELECT FILE
CHG FILE
(YES→)
EXIT MENU (YES→)

4 Move the cursor to CHG FILE and press the UP/ON button.

The screen appears as shown below.

→PAGE 10 (NEXT→ PREV←)
FILE RECALL
FILE: #FL
SELECT FILE
READY TAPE?
(YES→)
EXIT MENU (YES→)

5 Press the UP/ON button to call up the file. To abort the call up operation, press the DOWN/OFF button (the display returns to the one shown in step 3).

During the call up operation, the following display appears.

→PAGE 10 (NEXT→ PREV←)
FILE RECALL
FILE: #FL
SELECT FILE
TAPE
SETUP FILE
EXIT MENU (YES→)

When the call up operation ends, the display changes as shown below.

→PAGE 10 (NEXT→ PREV←)
FILE RECALL
FILE: #FL
SELECT FILE
TAPE
DONE
Name of file
recorded onto
tape

The settings of the camera head are now replaced by the settings in the called file.

Changing File Settings

When using advanced menu page 11 or 12, you can change the settings about picture quality in setup files. (In basic menu page 1, a part of items are changeable.) The changes are accepted only until another file is called up, after which the original settings are restored. If you save the changes, store the modified file as one of the user files or record it in a cassette. (See the following section "Saving File Settings".)

1 Perform the steps described in "To call up files recorded onto a tape (when using the DSR-1/1P)" above to call up the selected file.

2 Access advanced menu page 11 or 12.

→PAGE 11 (NEXT→ PREV←)
FILE ADJ. 1
FILE: #FL
STRETCH : ± 0
M. GAMMA : ± 0
DTL LEV : ± 0
DTL FREQ : ± M
EXIT MENU (YES→)

→PAGE 12 (NEXT→ PREV←)
FILE ADJ. 2
FILE: #FL
HUE : ± 20
SKIN SAT: 12
SKIN HUE: 15
EXIT MENU (YES→)

a) An asterisk (*) appears in front of any factory preset file whose contents have been revised at least once.

3 Make the desired changes.

Page 11

Item	Settings
M. BLACK, STRETCH and DTL LEV	See "Basic menu page 1" (page 58).
M. GAMMA	-99 to ±0 (normal value) to +99
V DTL LEV	-99 to ±0 (normal value) to +99
DTL FREQ	L, L, M (normal value), H, HH

Page 12


Item	Settings
SAT	-99 to ±0 (normal value) to +99 Adjusts the saturation of the image. Negative adjustment values decrease the saturation and positive adjustment values increase the saturation.
HUE	-99 to ±0 (normal value) to +99 Adjusts the hue of the image.
SKIN SAT	-99 to ±0 (normal value) to +99 Adjusts the saturation in the specified area of the image. Negative adjustment values decrease the saturation and positive adjustment values increase the saturation.
SKIN HUE	-99 to ±0 (normal value) to +99 Adjusts the hue in the specified area of the image.

Saving File Settings

Files whose settings have been changed for certain shooting conditions can be saved as a user file or onto a tape (when using the DSR-1/1P).

For details, see "To save setup files to a tape (when using the DSR-1/1P)" (page 74).

1 Set the SET UP switch to FILE.




2 Call up a setup file whose settings approximate the desired shooting conditions and then change some of the settings.

For details of this operation, see "Calling up a Setup File" (page 71), "Changing File Settings" (in the left column on this page), "Basic Menu Operations" (page 58), and "Advanced Menu Operations" (page 64).

(continued)


Setup Files

- 3 Access advanced menu page 13.




a) An asterisk (*) appears in front of any factory preset file whose contents have been revised at least once.

- 4 Move the cursor to DESTINATION FILE and repeatedly press the UP/ON button or the DOWN/OFF button to select USER1, USER2, or USER3.




- 5 Press the UP/ON button to move the cursor to STORE FILE?

The display changes as shown below.



- 6 Press the UP/ON button to store the file. To abort the save operation, press the DOWN/OFF button (the display returns to the one shown at step 4).


When the save operation is finished, the display changes as shown below.



To save setup files to a tape (when using the DSR-1/P)


Connect the DSR-1/P to the camera head and load the tape onto which the file will be recorded.

- 1 Perform steps 1 to 4 of "Saving File Settings" and select TAPE as the file saving destination.



- 2 Press the UP/ON button to move the cursor to STORE FILE?


The display changes as shown below.




- 3 Press the UP/ON button to store the file. To abort the save operation, press the DOWN/OFF button (the screen returns to the screen shown in step 2).

The tape automatically rewinds and recording starts.

The display changes as shown below, which includes color bars. "CAN NOT WRITE" appears on the screen if no tape is loaded or if the loaded tape is write-protected.)



After the settings are stored, the following display appears.



Using SetupNavi and SetupLog with the DSR-1/P

The SetupNavi function records the setup menu and setup files onto a tape, so that the same settings can be called up and used again or copied to another camera. The SetupLog function records a camera settings every few seconds at shooting and displays the recorded data in the viewfinder during playback.

Note on using an RM-M7G Remote Control Unit

When an RM-M7G is connected to the camera head, you cannot use the SetupNavi function. To make it possible to use the function, power OFF the camera head after disconnecting the RM-M7G, then power ON the camera head again.

Setting up the Camera Using Data Recorded on Tape

The procedure to replace camera's menu settings with settings recorded onto video tape is described here.

- 1 Connect the DSR-1/P and insert the cassette onto which the data was recorded. Set the SETUP switch to FILE, then set the POWER switch to ON while holding down the UP/ON button.

Advanced menu page 1 appears.

PAGE 1 (NEXT) PREVIOUS ALL RESET (YES)
EXIT MENU (YES)

- 2 Repeatedly press down on the MENU/STATUS switch until advanced menu 14 appears.

For details of menu operation, see "Advanced Menu Operations" (page 64).

PAGE 14 (NEXT) PREVIOUS SETUP NAVI TAPE-CAMERA RECALL DATA (YES)
EXIT MENU (YES)

"NO TAPE" is displayed if you neglected to load a cassette.

- 3 Press the UP/ON button to call up the data recorded on the tape. (Press the DOWN/OFF button to cancel).

The display changes as follows and the call up operation begins.

PAGE 14 (NEXT) PREVIOUS SETUP NAVI TAPE-CAMERA CANCEL TO RECALL? (YES)	NAME OF DATA BEING CALLED UP (MY FILE)
EXIT MENU (YES)	

To abort the call up operation while in progress Press the DOWN/OFF button.

The following display appears.

PAGE 14 (NEXT) PREVIOUS SETUP NAVI TAPE-CAMERA SURE TO RECALL? (YES)
EXIT MENU (YES)

- 4 Press the UP/ON button.

After the data has been read, the following display appears.

PAGE 14 (NEXT) PREVIOUS SETUP NAVI TAPE-CAMERA DONE
EXIT MENU (YES)

The previous menu settings are overwritten by the data recorded on the tape.

- 5 Change the menu settings if necessary.

Recording the Menu Settings onto a Tape

- 1 Connect the DSR-1/P and load the tape onto which the settings are to be recorded. Turn the camera power on.

- 2 Make your basic menu settings.

For details of this operation, see "Basic Menu Operations" (page 38).

- 3 Again, set the POWER switch to ON while holding down the UP/ON button.

- 4 Make your advanced menu settings.

For details of this operation, see "Advanced Menu Operations" (page 64).

- 5 Access advanced menu page 15.

PAGE 15 (NEXT) PREVIOUS SETUP NAVI CAMERA-TAPE STORE DATA (YES)
EXIT MENU (YES)

"NO TAPE" appears if you neglected to load a cassette.

- 6 Press the UP/ON button.

The following display appears.

PAGE 15 (NEXT) PREVIOUS SETUP NAVI CAMERA-TAPE SURE TO STORE? (YES)	NAME SET ()
EXIT MENU (YES)	

- 7 Set the cursor to "NAME SET" and press the UP/ON button to record the menu setting onto the tape. (Press the MENU/STATUS switch to cancel.)

The cursor (→) changes to the text entry cursor (↓).

PAGE 15 (NEXT) PREVIOUS SETUP NAVI CAMERA-TAPE SURE TO STORE? (YES)	NAME SET ↓
EXIT MENU (YES)	

- 8 Enter a name for the data.

Moving the text entry cursor: Press the MENU/STATUS switch up to move the cursor to the right, and press the MENU/STATUS switch down to move the cursor to the left.

Selecting the character: Press the UP/ON or DOWN/OFF button repeatedly until the desired character appears.

- 9 After completing text entry, move the cursor to the parenthesis position.

The display changes as follows.

PAGE 15 (NEXT) PREVIOUS SETUP NAVI CAMERA-TAPE SURE TO STORE? (YES)	NAME SET ()
EXIT MENU (YES)	

- 10 Move the cursor to "SURE TO STORE?" and press the UP/ON button to record the menu settings onto the tape (press the MENU/STATUS switch to cancel).

The display changes as follows and the data recording begins.

PAGE 15 (NEXT) PREVIOUS SETUP NAVI CAMERA-TAPE CANCEL TO STORE? (YES)	NAME OF DATA BEING RECORDED (MY FILE)
EXIT MENU (YES)	

After the data has been recorded, the following display appears.

```

PLAY      TCR 12:34:56:00
          W/A
          556 008 3200
          SETUP LOG 2/3
          Q1 R1 S1 : + + 0
          Q2 R2 S2 : + + 0
          Q3 R3 S3 : + + 0
          Q4 R4 S4 : + + 0
          Q5 R5 S5 : + + 0
          Q6 R6 S6 : + + 0
          Q7 R7 S7 : + + 0
          Q8 R8 S8 : + + 0
          Q9 R9 S9 : + + 0
          Q10 R10 S10 : + + 0
          Q11 R11 S11 : + + 0
          Q12 R12 S12 : + + 0
          Q13 R13 S13 : + + 0
          Q14 R14 S14 : + + 0
          Q15 R15 S15 : + + 0
          Q16 R16 S16 : + + 0
          Q17 R17 S17 : + + 0
          Q18 R18 S18 : + + 0
          Q19 R19 S19 : + + 0
          Q20 R20 S20 : + + 0
          Q21 R21 S21 : + + 0
          Q22 R22 S22 : + + 0
          Q23 R23 S23 : + + 0
          Q24 R24 S24 : + + 0
          Q25 R25 S25 : + + 0
          Q26 R26 S26 : + + 0
          Q27 R27 S27 : + + 0
          Q28 R28 S28 : + + 0
          Q29 R29 S29 : + + 0
          Q30 R30 S30 : + + 0
          Q31 R31 S31 : + + 0
          Q32 R32 S32 : + + 0
          Q33 R33 S33 : + + 0
          Q34 R34 S34 : + + 0
          Q35 R35 S35 : + + 0
          Q36 R36 S36 : + + 0
          Q37 R37 S37 : + + 0
          Q38 R38 S38 : + + 0
          Q39 R39 S39 : + + 0
          Q40 R40 S40 : + + 0
          Q41 R41 S41 : + + 0
          Q42 R42 S42 : + + 0
          Q43 R43 S43 : + + 0
          Q44 R44 S44 : + + 0
          Q45 R45 S45 : + + 0
          Q46 R46 S46 : + + 0
          Q47 R47 S47 : + + 0
          Q48 R48 S48 : + + 0
          Q49 R49 S49 : + + 0
          Q50 R50 S50 : + + 0
          Q51 R51 S51 : + + 0
          Q52 R52 S52 : + + 0
          Q53 R53 S53 : + + 0
          Q54 R54 S54 : + + 0
          Q55 R55 S55 : + + 0
          Q56 R56 S56 : + + 0
          Q57 R57 S57 : + + 0
          Q58 R58 S58 : + + 0
          Q59 R59 S59 : + + 0
          Q60 R60 S60 : + + 0
          Q61 R61 S61 : + + 0
          Q62 R62 S62 : + + 0
          Q63 R63 S63 : + + 0
          Q64 R64 S64 : + + 0
          Q65 R65 S65 : + + 0
          Q66 R66 S66 : + + 0
          Q67 R67 S67 : + + 0
          Q68 R68 S68 : + + 0
          Q69 R69 S69 : + + 0
          Q70 R70 S70 : + + 0
          Q71 R71 S71 : + + 0
          Q72 R72 S72 : + + 0
          Q73 R73 S73 : + + 0
          Q74 R74 S74 : + + 0
          Q75 R75 S75 : + + 0
          Q76 R76 S76 : + + 0
          Q77 R77 S77 : + + 0
          Q78 R78 S78 : + + 0
          Q79 R79 S79 : + + 0
          Q80 R80 S80 : + + 0
          Q81 R81 S81 : + + 0
          Q82 R82 S82 : + + 0
          Q83 R83 S83 : + + 0
          Q84 R84 S84 : + + 0
          Q85 R85 S85 : + + 0
          Q86 R86 S86 : + + 0
          Q87 R87 S87 : + + 0
          Q88 R88 S88 : + + 0
          Q89 R89 S89 : + + 0
          Q90 R90 S90 : + + 0
          Q91 R91 S91 : + + 0
          Q92 R92 S92 : + + 0
          Q93 R93 S93 : + + 0
          Q94 R94 S94 : + + 0
          Q95 R95 S95 : + + 0
          Q96 R96 S96 : + + 0
          Q97 R97 S97 : + + 0
          Q98 R98 S98 : + + 0
          Q99 R99 S99 : + + 0
          Q100 R100 S100 : + + 0
          Q101 R101 S101 : + + 0
          Q102 R102 S102 : + + 0
          Q103 R103 S103 : + + 0
          Q104 R104 S104 : + + 0
          Q105 R105 S105 : + + 0
          Q106 R106 S106 : + + 0
          Q107 R107 S107 : + + 0
          Q108 R108 S108 : + + 0
          Q109 R109 S109 : + + 0
          Q110 R110 S110 : + + 0
          Q111 R111 S111 : + + 0
          Q112 R112 S112 : + + 0
          Q113 R113 S113 : + + 0
          Q114 R114 S114 : + + 0
          Q115 R115 S115 : + + 0
          Q116 R116 S116 : + + 0
          Q117 R117 S117 : + + 0
          Q118 R118 S118 : + + 0
          Q119 R119 S119 : + + 0
          Q120 R120 S120 : + + 0
          Q121 R121 S121 : + + 0
          Q122 R122 S122 : + + 0
          Q123 R123 S123 : + + 0
          Q124 R124 S124 : + + 0
          Q125 R125 S125 : + + 0
          Q126 R126 S126 : + + 0
          Q127 R127 S127 : + + 0
          Q128 R128 S128 : + + 0
          Q129 R129 S129 : + + 0
          Q130 R130 S130 : + + 0
          Q131 R131 S131 : + + 0
          Q132 R132 S132 : + + 0
          Q133 R133 S133 : + + 0
          Q134 R134 S134 : + + 0
          Q135 R135 S135 : + + 0
          Q136 R136 S136 : + + 0
          Q137 R137 S137 : + + 0
          Q138 R138 S138 : + + 0
          Q139 R139 S139 : + + 0
          Q140 R140 S140 : + + 0
          Q141 R141 S141 : + + 0
          Q142 R142 S142 : + + 0
          Q143 R143 S143 : + + 0
          Q144 R144 S144 : + + 0
          Q145 R145 S145 : + + 0
          Q146 R146 S146 : + + 0
          Q147 R147 S147 : + + 0
          Q148 R148 S148 : + + 0
          Q149 R149 S149 : + + 0
          Q150 R150 S150 : + + 0
          Q151 R151 S151 : + + 0
          Q152 R152 S152 : + + 0
          Q153 R153 S153 : + + 0
          Q154 R154 S154 : + + 0
          Q155 R155 S155 : + + 0
          Q156 R156 S156 : + + 0
          Q157 R157 S157 : + + 0
          Q158 R158 S158 : + + 0
          Q159 R159 S159 : + + 0
          Q160 R160 S160 : + + 0
          Q161 R161 S161 : + + 0
          Q162 R162 S162 : + + 0
          Q163 R163 S163 : + + 0
          Q164 R164 S164 : + + 0
          Q165 R165 S165 : + + 0
          Q166 R166 S166 : + + 0
          Q167 R167 S167 : + + 0
          Q168 R168 S168 : + + 0
          Q169 R169 S169 : + + 0
          Q170 R170 S170 : + + 0
          Q171 R171 S171 : + + 0
          Q172 R172 S172 : + + 0
          Q173 R173 S173 : + + 0
          Q174 R174 S174 : + + 0
          Q175 R175 S175 : + + 0
          Q176 R176 S176 : + + 0
          Q177 R177 S177 : + + 0
          Q178 R178 S178 : + + 0
          Q179 R179 S179 : + + 0
          Q180 R180 S180 : + + 0
          Q181 R181 S181 : + + 0
          Q182 R182 S182 : + + 0
          Q183 R183 S183 : + + 0
          Q184 R184 S184 : + + 0
          Q185 R185 S185 : + + 0
          Q186 R186 S186 : + + 0
          Q187 R187 S187 : + + 0
          Q188 R188 S188 : + + 0
          Q189 R189 S189 : + + 0
          Q190 R190 S190 : + + 0
          Q191 R191 S191 : + + 0
          Q192 R192 S192 : + + 0
          Q193 R193 S193 : + + 0
          Q194 R194 S194 : + + 0
          Q195 R195 S195 : + + 0
          Q196 R196 S196 : + + 0
          Q197 R197 S197 : + + 0
          Q198 R198 S198 : + + 0
          Q199 R199 S199 : + + 0
          Q200 R200 S200 : + + 0
          Q201 R201 S201 : + + 0
          Q202 R202 S202 : + + 0
          Q203 R203 S203 : + + 0
          Q204 R204 S204 : + + 0
          Q205 R205 S205 : + + 0
          Q206 R206 S206 : + + 0
          Q207 R207 S207 : + + 0
          Q208 R208 S208 : + + 0
          Q209 R209 S209 : + + 0
          Q210 R210 S210 : + + 0
          Q211 R211 S211 : + + 0
          Q212 R212 S212 : + + 0
          Q213 R213 S213 : + + 0
          Q214 R214 S214 : + + 0
          Q215 R215 S215 : + + 0
          Q216 R216 S216 : + + 0
          Q217 R217 S217 : + + 0
          Q218 R218 S218 : + + 0
          Q219 R219 S219 : + + 0
          Q220 R220 S220 : + + 0
          Q221 R221 S221 : + + 0
          Q222 R222 S222 : + + 0
          Q223 R223 S223 : + + 0
          Q224 R224 S224 : + + 0
          Q225 R225 S225 : + + 0
          Q226 R226 S226 : + + 0
          Q227 R227 S227 : + + 0
          Q228 R228 S228 : + + 0
          Q229 R229 S229 : + + 0
          Q230 R230 S230 : + + 0
          Q2
```

```

PLAY      TCR  12:34:56:00


SETUP LOG 3/3
V. GAMMA 0 0
U. DTL LEV 1 1
DTL FREQ 0 0
SKIN SAT 0 0
SKIN HUE 0 0
SAT 0 0
HUE 0 0
RECEIVED

```

1 Connect the DSR-1/IP and load the tape that contains the recording to be viewed. Turn the camera power on.

- 2** Play back the tape.
For details of playback operation, see the operating instructions for the DSR-1/1P.
- 3** Press the MENU/STATUS switch up to the STATUS side.

The display changes to page 1 of the status display.



Each time you press upward the MENU/STATUS switch, the status display cycles through the status pages and play/back display in the order: page 2, page 3, the playback display (containing the current settings), and page 1.

Adjustments and Settings

Adjusting the white balance ensures that as lighting conditions change white objects remain white in the image and tones remain natural.


The color of light emitted varies from one light source to another, and as the lighting changes the apparent color of an illuminated subject changes. It is therefore necessary to adjust the white balance each time the principal lighting source changes.

You can save two white balance values in separate memories, A and B. Unless changed, the saved values are retained for approximately ten years, even when the camera is powered off.

Once a value is saved, you can automatically restore the adjustment by moving the W. BAL. switch to the A or B position. This makes shooting under alternating lighting conditions easy.

Separate white balance values for each FILTER control setting

In the default case, as described above, the same two A and B white balance values apply to all four settings of the FILTER control. It is possible, however, to change the AWB MEM menu setting to advanced menu 3 (see page 65) so that there are eight possibly different values for the A and B positions and for the four FILTER control settings.




- 1** Make the following settings on the camera.
 - **POWER switch:** ON/SAVE
 - **OUTPUT/DL/DCC+ switch:** one of the CAM positions
 - **Lens iris selector:** A (automatic)
 - **ATW button:** off
- 2** Set the **FILTER** control according to the lighting conditions. (See page 43.)
- 3** Set the **W. BAL** switch to A or B.


(continued)

White Balance Adjustment

- 4** Arrange a white subject (paper, cloth, etc.) under the same lighting conditions as for shooting, and zoom in on it so that as far as possible the whole screen is white. The minimum white area requirements for the adjustment are shown in the following figure.



- 5** Push the **WHT/BLK** switch in the **WHT** direction and release. The white balance adjustment is carried out. During the adjustment the legend "AUTO WHITE -OP-" appears in the viewfinder. After a few seconds the adjustment is complete, and the legend in the viewfinder changes to "AUTO WHITE-OK-" plus a color temperature, as shown in the following figure.



The adjustment value is automatically saved in memory A or B as selected above.

To save the white balance adjustment for different lighting conditions, repeat steps **2** to **4** above. You can save two different values for the white balance, in memories A and B.

Note

When using a camera control unit or remote control unit, if the **W/B BALANCE** switch of the control unit is set to **PRESET** or **MANUAL**, it is not possible to carry out white balance adjustment on the camera.

Message	Meaning and corrections to be made
WHITE-PRESET	The W. BAL switch is in the PRESET position. Move the W. BAL switch to the A or B position.
BARS	The camera is outputting a color bar signal. Move the OUTPUT/DL/DCC+ switch to one of the CAM positions.

Using the Preset White Balance Settings

The camera provides two preset white balance settings, for instant shooting with approximately the correct adjustment. The preset white balance can be selected between 2200 K and 4300 K when the **FILTER** control is set to 1 and between 4600 K and 12000 K when the **FILTER** control is set to 2, 3 or 4 (see page 59). There are also particular shooting conditions under which the preset values may give better results than the human eye adjustment.

- 1 Set the W. BAL switch to **PRESET**.
- 2 Set the **FILTER** control.

The white balance is automatically adjusted for the preset white balance selected in basic menu page 2 (see page 59).

Light Sources and Color Temperature

Adjustment of the white balance to match the light source is essential to ensure correct color rendering. The color of a light source is indicated as a color temperature in kelvins (K). It is higher for bluish light, and lower for reddish light. When the camera is shipped it is adjusted for use with video lights (halogen lamps with a color temperature of 3200 K). For use with other light sources, therefore, adjustment is required.

First use the **FILTER** control to set the approximate color temperature, then carry out white balance adjustment. The following table shows typical color temperature values for different light sources.

Light source	Color temperature (K)
Natural	10,000
Artificial	8,000
Clear sky	7,000
Light cloud	6,000
Cloudy or rainy skies	5,000
Direct sunlight, noon	White light
One hour after sunrise or before sunset	Fluorescent light (daylight white)
Mercury lighting	White light
Fluorescent light (warm white)	4,000
Studio lighting	3,500
Halogen lamps and video lights	3,200
Incandescent after sunrise or before sunset	Yellow light
Sodium street lighting	3,000
Candlelight	2,500
Sunrise or sunset	Red light

Using the ATW (Auto Tracing White Balance) Function

The ATW function continuously adjusts the white balance automatically to adapt to changes in lighting conditions.

Note

Depending on the shooting conditions, automatic adjustment may not necessarily give optimum results. For the best possible results, use the W. BAL switch.

To use the ATW function

Press the **ATW** button turning the indicator on. This activates the ATW function, and the ATW indication appears in the viewfinder. To disable the ATW function, press the **ATW** button again, turning the indicator off.

White Balance Adjustment


If the ATW function does not operate correctly
A warning message appears in the viewfinder as shown in the table below.

Message	Meaning and corrections to be made
TEMP LOW	If the FILTER control is in position 2, 3 or 4, change it to position 1, then retry the ATW operation.
TEMP HIGH	If the FILTER control is in position 1, change it to position 2, 3 or 4, then retry the ATW operation.




Black Balance Adjustment

Correct adjustment of the black balance is important for optimum operation of a video camera. It is necessary when using the camera for the first time or after a significant period out of use, and also when there has been a sudden change in temperature. The adjustment value is saved in memory, and readjustment is not normally necessary after powering the camera off or simply when lighting conditions change.



- 1 Move the POWER switch to the ON position, and check that the OUTPUT/DL/DCC+ switch is in one of the CAM positions.
- 2 Push the WHITE/BALANCE switch in the BLK direction and release.
The lens iris closes, and black balance adjustment is carried out.
During the adjustment the legend "AUTO BLACK -OP-" appears in the viewfinder.



After a few seconds the adjustment is complete, and the legend in the viewfinder changes to "AUTO BLACK -OK-".

Note

When using a camera control unit or remote control unit, if the W/B BALANCE switch of the control unit is set to MANUAL, it is not possible to carry out black balance adjustment on the camera.

If black balance adjustment cannot be completed automatically

The warning message "AUTO BLACK -NG-" appears in the viewfinder.
Make the necessary corrections, then carry out the process again.

Warning messages for black balance adjustment

Message	Meaning and corrections to be made
AUTO BLACK -NG- IRIS NOT CLOSED TRY AGAIN	The lens iris did not close fully. Check whether the lens cable is connected properly, and whether there is a fault in the lens. If a second attempt to carry out the adjustment fails, consult your Sony dealer.
AUTO BLACK -NG- ?? TRY AGAIN	The iris opened during adjustment or there is a hardware error. Close the iris and try again. If this fails, consult your Sony dealer.
BARS	The camera is outputting a color bar signal. Move the OUTPUT/DL/DCC+ switch to one of the CAM positions.



Shutter Settings

This section covers the settings for electronic shutter speed, CLS (clear scan) and EVS function. The new value for the shutter speed or clear scan frequency and EVS setting remains set until changed, even when the camera is powered off.

Shutter speeds

There are five shutter speeds, from $1/100$ s (DXC-D35/D35WSL) or $1/60$ s (DXC-D35P/D35WSP) to $1/2000$ s. Increasing the shutter speed reduces blurring when shooting a fast-moving subject. It is also possible to reduce flicker when shooting under fluorescent lighting by changing the shutter speed.

CLS (Clear Scan) function

When shooting a computer screen or projected image, horizontal bands may appear in the camera image. This is because the vertical scan frequency of the computer-generated image is different from the vertical scan frequency of the video system. The clear scan function allows you to select a vertical scan frequency to reduce this interference.

EVS (Enhanced Vertical Scan)

This function enhances the vertical scan resolution from 400 to 450 lines (or 450 to 530 lines) to reduce flicker. However, this increases the aliasing.


Setting the shutter speed, CLS and EVS function

Notes on setting the shutter speed

- The faster you make the shutter speed, the darker the image becomes. Check the brightness in the viewfinder, and if necessary increase the lighting level or adjust the iris.
- When the shutter speed is very fast, shooting a high intensity subject may cause long vertical tails to appear on the highlights (smear).

Notes on setting the CLS function

The vertical scan frequencies of computer screens vary, and it may not be possible to eliminate the interference patterns entirely. Note also that the vertical scan frequency may change depending on the software being run.




- 1 Set the SHUTTER switch to the ON position.

The SHUTTER indicator in the viewfinder comes on, and it is now possible to change the shutter speed or clear scan frequency setting and to set the EVS function. (If the EVS is already selected, the SHUTTER indicator will not light.)

- 2 Operate the MENU/STATUS switch to align the cursor with the item "SHUTTER" in basic menu page 1.

A.IRIS : #0
DTL LEV : #0
M.BLACK : #0
SHUTTER : #0
SHUTTER : 1/250

- 3 Press the UP/ON button or DOWN/OFF button to select the required shutter speed, scan frequency or EVS. Each time you press the UP/ON button or DOWN/OFF button, the shutter speed or clear scan frequency setting changes in the following order:



Setting the Clock and Timestamping Recordings

Use advanced menu page 8 to set the camera head's internal clock and record the date and time.


Note

If the following date/time setting procedure for the internal clock does not cause the date/time information to be displayed in advanced menu page 8, it may be due to a worn-out lithium battery in the camera head. See page 23 and replace the lithium battery.

How to set the date and time


- 1 Access advanced menu page 8.

For details of menu operations, see "Advanced Menu Operations" (page 64).



- 2 Move the cursor to CLOCK SET, then press the UP/ON button.

The following display appears, in which the year indication is flashing.



- 3 Press the MENU/STATUS switch and the UP/ON button to set the desired date and time.
1) Press the MENU/STATUS switch up or down until the item to be changed starts flashing.
2) Press the UP/ON button to change the number.

Repeat 1) and 2) until you have completed your date and time settings.

Timestamping recordings

You can timestamp recordings by superimposing the current date and time.

- 1 Before shooting, set the CLOCK IND to CAM in advanced menu page 8.

The date and time appear in the viewfinder, and are superimposed on the video signal output from the camera.

- 2 To stop superimposing the date and time, set the CLOCK IND to OFF.

- 4 Select whether to display a 12-hour clock (showing AM and PM hours) or a 24-hour clock.

1) Press the MENU/STATUS switch up or down to select the desired setting (12-hour clock display or 24-hour clock display).

Example of 12-hour clock display: 6:49 PM
("6" and "PM" are flashing)

Example of 24-hour clock display: 18:49 ("18" is flashing)

- 2) Press the UP/ON button.


- 5 Press the UP/ON button to select the date display format.

Each press of the UP/ON button cycles through the following options.

- Year-month-day:
YY MM DD
99 10 27
- Month-day-year:
MM DD YY
10 27 99
- Day-month-year:
DD MM YY
27 10 99

- 6 Press the MENU/STATUS switch down.

The cursor is shown at the CLOCK SET position.




- 7 Press the UP/ON button (to a time signal).

The clock starts from 00 seconds. The clock display can be viewed if CLOCK IND has been set to ON.



Viewfinder Screen Adjustments

The following adjustments are provided to improve the visibility of the viewfinder screen. Although these adjustments may make the viewfinder image clearer, they have no effect on the output video signal from the camera.



Contrast and brightness adjustment

Carry out these adjustments with the color bars displayed.

- 1 Set the OUTPUT/DL/DCC+ switch to the BARS position. The color bars appear in the viewfinder.
- 2 Watching the color bars, turn the CONTRAST and BRIGHT controls to adjust the contrast and brightness.
- 3 Return the OUTPUT/DL/DCC+ switch to its original position.

Outline emphasis adjustment

Turning the PEAKING control changes the degree of outline emphasis in the viewfinder image, to make focusing easier.

Adjusting the eyepiece focus

Depending on the eyesight of the camera operator — whether farsighted or shortsighted — the optimal position of the viewfinder image varies. Adjust the eyepiece focus to get the clearest viewfinder image for your eyesight. First focus the image with the lens, then adjust the eyepiece focusing knob. The adjustment range is from -3 to 0 diopters¹⁾ (default when shipped is 0 diopters).

Using an optional part allows you to modify the adjustment range to -2 to +1 diopters or -0.5 to +3 diopters.

For details, consult your Sony dealer.


1) Diopter: A unit to indicate the degree of convergence or divergence of a bundle of rays.

Adjusting the Lens

Flange Focal Length Adjustment

It is necessary to adjust the flange focal length (the distance from the lens flange to the plane of the image along the optical axis) in the following cases.


- When a lens is fitted for the first time
- After changing lenses
- When during zoom operations the focus does not match properly from telephoto to wide angle



- 1 Set the iris selector to the M position.
- 2 Turn the iris ring to f/1.8 (fully open).
- 3 Place the supplied flange focal length adjustment test chart at a range of about 3 meters (10 feet), and adjust the lighting so that an appropriate video output level is obtained with the iris at f/1.8.
- 4 Loosen the F.B. fixing screw.
- 5 Set the ZOOM selector to the MANU. position.
- 6 Move the manual zoom control to the telephoto position.
- 7 Turn the focusing ring so that the test chart is in focus.
- 8 Move the manual zoom control to the wide angle position.
- 9 Turn the F.B. adjustment ring so that the test chart is in focus. Do not move the focusing ring.
- 10 Repeat steps 6 to 9 until the image stays in focus from telephoto to wide angle.
- 11 After adjustment, tighten the F.B. fixing screw.

Adjusting the Lens

Iris Adjustments



There are three ways of adjusting the iris: automatically, manually, and with the instant automatic iris adjustment function.

Iris adjustment	
Adjustment method	Operation
Automatic adjustment mode The iris is adjusted automatically to adapt to changes in the brightness of the subject. This is the mode for normal shooting.	Set the iris selector to the A position.
Manual adjustment mode Use this mode in the following cases: • For special effects • When filming a person with a very bright sky background • When shooting a subject with extreme contrast The zebra pattern can be used as a guideline for iris adjustment.	Set the iris selector to the M position and turn the iris ring as required.
Instant automatic adjustment function While in manual adjustment mode, this function makes a temporary automatic adjustment.	With the iris selector in the M position, hold down the instant automatic iris button for as long as necessary.

To make the image lighter when shooting against the light

In the automatic iris adjustment mode, set the A.IRIS MODE switch to BACK L, turning the indicator on.

To make the image clearer when shooting a subject lit by a spotlight
In the automatic iris adjustment mode, set the A.IRIS MODE switch to SPOT L, turning the indicator on.

Using the zebra pattern in manual adjustment mode

To use the zebra pattern as a guideline for iris adjustment in manual adjustment mode, set the ZEBRA switch to the ON position.
Select the zebra pattern to be displayed in advanced menu page 4 (see page 65).
• **When the subject is a person**
Adjust the iris manually so that the zebra pattern appears on the highlights of the subject's face.
• **For other subjects**
Adjust the iris manually so that the zebra pattern appears on the most important parts of the subject.

Designating the lens

You have to designate the lens number according to the types of your lens.
If the number is not designated properly, other colors may appear on the upper and lower of the screen when shooting a white subject.
Set the number in advanced menu page 4 (page 65) according to the following table.

Product	Lens number
Fujinon: VCL-918BYA, A16X9 BRM, A12X6.8 BRM	1
Canon: VCL-918BT, Y118X9B KFS	2
Fujinon: A10X4.8 BEVMBERD, A15X8 BEVMBERD, A16X9 BRM, A20X8 BEVMBERD, A19X3.7 BRM, A19X8.7 BRM	3
Canon: J8aX5.2B IRS/IAS, J15aX8B IRS/IAS	4
Canon: J21aX7.8B IRS/IAS, Y118X9B IRS	

Set up the data with Sony dealer.

If you use the lens that is not mentioned above, set the lens number as follows:


- When using a lens without an extender, set it to 1.
- When using a lens with an extender, set it to 2.
- When using a lens with a ratio converter, set it to 2.

You can also ask a Sony dealer more precise settings according to your lens. In this case, set it to 4.

Adjusting the Iris Sensitivity

You usually need not adjust the iris sensitivity because lenses are equipped with iris sensitivity adjustment function.

In auto iris mode, if hunting or response delay happens, adjust the iris sensitivity using the iris sensitivity trimmer.




You can see the iris sensitivity trimmer when removing the gum cap on the front of the lens driving unit.

Use a mini-screwdriver to turn the trimmer. If you turn it clockwise, the sensitivity increases, and if you turn it counterclockwise, the sensitivity decreases. It is recommended that you confirm the iris sensitivity after replacing the lens.

For more information, refer to the operating instructions for the lens (or consult the lens maker).

Macrophotography

Use the macro function when the subject is less than about 90 cm (3 feet) (for the VCL-918BY) from the front of the lens. It is possible to shoot close-ups down to a range of 10 mm (wide angle, F = 9 mm).



1 Bring the lens up to the subject so that the image is the required size.

2 Move the focusing ring to the closest focus position.

3 Slide the M button toward the rear of the camera, and turn the MACRO ring fully in the direction shown by the arrow.

4 Move the ZOOM selector to the MANU position, and turn the manual zoom control to focus the image.

Ending close-up shooting

Return the MACRO ring to its original position (turn fully in the opposite direction to the arrow in the figure).

Reducing the size of the image

After completing steps 1 to 4 above, if you wish to reduce the size of the image, turn the MACRO ring back slightly, then use the manual zoom control again to focus the image.




Settings for Special Cases

Settings for special cases

Shooting conditions	Setting	Effect
The background is very bright, and the subject is too dark.	Set the A.I.RIS MODE switch to BACK L, turning the indicator on.	This lightens the foreground.
The subject is under a spotlight.	Set the A.I.RIS MODE switch to SPOT L, turning the indicator on.	This prevents white burn-out in highlights of faces and clothes.
The subject is completely still (e.g. when shooting documents, drawings, etc.).	Enable the EVS (Enhanced Vertical definition System) function. (See page 84.)	This enhances the vertical resolution.
	NOTE Enabling the EVS function tends to increase the occurrence of aliasing problems (more patterns). Therefore, normally leave the function disabled.	
When you wish to give a lush effect, as when shooting a wedding or similar occasion.	Use the HI SAT file. (Access advanced menu page 10 with the SET UP switch set to FILE.)	This increases the saturation of primary colors.
Shooting under fluorescent lighting.	Use the FL file. (Access advanced menu page 10 with the SET UP switch set to FILE.)	This eliminates the blue-green cast, and restores natural hues.
When shooting bright areas mixed with dark areas (Example: A person indoors looking through a window at a bright landscape outdoors)	Set DL to ON in the advanced menu page 2 and, then set the OUTPUT/DL/DCC+ switch to CAM DL.	Prevents white breakup and color faults in bright areas.
When adjusting for skin detail or tone (Example: When shooting to hide skin details)	See "Skin Detail Correction" or "Adjusting Color in the Specified Area" (page 93).	Adjusts the skin detail or tone to a designated active area.
When you wish to give pictures a natural taste created by film camera.	Use the FILMLIKE file. (Access advanced menu page 10 with the SET UP switch set to FILE.)	The "filmlike" effect is added to the picture.
To make focusing before shooting easier.	Press the EZ FOCUS button, turning the "easy focus" function on.	This opens the iris, to make it easier to focus before beginning shooting.
To begin shooting immediately when there is no time to make adjustments.	Set the EZ MODE switch to the ON position.	This provides automatic adjustment to a set of standard values, to allow immediate shooting.

Skin Detail Correction

The DXC-D35/D35P/D35WSL/D35WSP/L provides an easy push-button function that designates an active skin tone area.



1 Set the SKIN DTL switch to ON.

The indication "SKIN AREA: ±0" appears in the viewfinder.

2 Press the SKIN DTL SET button.

This causes the area detect cursor to be shown in the viewfinder (for 10 seconds).

3 Place the area detect cursor on the target, then press the SKIN DTL SET button.

This designates the correction area, which is indicated by a zebra pattern, and the indication "SKIN AREA: ±0" appears again. If the area detect cursor disappears before designating the area, press the SKIN DTL SET button again to display the cursor. (Return to step 2.)

4 Press the UP/ON or DOWN/OFF button to change the SKIN AREA value (–99 to +99) so that the zebra pattern may be displayed in the target area. Use basic menu page 2 to set the correction level (see page 59).


You can also change color in the designated area (see the following section).

Adjusting Color in the Specified Area

You can adjust the specified color using setup files. Perform the same procedure with the skin detail correction to designate the target area.

1 Turn the POWER switch on with holding down the UP/ON button.

2 Perform steps 1 and 2 in "Changing File Settings" (page 73) and display advanced menu page 12 in the most suitable file for shooting.



3 Perform the procedure for the skin detail correction to designate the area to which you apply color adjustment.

While this procedure is being performed, the menu is not displayed.

4 When advanced menu page 12 appears, change the value of the SKIN SAT or SKIN HUE to adjust color in the area designated in step 3.

Note

Set the SKIN DTL to 1.0 in basic menu page 2 if the skin detail correction is unnecessary.

Appendix

Important Notes on Operation

Fitting the zoom lens

It is important to fit the lens correctly, as otherwise damage may result. Be sure to refer to the section "Fitting the Lens" (See page 30).

Do not cover the unit while operating

Putting a cloth, for example, over the unit can cause excessive internal heat build-up.

Operation and storage

Avoid storing or operating the unit in the following conditions.

- In excessive heat or cold (operating temperature range: -10°C to $+45^{\circ}\text{C}$ (14°F to 113°F)). Remember that in summer in warm climates the temperature inside a car with the windows closed can easily exceed 50°C (122°F).
- In damp or dusty locations
- Locations where the unit may be exposed to rain
- Locations subject to violent vibration
- Close to radio or TV transmitters producing strong electromagnetic fields.

Viewfinder

- Do not leave the camera with the eyepiece pointing directly at the sun.
The eyepiece lens can concentrate the sun's rays and melt the interior of the viewfinder.
- Do not use the viewfinder close to strong magnetic fields. This can cause picture distortion.

Shipping

Use the optional LC-421 Carrying Case for optimal shipping.

If sending the camera by truck, ship, air or other transportation service, first store it in the carrying case, then pack the carrying case in the supplied carton (or an equivalent).

Care of the unit

Remove dust and dirt from the surfaces of the lenses or optical filters using a blower.

If the body of the camera is dirty, clean it with a soft, dry cloth. In extreme cases, use a cloth steeped in a little neutral detergent, then wipe dry. Do not use organic solvents such as alcohol or thinners, as these may cause discoloration or other damage to the finish of the unit.

In the event of operating problems

If you should experience problems with the unit, contact your supplier or Sony service representative.


Important Notes on Operation

Characteristics of CCD Sensors

The following effects may appear in the image. They are characteristic of cameras using CCDs (charge-coupled devices), and do not indicate a malfunction.

Vertical smear

When shooting a very bright object, such as a light, the highlight tends to produce vertical tails. This effect is much reduced in this camera.



White flecks

If the camera is operated at a high temperature, white flecks may appear in the image.

Warning Indications

If a fault occurs during operation, a warning is given by the REC/TALLY and BATT indicators in the viewfinder and the tally lamp lighting or flashing, and also by warning indications on the viewfinder screen. When you are using a DSR-1/P or PVV-3/P, the

WARNING indicator on the VTR also lights or flashes, and warning indications appear in the display window. There is also a warning tone in the earphone.

Warning indications

Camera	VTR		Fault		VTR action	What to do
	BATT indicator and tally lamp	Viewfinder screen indication	Warning tone	Display window		
REC/TALLY indicator and tally lamp	—	—	—	RF (during recording only)	—	—
—	—	—	—	SERVO	—	—
—	—	—	—	HUMID	—	—
—	—	—	—	SLACK	—	—
—	—	—	—	TAPE (flashing, during recording only)	—	—
—	—	—	—	TAPE (flashing)	—	—
—	—	—	—	BATT (flashing)	—	—
—	—	—	—	BATT (flashing)	—	—
—	—	—	—	Continuous	—	—

REC/TALLY indicator and tally lamp: Four beeps per second
Viewfinder screen: Four beeps per second
BATT indicator and tally lamp: One beep per second
For the warnings appearing in the viewfinder when a VTR is connected, see the section "Viewfinder Normal Indications" (page 54).



Appendix



Appendix

Specifications

DXC-D35P/D35WS/D35WSP Camera Head

Imaging element Three-chip interline transfer CCD
Pixel resolution DXC-D35: 768 (horizontal) × 494 (vertical)
DXC-D35P: 752 (horizontal) × 582 (vertical)
DXC-D35WS: 980 (horizontal) × 494 (vertical)
DXC-D35WSP: 980 (horizontal) × 582 (vertical)
Imaging area DXC-D35/D35P: 8.8 × 6.6 mm (2 1/8 inch, 4/3 optical system)
DXC-D35WS/D35WSP: 9.6 × 5.4 mm (3/8 inch, 16/9 optical system)

Built-in filter settings

1: 3200K
2: 5600K + 1/8ND
3: 5600K
4: 5600K + 1/8ND
Lens mount Bayonet mount
Signal standards EIA standard signal (NTSC color system) (DXC-D35/D35WS)
CCIR standard signal (PAL color system) (DXC-D35P/D35WSP)
Scanning system 525 lines, 2:1 interface (DXC-D35/D35WS)
625 lines, 2:1 interface (DXC-D35P/D35WSP)

Scanning frequencies

Horizontal: 15.734 kHz (DXC-D35/D35WS)
15.625 kHz (DXC-D35P/D35WSP)
Vertical: 59.94 Hz (DXC-D35/D35WS)
50.00 Hz (DXC-D35P/D35WSP)
Synchronization Internal sync
External sync, using signal input (VBS or BS) to the GEN LOCK IN connector of an optional camera adaptor or input from the GEN LOCK connector of a camera control unit to the YTR/CCU/CMA connector of an optional camera adaptor.

Horizontal resolution (center)

DXC-D35/D35P: 880 TV lines
DXC-D35WS/D35WSP: 850 TV lines (4:3 mode), 800 TV lines (16:9 mode)

Minimum illumination

0.25 lux (at f/1.4, +42 dB)
0.4 lux (at f/1.8, +42 dB)
2000 lux (f/11.0 standard, 3200 K)
Sensitivity Selectable -3 dB, 0 dB, 3 dB, 6 dB, 9 dB, 12 dB, 18 dB, 18 dB + DPR, 24 dB, 24 dB + DPR, hyper gain (30 dB + DPR or 36 dB + DPR)
Gain levels

Video output

Composite signal 1.0 Vp-p, sync negative, 75 Ω, unbalanced
Y/C separate signals Y: 1.0 Vp-p, sync negative, unbalanced
C: burst level 0.286 Vp-p, no sync

Video SN ratio

63 dB (typical) (DXC-D35/D35WS)
61 dB (typical) (DXC-D35P/D35WSP)

Registration

0.05% for all zones, without lens

Input/output connectors

VIDEO OUT connector: BNC, 75 Ω, unbalanced
LENS connector: 12-pin, for 7/8-inch lens
VF connector (front): 20-pin
VF connector (left side): 8-pin
REMOTE connector 1: Stereo mini-jack
REMOTE connector 2: 10-pin
MONITOR OUT connector: BNC, 75 Ω, unbalanced
Power supply 12 V DC
Power consumption DXC-D35/D35P: 12 W (12.7 W when the DSR I/P is connected)
DXC-D35WS/WSP: 14.9 W (15.3 W when the DSR I/P is connected)

Operating temperature


-10 °C to +45 °C (14 °F to 113 °F)

Storage temperature

-20 °C to +60 °C (-4 °F to 140 °F)
DXC-D35/D35P: 2.4 kg approx. (5 lb 4 oz)
DXC-D35WS/D35WSP: 2.5 kg approx. (5 lb 8 oz)

Mass

External dimensions in millimeters (inches)



DXF-801/801CE Viewfinder

Picture tube 1.5-inch monochrome
Indicators REC/TALLY (x2), BATT., SHUTTER, GAIN UP
Resolution 600 TV lines
Power supply 12 V DC
Power consumption 2.1 W
Mass 620 g approx. (1 lb 5 oz)
Maximum external dimensions 241 (W) × 91 (H) × 203 (D) mm (9 1/2 × 3 1/4 × 8 inches)
Scan size Switchable between 4:3 and 16:9

Supplied accessories

RM-LGH Remote Control Unit¹⁾ (1)
VCL-918BY Zoom Lens¹⁾ (1)
DXF-801/801CE Viewfinder²⁾ (1)
Microphone³⁾ (1)
Wind screen³⁾ (1)
VCT-U14 Tripod Adaptor³⁾ (1)
Lens mount cap (1)
Flange focal length adjustment test chart (1)
Operating Instructions (1)

Design and specifications are subject to change without notice.

Related Products

There is a range of Sony products available to meet every conceivable video shooting requirement. For details, consult your Sony sales representative or supplier.

Lenses

VCL-918BYA/916BY/916BYA/918BY Zoom Lens

Camera adaptor products

CA-325A/325AP/327P/511/512P/513/537/537P Camera Adaptor
CMA-8A/8ACE AC Adaptor
RM-M7G Camera Remote Control Unit

3) When connecting a CA-512/512P, remove the blank panel on the CA-512/512P.



Chart of Optional Components and Accessories

VTR products
 DSR-1/1P Digital Videocassette Recorder
 EVY-9000/9000P Videocassette Recorder
 PVV-1/1P/1A/1AP/3/3P Portable Videocassette Recorder
 VVO-8800/8800P Portable Videocassette Recorder
 BVU-150/150P Portable Videocassette Recorder
 BVU-5/5PS Videocassette Recorder
 BYW-50/50P Portable Videocassette Recorder
 A-5/59/5900P VTR Adapter

Battery products
NP-1B/1A Battery Pack
BP-90A Battery Pack
BC-1WD/1WDCE/1WB/1WBCE/140/410CE Battery
Charger

Microphone products
ECM-670/672 Electret Condenser Microphone
C-74 Condenser Microphone
CAC-12 Microphone Holder
EC-0.5C2 Microphone Cable
EC-0.3C2 Microphone Cable

Studio equipment	Unit
CCU-M5/M5P/M5A/M5AP/M7/M7P Camera Control	
DXF-51 5-inch Viewfinder (monochrome)	
DXF-41 4-inch Viewfinder (monochrome)	
PR-100 Intercom Headset	

Cables and miscellaneous
The suffix number on a cable part number indicates the length in meters: e.g. a CCZ-A2 is 2 meters long.
Approximate equivalents in feet: 2 m = 6 ft, 5 m = 16 ft, 10 m = 33 ft, 25 m = 82 ft, 50 m = 164 ft, 100 m = 28 ft)

CCZ-A2/A5/A10/A25/A50/A100

CCZQ-A2/A5/A10/A2AM


Camera cables with Q-type 14-pin connectors

CCQ-10AM/25AM/50AM/100AM

and J-type 10-pin connector

CR-1 Rain Cover

C-DS300SF1 Soil Case



What is ClipLink?

The ClipLink™ function greatly improves the efficiency of the video production process as a whole by recording various editing-related data on tape when shooting. As such, ClipLink is a revolutionary function that transcends the conventional separation of shooting and editing.

Note

When an external equipment, such as VCR, is connected to the DV OUT connector, the ClipLink function will not work.

How ClipLink Changes Video Production Techniques

The following describes various ways in which ClipLink[®] video production differs from conventional video production.

Recording of ClipLink log data lightens the shooting workload

When you start shooting a scene, ClipLink log data such as the scene number and time code data are automatically recorded into the cassette memory. This eliminates the need for a conventional "shot list" compiled by someone using a stopwatch, clipboard and pencil. You can also designate unwanted scenes as "NG" (no good) and automatically skip all "NG" scenes when editing.

Recorded Index Pictures drastically cut editing time

The ClipLink function also features Index Pictures a time-saving tool for rough editing. Each Index Picture is a compressed image taken from the start of each scene, which is recorded onto the tape as a still picture. When editing, begin by transferring only the Index Pictures and the ClipLink log data to the EditStation's hard disk. You can also transfer OK scenes only ("NG" scenes are skipped).


- 1) The ClipLink system is a video production system which uses the cassette memory function.

ClipLink Operation Flow

The following is a detailed description of how to use the ClipLink function during the video production process.

Example System Configuration

The following illustration shows the optimum system configuration for using the ClipLink function. ClipLink operation is possible even with a system containing existing analog equipment. However, note that a part of functions are disabled.



- a) The DSR-6080P is a videocassette player.
- b) Between the DSR-8585P and ES-7, quadruple transfer is possible through the OSDI.


ClipLink Operation Flow

Data Generated When Shooting

The following describes the kinds of data that is generated when using the ClipLink function.

Index Pictures

When shooting, a single-frame image from the Mark IN point at the start of each scene is recorded as a still picture into the DSR-1/P's internal memory. These images are called "Index Pictures". When you finish shooting, the Index Pictures from all scenes are recorded onto the tape after the last scene.




Up to 32 Index Pictures can be recorded onto the tape space normally occupied by one frame, as shown below.

ClipLink log data

ClipLink log data can be recorded automatically or manually into the cassette memory for use as a

ClipLink log data	Description
Reel number (cassette number)	Data (maximum length: 8 digits) consisting of alphanumeric characters and/or symbols (This is left blank at shipping.)
Scene number	A three-digit number from 001 to 198 (starts at 001 and is automatically incremented with each scene).
Take number	This cannot be changed (set to "1" at shipping).
OK/NG	Indicates the OK/NG status of a particular scene. (In the OK case, nothing is recorded.)
Mark IN/OUT point time codes	These are the time codes that indicate the Mark IN and Mark OUT points for each scene (HH:MM:SS). These time codes are recorded when the camcorder has been set to Mark mode.
Cue point time code	The frame digit is incremented at each Mark IN point and is decremented at each Mark OUT point. (For details, see "Time codes recorded for Mark IN/OUT points" on page 106)



Seven frame spaces are reserved at the end of the last scene as a recording area for Index Pictures. (A cassette with 16 Kbits of cassette memory can record up to 198 Index Pictures, and a cassette with 4 Kbits of cassette memory can record up to 45 Index Pictures.)

convenient alternative to the conventional "shot list". ClipLink log data includes the following items.

How to record ClipLink log data


The following describes how to record the various ClipLink log data items.

OK/NG status

To designate a scene as "NG", press the NG button on the camcorder while shooting the scene or at any time before you begin shooting the next scene. All scenes that do not receive an "NG" designation are recorded as "OK" scenes. (When you exit the VCR recording mode, changing the OK/NG status is no longer possible.)


Mark IN/OUT points time codes

This data is especially useful when shooting a video program for which a scenario has been created. Set the camcorder to Mark mode before you start shooting. While shooting, each time you press the camcorder's TAKE button, Mark IN and Mark OUT time codes are recorded alternately.



Cue point time codes

This type of data is especially useful when shooting scenes that may contain unexpected events, such as when shooting for sports coverage or documentaries. Set the camcorder to Cue mode before you start to record. While recording, each time you press the camera's TAKE button, the current time code is recorded as a cue point time code.




Appendix

ClipLink Operation Flow

Time codes recorded for Mark IN/OUT points

There is a gap between actual time codes and Mark IN/OUT time codes recorded in the cassette memory, as shown in the figure below. The frame digit is incremented at each Mark IN point and is decremented at each Mark OUT point.



Recording capacity for Mark IN/OUT time codes and Cue point time codes

When in Mark mode, up to 198 pairs of Mark IN and Mark OUT points can be recorded (if using a cassette with 16 Kbits of cassette memory).
When in Cue mode, up to 396 time codes points (including all cue point time codes and all Mark (Rec) IN and Mark (Rec) OUT time codes) can be recorded (if using a cassette with 16 Kbits of cassette memory).




Appendix

Section 2

Service Overview

2-1. Board Layout




*1 : DXC-D35/D35P

*2 : DXC-D35WS/D35WSP

2-2. Removal/Attachment of Cabinet


2-2-1. Removal of Side Plate

Slacken the eight screws as shown in the figure and remove the right and left side plates.




2-2-2. Removal/Attachment of Top Chassis

1. Remove the right and left side plates. (Refer to Section 2-2-1.)
2. Remove the two screws of the rear plate to remove the DC/DC converter.
3. Remove the VA, PR, IF and ES boards.



4. Remove the three screws and take off the SW board in the horizontal direction.




5. Remove the two screws and take off the AT board in the horizontal direction.
6. Disconnect the four flexible card wires from the three connectors (CN805, CN806 and CN807) on the CN board and from the connector (CN103) on the MB board.


Note

When disconnecting flexible card wires, refer to Section 2-11.

7. Disconnect the eleven harness connectors from the connectors on the MB board (CN2, CN105, CN106, CN107, CN117, CN118, CN119, CN120, CN121, CN122 and CN123).
8. Remove the two screws and two supports on the MB board and take off the MB board in the horizontal direction.




9. Remove the two screws of the front unit assembly shown in the figure and the two screws of the rear plate, and then remove the top chassis.



10. To reattach, perform in the reverse order of steps 1 to 9.

Notes

- Be sure to route the harnesses as shown in the figure when reattaching the MB board.
- When reinstalling the VA, PR, IF and ES boards, use care to insert securely the connectors on each board to the connectors of the MB board as far as they will go.
- When reconnecting the flexible card wires, refer to Section 2-11.



2-3. Replacement of CCD Unit

Description on CCD Block Number

Every CCD unit has its own ID number called CCD block number. It shows the CCD block type and serial number for the CCD block.

The CCD block number label is put in the CCD unit.

GUA xxxxx : DXC-D35 (NTSC)

GVA xxxxx : DXC-D35P (PAL)

HDA xxxxx : DXC-D35WS (NTSC)

HEA xxxxx : DXC-D35WSP (PAL)

Serial number for the CCD unit
CCD block type

1. Remove the lens and viewfinder. (Refer to the instruction manual.)


Note

To protect the prism block, be sure to cover the lens mount portion with the mount cap.


2. Remove the left side plate. (Refer to Section 2-2-1.)
3. Remove the AT board. (Refer to Section 2-2-2.)
4. Disconnect the harness connectors from the four connectors (CN2, CN105, CN106 and CN107) and the flexible card wire from the connector (CN103) on the MB board.

Note

When disconnecting the flexible card wire, refer to Section 2-11.




5. Remove the four screws to remove the front unit assembly.



6. Remove the setscrew shown in the figure and take off the filter knob.
7. Remove the four screws and four washers of the front panel to remove the CCD unit.


Note

Use great care to avoid any pressure on the PA board when handling the CCD unit.



2-3. Replacement of CCD Unit

8. Take a new CCD unit out of a transport holder and install it to the unit in the reverse order of steps 1 to 7.



9. Perform the pedestal alignment (in Section 3-3-12), the shading alignment (in Section 3-3-13) and the flare alignment (in Section 3-3-14).

Notes

- Before performing alignment, be sure to read each item in Section 3-1-4 "Note on Alignment".
- Reuse the transport holder to transport the CCD unit removed from the unit.

2-4. Connectores and Cables


2-4-1. Connector Input/Output Signals

The main connector input/output signals are as follows:

MONITOR OUT (BNC) ; 1.0 V p-p ± 0.1 V, sync negative 75 Ω

VIDEO OUT (BNC) ; 1.0 V p-p ± 0.1 V, sync negative 75 Ω

CAMERA/CA (50P, MALE)



(EXTERNAL VIEW)


No.	Signal	I/O	Specifications
A1	MODE ID	IN	OPEN : COMP, GND : R/G/B
B1	GND (CHASSIS)	—	
A2	MIC (Y)	OUT	−60 dBm
B2	MIC (X)	OUT	
A3	MIC (G)	—	
B3	EAR (G)	—	
A4	REC TALLY IND	IN	$Z_i \geq 600 \Omega$
B4	EAR (X)	IN	−6 dBu
A5	VTR TRIG	OUT	
B5	REC RESET	IN	
A6	S.D (V/C)	IN	H : 5 V
B6	S.D (V/C)	OUT	L : 0 ± 0.5 V
A7	CS VTR	IN	$Z_i \geq 47 \text{ k}\Omega$
B7	SCL VTR	IN	$Z_o \leq 1 \text{ k}\Omega$
A8	GENLOCK VIDEO (G)	—	VBS : 1.0 V p-p
B8	GENLOCK VIDEO (X)	IN	$Z_i \geq 1 \text{ k}\Omega$
A9	SYNC (G)	—	H : 4.0 to 5.5 V p-p : NEGATIVE
B9	SYNC (X)	OUT	L : 0 ± 0.4 V dc $Z_o \geq 2 \text{ k}\Omega$
A10	PB RET VIDEO (G)	—	1.0 V p-p
B10	PB RET VIDEO (X)	IN	$Z_i \geq 10 \text{ k}\Omega$
A11	CF/V RESET	I/O	H : 4.0 to 5.5 V p-p $Z_o \leq 2 \text{ k}\Omega$ L : 0 ± 0.4 V dc
B11	VF VIDEO CONT	IN	CAM : OPEN $Z_i \geq 1 \text{ k}\Omega$, PB : 0 V
A12	VBS (CA) (G)	—	1.0 V p-p, SYNC NEGATIVE
B12	VBS (CA) (X)	OUT	$Z_o = 75 \Omega \pm 5 \%$
A13	STBY/SAVE	OUT	STBY : 4.0 to 5.5 V p-p $Z_o \leq 100 \Omega$ SAVE : 0 ± 0.25 V
B13	VTR/CCU CONT	OUT	VTR : 0 ± 0.25 V $Z_o \leq 1 \text{ k}\Omega$ CCU : 5.0 ± 0.5 V
A14	CHROMA (G)	—	NTSC : 0.286 V p-p $\pm 10 \%$
B14	CHROMA (X)	OUT	PAL : 0.300 V p-p $\pm 10 \%$ $Z_o \leq 75 \pm 5 \%$

No.	Signal	I/O	Specifications
A15	Y (G)	—	1.0 V p-p, SYNC NEGATIVE
B15	Y (X)	OUT	$Z_o \leq 75 \Omega \pm 5 \%$
A16	COMP (CA) GND	—	R/G/B
B16	R/R-Y (CA)	OUT	1.4 V p-p, POSITIVE
A17	G/Y (CA)	OUT	$Z_o \leq 75 \Omega \pm 5 \%$
B17	B/B-Y (CA)	OUT	COMPONENT OUT*1
A18	BATT ALARM/S. DATA		
B18	REC REVIEW CONT	OUT	GND ; REC REVIEW
A19	(SPARE)		
B19	(SPARE)		
A20	+8.5 V	OUT	8.3 V to 9.1 V
B20	+5 V	OUT	5 V ± 0.1 V
A21	−5 V	OUT	−5 V ± 0.1 V
B21	AGND	—	REG, GND
A22	POWER EXT DC	IN	10.6 V to 17.0 V dc
B22	POWER EXT DC	IN	
A23	POWER EXT DC GND	—	GND for EXT DC
B23	POWER EXT DC GND	—	
A24	(SPARE)		
B24	(SPARE)		
A25	GND (CHASSIS)	—	CHASSIS GND
B25	GND (CHASSIS)	—	

*1

	UC	CE
Y	0.714 V p-p	0.700 V p-p
R-Y	0.756 V p-p	0.525 V p-p
B-Y	0.756 V p-p	0.525 V p-p

CAMERA/CA (76P, MALE)




(EXTERNAL VIEW)

No.	Signal	I/O	Specifications
1	REC TALLY	IN	$Z_i \geq 600 \Omega$
2	S.D. (V/C)	IN	H : 5 V L : 0 ± 0.5 V
3	SCL VTR	IN	$Z_i \geq 47 \text{ k}\Omega$ $Z_o \leq 1 \text{ k}\Omega$
4	GENLOCK (G)	—	GND for GENLOCK (X)
5	SYNC (G)	—	GND for SYNC (X)
6	PB (G)	—	GND for PB (VBS) (X)
7	PB (Y) (X)	IN	1.0 V p-p, NEGATIVE, $Z_i \geq 1 \text{ k}\Omega$
8	VBS (CA) (G)	—	GND for VBS (CA) (X)
9	VTR/CCU	OUT	VTR : 0 ± 0.25 V, $Z_o \leq 1 \text{ k}\Omega$ CCU : 5.0 ± 0.5 V
10	C (X)	OUT	NTSC : 0.286 V p-p ± 10 % PAL : 0.300 V p-p ± 10 % $Z_o \leq 75 \Omega \pm 5$ %
11	Y (X)	OUT	1.0 V p-p, SYNC NEGATIVE $Z_o \leq 75 \Omega \pm 5$ %
12	R/R-Y (CA)	OUT	R/G/B 1.4 V p-p, POSITIVE
13	B/B-Y (CA)	OUT	$Z_o \leq 75 \Omega \pm 5$ % COMPONENT OUT*1
14	SKIN GATE	OUT	Gate area (H : 4 to 5.5 V dc) Non gate area (L : 0 ± 0.2 V dc)
15	+5.0V	OUT	5 V ± 0.1 V
16	AGND	—	REG, GND
17	EXT DC	IN	10.6 V to 17.0 V dc
18	EXT DC GND	—	GND for EXT DC
19	DCLK (X)	OUT	
20	VTR TRIG	OUT	
21	S.D. (C/V)	OUT	H : 5 V L : 0 ± 0.5 V
22	CS VTR	IN	$Z_i \geq 47 \text{ k}\Omega$ $Z_o \leq 1 \text{ k}\Omega$
23	GENLOCK (X)	IN	VBS : 1.0 V p-p $Z_i \geq 1 \text{ k}\Omega$
24	SYNC (X)	IN	H : 4.0 to 5.5 V p-p : NEGATIVE L : 0 ± 0.4 V dc $Z_o \leq 2 \text{ k}\Omega$
25	PB (VBS) (X)	IN	1.0 V p-p, SYNC NEGATIVE $Z_o \leq 75 \Omega \pm 5$ %
26	CF/V RESET	I/O	H : 4.0 to 5.5 V p-p, $Z_o \leq 2 \text{ k}\Omega$ L : 0 ± 0.4 V dc

No.	Signal	I/O	Specifications
27	VBS (CA) (X)	OUT	1.0 V p-p, SYNC NEGATIVE $Z_o = 75 \Omega \pm 5$ %
28	C (G)	—	GND for C (X)
29	Y (G)	—	GND for Y (X)
30	COMP GND	—	GND for G/Y (CA)
31	G/Y (CA)	OUT	R/G/B 1.4 V p-p, POSITIVE $Z_o \leq 75 \Omega \pm 5$ % COMPONENT OUT*1
32	BATT S.DATA	IN	
33	+9.0 V	OUT	8.3 V to 9.1 V
34	-5.0 V	OUT	-5 V ± 0.1 V
35	EXT DC	IN	10.6 V to 17.0 V dc
36	EXT DC GND	—	GND for EXT DC
37	DCF	OUT	
38	DCLK GND	—	
39	MODE ID	IN	OPEN : COMP, GND : R/G/B
40	MIC1 (G)	—	
41	AUDIO LEV	OUT	H : 4 to 5.5 V dc L : 0 ± 0.2 V dc, 1 k Ω
42	(SPARE)		
43	DIGI/ANA	IN	H : Analog L : Digital
44	(SPARE)		
45	(SPARE)		
46	(SPARE)		
47	(SPARE)		
48	(SPARE)		
49	(SPARE)		
50	(SPARE)		
51	(SPARE)		
52	DCLK GND	—	GND for DCLK (X)
53	BYRY (0)	OUT	H : 3 ± 0.2 V dc
54	BYRY (2)	OUT	L : 0 ± 0.2 V dc
55	BYRY (4)	OUT	
56	BYRY (6)	OUT	
57	BYRY (8)	OUT	
58	MIC1 (X)	OUT	-20 dBm, $Z_o \leq 100 \Omega$
59	MIC1 (Y)	OUT	

REMOTE (10P, FEMALE)




(EXTERNAL VIEW)


No.	Signal	I/O	Specifications
60	(SPARE)		
61	(SPARE)		
62	76P ID		
63	(SPARE)		
64	(SPARE)		
65	(SPARE)		
66	(SPARE)		
67	(SPARE)		
68	(SPARE)		
69	(SPARE)		
70	(SPARE)		
71	(SPARE)		
72	BYRY (1)	OUT	H : 3 ± 0.2 V dc
73	BYRY (3)	OUT	L : 0 ± 0.2 V dc
74	BYRY (5)	OUT	
75	BYRY (7)	OUT	
76	BYRY (9)	OUT	

*1

	UC	CE
Y	0.714 V p-p	0.700 V p-p
R-Y	0.756 V p-p	0.525 V p-p
B-Y	0.756 V p-p	0.525 V p-p


No.	Signal	I/O	Specifications
1	(SPARE)		
2	VBS (RM)	OUT	1.0 V p-p, SYNC NEGATIVE
3	VBS (RM)	OUT	
4	RS232C (C/RM)	IN	
5	VTR START/STOP	IN	$Z_i \geq 10 \text{ k}\Omega$  OPEN (4.5 ± 0.5 V) 0 ± 0.5 V
6	S. DATA (X)		0 to 5 V $Z_i \geq 10 \text{ k}\Omega$
7	RS232C (RM/C)	OUT	GND for S. DATA
8	REC TALLY IND	OUT	$Z_o \geq 600 \Omega$
9	POWER EXT DC GND	-	GND for EXT DC
10	POWER EXT DC	OUT	10.6 V to 17.0 V dc

VF (8P, FEMALE)




(WIRING SIDE)

No.	Signal	I/O	Specifications
1	POWER EXT DC GND	-	GND for EXT DC
2	REC TALLY IND	OUT	$Z_o \leq 1.1 \text{ k}\Omega$
3	SHUTTER IND	OUT	$Z_o \leq 1.1 \text{ k}\Omega$
4	VF VIDEO (G)	OUT	GND for VF VIDEO
5	BATT IND	OUT	$Z_o \leq 1.1 \text{ k}\Omega$
6	VF VIDEO (X)	OUT	V = 1 V p-p
7	POWER EXT DC	OUT	10.6 V to 17.0 V dc
8	GAIN UP IND	OUT	$Z_o \leq 1.1 \text{ k}\Omega$

LENS (12P, FEMALE)


(EXTERNAL VIEW)

No.	Signal	I/O	Specifications
1	RET SW	IN	ON : 0 ±0.5 V dc
2	VTR START/STOP	IN	TRIG : 0 ±0.5 V
3	POWER EXT DC GND	—	GND for EXT DC
4	COMPULSORY AUTO IRIS CONT	OUT	AUTO : 4.5 ±0.5 V MANU : 0 +0.5 V or OPEN
5	IRIS CONT	OUT	F16 : 3.4 V dc F2.8 : 6.2 V dc
6	POWER EXT DC	OUT	10.6 V to 17.0 V dc
7	IRIS POSI	IN	F16 : 3.4 ±0.1 V dc F2.8 : 6.2 ±0.1 V dc
8	REMOTE/LOCAL	OUT	REMOTE : 5 V LOCAL : 0 V
9	EXTND ON/OFF	IN	
10	ZOOM POSI	IN	
11	(SPARE)		
12	(SPARE)		

MIC (3P, FEMALE)

(EXTERNAL VIEW)

No.	Signal	I/O	Specifications
1	MIC (G)	IN	GND for MIC
2	MIC (X)	IN	-60 dB
3	MIC (Y)	IN	BALANCED (0 dB = 0.775 V)

VF (20P, FEMALE)

(EXTERNAL VIEW)

No.	Signal	I/O	Specifications
1	PEAKING CONT	IN	Zi ≥ 5 kΩ
2	POWER EXT DC	OUT	10.5 V to 17.0 V dc, 2 A
3	REC TALLY IND	OUT	Zo ≤ 500 Ω
4	BATT IND	OUT	Zo ≤ 1.1 kΩ
5	ZEBRA SW	IN	ON : 0 ±0.5 V
6	VF VIDEO (X)	OUT	V = 1.0 V p-p
7	POWER EXT DC	OUT	10.5 V to 17.0 V dc, 2 A
8	(SPARE)		
9	(SPARE)		
10	SDA (VF)	OUT	Zo ≤ 500 Ω, 5 V p-p
11	VF VIDEO (G)	OUT	GND for VF VIDEO
12	EXT DC GND	—	GND for EXIT DC
13	(SPARE)		
14	DISPLAY SW	IN	ON : 4.5 ±0.5 or OPEN OFF : 0 +0.5 V
15	SCL (VF)	OUT	Zo ≤ 500 Ω, 5 V p-p
16	R-Y (VF)	OUT	V = 830 mV
17	EXT DC GND	—	GND for EXIT DC
18	B-Y (VF)	OUT	V = 830 mV
19	SYNC (VF)	OUT	V = 5 V p-p
20	LD (VF)	OUT	Zo ≤ 500 Ω, 5 V p-p


2-4-2. Connection Connector

Connections made with the connector panels during installation or service, should be made with the connectors or complete cable assemblies specified in the following list, or equivalent parts.

Connector Name	Parts No. and name of connector with cable
REMOTE (10P, FEMALE)	1-506-522-11 CONNECTOR, ROUND 10P, MALE HIROSE HR 10A-10P-10P equality or CCA-7-20.Cable assembly (optional)
VIDEO OUT (BNC)	1-560-661-11 PLUG, BNC
MONITOR OUT (BNC)	1-560-661-11 PLUG, BNC
VF (8P, FEMALE)	9-994-797-01 CABLE, VF
LENS (12P, FEMALE)	1-564-360-11 CONNECTOR, 12P, MALE HIROSE HR 10-10PA-12P equality
MIC (3P, FEMALE)	1-508-084-31 CONNECTOR, 3P, MALE CANNON XLA-3-12C equality
VF (20P, FEMALE)	1-778-661-11 CONNECTOR, 20P, MALE HIROSE HR 12-14PA-20PC equality

2-5. How to Attach of the Extension Board EX-591

When using the extension board EX-591, attach as follows.




2-6. Replacement Way of ROM (IC102)

Note

Perform "RESET" of PAGE 1 in the SERVICE menu after replacing a ROM.

1. Slide the IC socket cover in the arrow A direction until it clicks and remove the IC socket cover.
2. Replace a new ROM (IC102).
3. Place the IC socket cover with a clearance at the arrow A side. (Refer to Fig.1)
4. For attachment, press the IC socket cover in the reverse direction of arrow A until it clicks while holding the ROM.



2-7. Switch Settings on Boards

Note

Do avoid changing settings of switches designated as "For factory adjustment".


AT-114 board

S101: Camera mode setting ON or OFF

	ON	OFF
S101-1	NTSC	PAL
S101-2	DXC-D35WS	DXC-D35

S102: For factory adjustment


Use always with the setting OFF




2-8. DC-DC Converter Voltage

Voltage values can be checked as following ① to ⑫ points on MB board and MIC connector.

• MB board



• MIC connector



(EXTERNAL VIEW)

No.	CHECK POINT	VOLTAGE VALUE
①	CN117-2 pin	EXT. DC OUT
②	CN117-1 pin	EXT. DC GND
③	CN114-20 pin	+3.1 V
④	CN103-25 pin	+5.3 V
⑤	CN103-23 pin	-5 V
⑥	CN103-22 pin	+9 V


No.	CHECK POINT	VOLTAGE VALUE
⑦	CN103-21 pin	-10 V
⑧	CN103-28 pin	+6.5 V
⑨	CN103-27 pin	+16 V
⑩	CN103-26 pin	+32 V
⑪	E1 (GND)	---
⑫	MIC 2 pin/1 pin(GND)	+48 V

2-9. Recommended Replacement Parts

Parts listed below are recommended replacement parts. Optical filter unit may be turned cloudy with the lapse of time. If using a cloudy filter, the performance of the camera will not be delivered. Replace it according to necessary.

Parts made of rubber used in the unit are subject to cracks with the lapse of time. Visually check them sometimes and replace them according to necessary.

Fig No.	Description	Sony P/N	Remarks
①	PAD ASSY	A-8278-807-C	rubber
②	FILTER UNIT, OPTICAL	1-547-985-11	for DXC-D35
	FILTER UNIT, OPTICAL	1-547-985-21	for DXC-D35P
	FILTER UNIT, OPTICAL	1-758-131-11	for DXC-D35WS/D35WSP
③	RACKING, CONTROL	3-672-221-02	rubber



2-10. Attaching the 4-type or 5-type Viewfinder

An optional 4-type viewfinder (DXF-40 series) or 5-type viewfinder (DXF-50 series) can be attached in accordance with the following procedures:


Parts Required (sold separately)

Name	Sony Part No.
• Accessory shoe kit	A-8274-968-B
Shoe	3-664-218-0X
Plate spring	3-664-228-0X
Stop screw	3-664-213-0X
Screw K3 x 6 (4 pcs)	7-682-247-0X
Screw K3 x 12 (4pcs) *1	7-682-250-0X

*1 : These screws are not used.


Attaching Procedure

1. Remove a screw and remove the blind pate.
2. Tighten the shoe with four screws (K3 x 6).
3. Fix the plate spring in the shoe in the arrow direction and tighten it with the stop screw.



DXC-D35/D35WS(UC)
DXC-D35P/D35WSP(CE) V1

4. Fit the guide plate in the shoe and tighten the fixing ring.
5. Connect the VF connection cable.



2-11. Disconnecting/Connecting the Flexible Card Wire

The flexible card wires are used among the CN-1294 board and the MB board, the MB board and the TG board. Be careful not to bend these wires. This shortens the wire life.

Disconnecting

1. Turn off the power of the camera.

Type A


(between the MB board and CN-1294 board.)

2. Disconnect the flexible card wire.

Type B

(between the MB board and TG board)

2. Slide portion A in the direction of the arrow and disconnect the flexible card wire.



Connecting

Notes

- Be careful not to insert the flexible card wires obliquely.
- Check that the contact surface of the flexible card wire is not soiled with dust.

Type A

1. Insert the flexible card wire as far as it will go into connector with the contact surface of the wire faced to the board.

Type B

1. Slide portion A in the direction of the arrow and insert the flexible card wire as far as it will go into connector with the contact surface of the wire put down.
2. Slide portion A in the opposite direction of the arrow and lock.

2-12. Service Mode Operation


This unit has the BASIC menu, ADVANCE menu, SERVICE menu to be operated in the service mode, and FILE menu.

- **SERVICE mode**

To enter the service mode, set the S105 (OPE ↔ ADJ) on the SW-791 board to ADJ.

- **Menu select screen**

When the S105 on the SW-791 board is set to ADJ, the menu select screen is displayed.



- **Operating method**

Move the cursor to the menu items by the MENU/STATUS switch, select the menu by UP/ON button or DOWN/OFF button. (The menu changes in turn SERVICE ↔ BASIC ↔ ADVANCE ↔ FILE ↔ SERVICE.)

Under displaying the menu item to be operated, move the cursor to "OPEN MENU" and press the UP/ON button to go to the selected menu page.

When the page of the selected menu is displayed, the normal operation for the menu is available.

When exiting from the menu, the screen returns to the menu select screen.

Reference

The menu screen can be seen on the viewfinder or MONITOR OUT of this camera unit.

2-12-1. Service Menu

Reset items and standard values to be set.

Page	Item	Standard set value	
		UC	PAL
4	M.PKNEE1	65	65 70 *
	M.PKNEE2	120	120
	M.PKNEE3	160	160
	M.PKNEE4	215	215
	R PKNEE	128	128
	B PKNEE	128	128
9	NTSC SETUP	ON	—
		FD	—
		20H	—
	PAL	—	525
		—	FD
		—	—
10	TEST	OFF	OFF
	R-Y	ON	ON
	B-Y	ON	ON
13	GAMMA	ON	ON
	MATRIX	ON	ON
	DETAIL	ON	ON
	APERTURE	ON	ON
	FLARE	ON	ON
14	R TITLE	75	75
	G TITLE	75	75
	B TITLE	75	75
	R EDGE	0	0
	G EDGE	0	0
	B EDGE	0	0
15	M.GAMMA	132	132
	R GAMMA	±0	±0
	B GAMMA	±0	±0
	M.BLACK	2070	2075
16	WHT CLIP	255	255
	HI L.SAT	152	152
	IRIS GAIN	128	128
	IRIS MODE	100	100
	IRIS SET	144	144
	LOW LIGHT	144	160

Page	Item	Standard set value	
		UC	PAL
18	FILTER1	3200k	3200k
	FILTER2	5600k + 1/8ND	5600k + 1/8ND
	FILTER3	5600k	5600k
	FILTER4	5600k + 1/64ND	5600k + 1/64ND
19	DIAG ERROR RESET	—	—
	MEMORY BACKUP	—	—
20	Self-diagnosis result display1	1	1
21	Self-diagnosis result display2	1	1
22	Self-diagnosis result display3	1	1
26	OPTION1	OFF	OFF
	OPTION2	OFF	OFF

* : for DXC-D35WSP

• **Page 1 RESET**
(For DXC-D35/D35WS)

```

→PAGE1 (NEXT→▼ PREV→▲)
RESET
  (YES→▲)
DEST : UC
ROM VER : ***

EXIT MENU (YES→▲)

```

Adjusting values such as the electronic volume control of each board except the values differ in every unit can be restored to their standard setting values.

Move the cursor to "DEST" position, select "UC," and move the cursor to "RESET," then press UP/ON button twice.

(For DXC-D35P/D35WSP)

```

→PAGE1 (NEXT→▼ PREV→▲)
RESET
  (YES→▲)
ROM VER : ***

EXIT MENU (YES→▲)

```

• **Page 2 Shading Correction**

```

→PAGE2 (NEXT→▼ PREV→▲)
EXTENDER  OFF
AUTO SHAD
  (YES→▲)
R W. SHAD : 128
G W. SHAD : 128
B W. SHAD : 128

EXIT MENU (YES→▲)

```

EXTENDER Current LENS EXTENDER status display
 AUTO SHAD Performing of AUTO SHADING correction
 R W.SHAD/G W.SHAD/B W.SHAD
 White shading correction of V
 Standard (correct.on 0) = 128

• **Page 3 Flare Adjustment**

```

→PAGE3 (NEXT→▼ PREV→▲)
R FLARE : 0
G FLARE : 0
B FLARE : 0

EXIT MENU (YES→▲)

```

R FLARE Rch flare correction (0 = no correction) amount adjustment
 G FLARE Gch flare correction (0 = no correction) amount adjustment
 B FLARE Bch flare correction (0 = no correction) amount adjustment

• Page 4 Pre Knee Setting

→PAGE4 (NEXT→▼ PREV→▲)

M.PKNEE1 : 65
M.PKNEE2 : 120
M.PKNEE3 : 160
M.PKNEE4 : 215
R PKNEE : 128
B PKNEE : 128

EXIT MENU (YES→▲)

M.PKNEE1 Usual master pre-knee point adjustment
M.PKNEE2 Master pre-knee point in GAIN -3 dB adjustment
M.PKNEE3 Master pre-knee point in flame read out mode adjustment
M.PKNEE4 Master pre-knee point in GAIN -3dB & flame read out mode adjustment

P PKNEE Fine adjustment for the R channel's pre-knee point

B PKNEE Fine adjustment for the B channel's pre-knee point

• Page 5 Camera COMPONENT Level Adjustment

→PAGE5 (NEXT→▼ PREV→▲)

W Y LEV : 120
W R-Y LEV : 100
W B-Y LEV : 100
Y LEV : 120
R-Y LEV : 111
B-Y LEV : 100
SYNC LEV : 80
SETUP LEV : 135
EXIT MENU (YES→▲)

WY LEV 16:9 Y level adjustment*

W R-Y LEV 16:9 R-Y level adjustment*

W B-Y LEV 16:9 B-Y level adjustment*

Y LEV 4:3 Y level adjustment

R-Y LEV 4:3 R-Y level adjustment

B-Y LEV 4:3 B-Y level adjustment

SYNC LEV SYNC level adjustment

SETUP LEV SETUP level adjustment

(NTSC model only adjustable when setup is on.)

* : Adjustable only for DXC-D35WS/D35WSP

• Page 6 Camera CLAMP Level Adjustment

→PAGE6 (NEXT→▼ PREV→▲)

Y CLP : 128
R-Y CLP : 120
B-Y CLP : 120

EXIT MENU (YES→▲)

Y CLP Y clamp level adjustment

R-Y CLP R-Y clamp level adjustment

B-Y CLP B-Y clamp level adjustment

• Page 7 Chroma/VF Adjustment

→PAGE7 (NEXT→▼ PREV→▲)

R-Y C/B : 110
R-Y BST : 0
B-Y C/B : 110
B-Y BST : 75
VF SYNC : 170
VF BLKG : 135

EXIT MENU (YES→▲)

R-Y C/B R-Y carrier balance adjustment

R-Y BST R-Y burst level adjustment

B-Y C/B B-Y carrier balance adjustment

B-Y BST B-Y burst level adjustment

VF SYNC Viewfinder video sync level adjustment

VF BLKG Viewfinder video blanking level adjustment

• Page 8 Chroma SC Adjustment

→PAGE8 (NEXT→▼ PREV→▲)
 SC FREQ : 2550
 SC-H : 450
 EXIT MENU (YES→▲)

SC FREQ SC frequency adjustment

SC-H SC-H phase adjustment

• Page 9 Various Setting 1 (For DXC-D35/D35WS)

→PAGE9 (NEXT→▼ PREV→▲)
 SETUP : OFF
 READ OUT : FD
 V BLKG : 20H
 EXIT MENU (YES→▲)

SETUP ON/OFF control of setup

READ OUT FD (Field): CCD switches to Field read mode

FM (Frame): CCD switches to Frame read mode

V BLKG V blanking width setting (19/20/21H)

Reference

In frame read out, higher vertical resolution can be obtained, however, in such a case image lag is increasing.

If shutter function is on in frame read out, sensitivity drops in half against the normal.

(For DXC-D35P/D35WSP)

→PAGE9 (NEXT→▼ PREV→▲)
 SETUP : OFF
 READ OUT : FD
 V BLKG : 20H
 EXIT MENU (YES→▲)

COMP LEV 525/700 selection of color difference output
(pin 26)

READ OUT FD (Field): CCD switches to Field read mode

FM (Frame): CCD switches to Frame read mode

• Page 10 TEST MODE

→PAGE10 (NEXT→▼ PREV→▲)
 TEST : OFF
 R-Y : ON
 B-Y : ON
 EXIT MENU (YES→▲)

TEST TEST OFF: TEST SAW

TEST: 1 Displays 100 % TEST SAW.

TEST: 2 Displays 226 % TEST SAW.

TEST: 3 Displays 226 % TEST SAW
in the lower side of screen.

R-Y ON/OFF control of R-Y output

B-Y ON/OFF control of B-Y output

• Page 11 CCD BLOCK No. Information

```

→PAGE11 (NEXT→▼ PREV→▲)

HEAD 1 : G
HEAD 2 : V
HEAD 3 : 0
HEAD 4 : 0
HEAD 5 : 0
HEAD 6 : 1
HEAD 7 : 6

EXIT MENU (YES→▲)

```

HEAD1 to 7 CCD block number

Note

Be sure to input the CCD block number which is shown on the side of CCD unit after the replacement of TG board or the EEPROM (IC1) on the TG board.

• Page 12 Sub-Voltage Information

```

→PAGE12 (NEXT→▼ PREV→▲)

R RG : 90
G RG : 90
B RG : 90
R SUB : 128
G SUB : 128
B SUB : 128
TPC : ±0

EXIT MENU (YES→▲)

```

R RG	R RG-voltage setting
G RG	G RG-voltage setting
B RG	B RG-voltage setting
R SUB	R channel sub-voltage setting
G SUB	G channel sub-voltage setting
B SUB	B channel sub-voltage setting
TPC	NR temperature compensation constant setting

Note

Values shown on the screen depend on each CCD unit. Never change the value.

• Page 13 Various Setting 2

```

→PAGE13 (NEXT→▼ PREV→▲)

GAMMA : ON
MATRIX : ON
DETAIL : ON
APERTURE : ON
FLARE : ON

EXIT MENU (YES→▲)

```

GAMMA	ON/OFF control of GAMMA
MATRIX	ON/OFF control of MATRIX
DETAIL	ON/OFF control of DETAIL
APERTURE	ON/OFF control of APERTURE
FLARE	ON/OFF control of FLARE correction

• Page 14 TITLE Color Setting

```

→PAGE14 (NEXT→▼ PREV→▲)

R TITLE : 75
G TITLE : 75
B TITLE : 75
R EDGE : 0
G EDGE : 0
B EDGE : 0
ABC123

EXIT MENU (YES→▲)

```

When displaying the title in the video signal, title color can be set manually. Besides, edge color of title character can be set manually.

R TITLE	Title's R level (0/25/50/75)
G TITLE	Title's G level (0/25/50/75)
B TITLE	Title's B level (0/25/50/75)
R EDGE	Title edge's R level (0/25/50/75)
G EDGE	Title edge's G level (0/25/50/75)
B EDGE	Title edge's B level (0/25/50/75)
ABC123	Indication for checking actual title color

• Page 15 Various Setting 3

```

→PAGE15 (NEXT→▼ PREV→▲)

M.GAMMA : 132
R.GAMMA : ± 0
B.GAMMA : ± 0
M.BLACK : 2083

EXIT MENU (YES→▲)

```

M.GAMMA Standard value setting of master GAMMA
 R.GAMMA R channel's GAMMA offset setting
 B.GAMMA B channel's GAMMA offset setting
 M.BLACK Standard value setting of master BLACK

• Page 16 CLIP/IRIS Related Setting

```

→PAGE16 (NEXT→▼ PREV→▲)

WHT CLIP : 255
HI L.SAT : 152
IRIS GAIN : 128
IRIS MODE : 100
IRIS SET : 144
LOW LIGHT : 152

EXIT MENU (YES→▲)

```

WHT CLIP Standard value setting of WHITE CLIP level
 HI L.SAT Setting of saturation in the high-light portion
 IRIS GAIN Setting of auto iris following speed
 IRIS MODE Setting of auto iris's peak and average values.
 IRIS SET Setting of the target value of auto iris
 LOW LIGHT Setting of LOW LIGHT warning indication level
 * For DXC-D35/D35WS : 152
 For DXC-D35P/D35WSP : 160

• Page 17 Color Temperature Calculation Reference Setting

```

→PAGE17 (NEXT→▼ PREV→▲)

COLOR TEMP CAL.
  (YES→PUSH)
  R : 128
  B : 128
  MIC ADJ : 130

EXIT MENU (YES→▲)

```

COLOR TEMP CAL. Captures the reference value of color temperature indication

R R channel's color temperature indication ;

- Reference value setting
- Result of capturing the reference value

B B channel's color temperature indication ;

- Reference value setting
- Result of capturing the reference value

Notes

In COLOR TEMP CAL., it captures the color temperature calculation reference value during operating of White Balance auto adjustment. Normally, it is not necessary to perform this adjustment.

If the color temperature value, which is indicated on the screen, differs from an actual value, perform CCD OUT level adjustment and etc. and to capture the reference value as follows:

1. Shoot the pattern (color temperature = 3200 K).
2. Set the WHT BAL switch to A or B, and perform Auto White adjustment.
3. Move the cursor on the COLOR TEMP CAL. position and push the UP /ON button.

MIC ADJ Setting of musical note mark indication level

• Page 18 FILTER Display Setting

→PAGE18 (NEXT→▼ PREV→▲)

FILTER1	: 3200
FILTER2	: 5600+1/8ND
FILTER3	: 5600
FILTER4	: 5600+1/64ND

EXIT MENU (YES→▲)

FILTER 1 to 4

Make this setting in accordance with a kind of filter attached.

Note

When changing the filter, be sure to make a set.

• Page 19 Self Diagnosis 1

→PAGE19 (NEXT→▼ PREV→▲)

DIAG ERROR RESET
(YES→▲)

MEMORY BACKUP
(YES→▲)

EXIT MENU (YES→▲)

DIAG ERROR RESET

This item is used for erasing an error check results and a history of error items.

MEMORY BACKUP

This item is used when back up the EEPROMs data on the TG, IF, and ES boards to EEPROM on the MB board.

Note

Backup is needed when the TG, IF, or ES board has been replaced.

Reference

If there is a communication error between the TG, IF, or ES board's EEPROM and microcomputer when the power is turned on, the backed up data in EEPROM on the MB board is used.

The "DIAG ERROR RESET" and "MEMORY BACKUP" will be also carried out when the RESET in Service Menu Page 1 is executed.

• Page 20 Selfdiagnosis 2

```

PAGE20 (NEXT→▼ PREV→▲)

ERROR DISP 1/3
→DISP SELECT : 1
PP-PMPD : 000H
PR-PMPD1 : 000H
PR-PMPD2 : 000H
PR-G2 : 000H
PR-R2 : 000H

EXIT MENU (YES→▲)

```

DISP SELECT

The contents of the defective item display are switched.

- 1: The result of latest error check is displayed.
- 2: This selfdiagnosis is automatically carried out, and the defective items diagnosed in the past are displayed.

PP-PMPD

The details of check result for the synchronization signal input and the internal RAM in PP LSI are displayed.

800H: The internal RAM of PP LSI is abnormal.

002H: The input HD signal (PR board IC405, pin 102) to the PP LSI is abnormal.

001H: The input VD signal (PR board IC405, pin 101) to the PP LSI is abnormal.

PR-PMPD1

The details of check result for the synchronization signal input in RP LSI are displayed.

002H: The input HD signal (PR board IC411, pin74) to the PR LSI is abnormal.

001H: The input VD signal (PR board IC411, pin73) to the PR LSI is abnormal.

PR-PMPD2

The details of check result for the internal RAM in PR LSI are displayed.

800H: The internal RAM of PR LSI is abnormal.

PR-G2

This display item is not used.

PR-R2

This display item is not used.

Reference

When the plurality of abnormality is occurs, the hexadecimal numbers of three digits are displayed for indicating the total value of each error codes.

Example : When both HD and VD signals input to the PP LSI are abnormal, the PP-PMPD displays is 003H.

• Page 21 Selfdiagnosis 3

```

PAGE21 (NEXT→▼ PREV→▲)

ERROR DISP 2/3
→DISP SELECT : 1
PR-G1 : 000H
PR-R1 : 000H
PR-G0 : 000H
PR-R0 : 000H
PR-B1 : 000H

EXIT MENU (YES→▲)

```

PR-G1

This display item is not used.

PR-R1

This display item is not used.

PR-G0

This display item is not used.

PR-R0

This display item is not used.

PR-B1

This display item is not used.

• Page 22 Selfdiagnosis 4

```

PAGE22 (NEXT→▼ PREV→▲)
ERROR DISP 3/3
→DISP SELECT : 1
RC- PMPD: 000H
RC- CY : 000H
RC- CCR : 000H
RC- CCB : 000H
DSP COM.: 000H
MEMORY : 000H
EXIT MENU (YES→▲)
    
```

RC-PMPD

The details of check result for synchronization signal input and the internal RAM in RC LSI are displayed.

800H: The internal RAM of RC LSI is abnormal.

004H: The input CF signal (IF board IC520, pin63) to the RC LSI is abnormal.

002H: The input HD signal (IF board IC520, pin64) to the RC LSI is abnormal.

001H: The input VD signal (IF board IC520, pin65) to the RC LSI is abnormal.

RC-CY

The details of check result for the connection regarding the Y signal between PR LSI and RC LSI are displayed.

400H: The connection between PR board IC411 pin94 and IF board IC520 pin97 is abnormal. (The No.10 of Y signal)

200H: The connection between PR board IC411 pin93 and IF board IC520 pin98 is abnormal. (The No.9 of Y signal)

100H: The connection between PR board IC411 pin92 and IF board IC520 pin99 is abnormal. (The No.8 of Y signal)

080H: The connection between PR board IC411 pin91 and IF board IC520 pin100 is abnormal. (The No.7 of Y signal)

040H: The connection between PR board IC411 pin90 and IF board IC520 pin101 is abnormal. (The No.6 of Y signal)

020H: The connection between PR board IC411 pin89 and IF board IC520 pin103 is abnormal. (The No.5 of Y signal)

010H: The connection between PR board IC411 pin88 and IF board IC520 pin104 is abnormal. (The No.4 of Y signal)

008H: The connection between PR board IC411 pin86 and IF board IC520 pin105 is abnormal. (The No.3 of Y signal)

004H: The connection between PR board IC411 pin85 and IF board IC520 pin106 is abnormal. (The No.2 of Y signal)

002H: The connection between PR board IC411 pin84 and IF board IC520 pin107 is abnormal. (The No.1 of Y signal)

001H*: The connection between PR board IC411 pin83 and IF board IC520 pin108 is abnormal. (The No.0 of Y signal)

*: DXC-D35WS/D35WSP do not have this function.

RC-CCR (DXC-D35WS/D35WSP do not have this function.)

The details of check result for the connection regarding the CR signal between PR LSI and RC LSI are displayed.

- 400H: The connection between PR board IC411 pin108 and IF board IC520 pin84 is abnormal. (The No.10 of CR signal)
- 200H: The connection between PR board IC411 pin107 and IF board IC520 pin85 is abnormal. (The No.9 of CR signal)
- 100H: The connection between PR board IC411 pin106 and IF board IC520 pin86 is abnormal. (The No.8 of CR signal)
- 080H: The connection between PR board IC411 pin104 and IF board IC520 pin87 is abnormal. (The No.7 of CR signal)
- 040H: The connection between PR board IC411 pin103 and IF board IC520 pin88 is abnormal. (The No.6 of CR signal)
- 020H: The connection between PR board IC411 pin102 and IF board IC520 pin89 is abnormal. (The No.5 of CR signal)
- 010H: The connection between PR board IC411 pin101 and IF board IC520 pin92 is abnormal. (The No.4 of CR signal)
- 008H: The connection between PR board IC411 pin100 and IF board IC520 pin93 is abnormal. (The No.3 of CR signal)
- 004H: The connection between PR board IC411 pin99 and IF board IC520 pin94 is abnormal. (The No.2 of CR signal)
- 002H: The connection between PR board IC411 pin98 and IF board IC520 pin95 is abnormal. (The No.1 of CR signal)
- 001H: The connection between PR board IC411 pin95 and IF board IC520 pin96 is abnormal. (The No.0 of CR signal)

RC-CCB (DXC-D35WS/D35WSP do not have this function.)

The details of check result for the connection regarding the CB signal between PR LSI and RC LSI are displayed.

- 400H: The connection between PR board IC411 pin121 and IF board IC520 pin70 is abnormal. (The No.10 of CB signal)
- 200H: The connection between PR board IC411 pin120 and IF board IC520 pin71 is abnormal. (The No.9 of CB signal)
- 100H: The connection between PR board IC411 pin119 and IF board IC520 pin72 is abnormal. (The No.8 of CB signal)
- 080H: The connection between PR board IC411 pin118 and IF board IC520 pin75 is abnormal. (The No.7 of CB signal)
- 040H: The connection between PR board IC411 pin117 and IF board IC520 pin76 is abnormal. (The No.6 of CB signal)
- 020H: The connection between PR board IC411 pin116 and IF board IC520 pin77 is abnormal. (The No.5 of CB signal)
- 010H: The connection between PR board IC411 pin115 and IF board IC520 pin78 is abnormal. (The No.4 of CB signal)
- 008H: The connection between PR board IC411 pin112 and IF board IC520 pin79 is abnormal. (The No.3 of CB signal)
- 004H: The connection between PR board IC411 pin111 and IF board IC520 pin80 is abnormal. (The No.2 of CB signal)
- 002H: The connection between PR board IC411 pin110 and IF board IC520 pin82 is abnormal. (The No.1 of CB signal)
- 001H: The connection between PR board IC411 pin109 and IF board IC520 pin83 is abnormal. (The No.0 of CB signal)

Reference

If the input of synchronization signal to the PR LSI or RC LSI is abnormal, the connection check between PR LSI and RC LSI also detects the abnormality.

RC LSI relation check is carried out only when the digital output of DXC-D35/D35P is used for connecting DSR-1/1P and so on.

DSP COM

The details of check result for the communication between each LSI and microcomputer are displayed.

004H: The communication between RC LSI and microcomputer is abnormal. (IF IC520)

002H: The communication between PR LSI and microcomputer is abnormal. (PR IC411)

001H: The communication between PP LSI and microcomputer is abnormal. (PR IC405)

Reference

The RC LSI communicates with the microcomputer by six pins of pin26(CS), pin25(SCK), pin24(SDA0), pin23(SDA1), pin22(SDA2) and pin21(SDA3).

The PR LSI communicates with the microcomputer by six pins of pin58(CS), pin57(SCK), pin56(SDA0), pin55(SDA1), pin54(SDA2) and pin53(SDA3).

The PP LSI communicates with the microcomputer by six pins of pin41(CS), pin40(SCK), pin39(SDA0), pin38(SDA1), pin37(SDA2) and pin36(SDA3). If the communication between LSI and the microcomputer is abnormal, the abnormality of other item may be detected at the same time.

MEMORY

The details of check result for the communication between each EEPROM and microcomputer are displayed.

080H: The communication between EEPROM of ES and microcomputer is abnormal.

040H: The communication between EEPROM of IF and microcomputer is abnormal.

020H: The communication between EEPROM of TG and microcomputer is abnormal.

010H: The communication between EEPROM of MB and microcomputer is abnormal.

Reference

The corresponding display for the data of each EEPROM on the service menu becomes a blank column, when the EEPROM on the TG, IF, ES and MB boards is abnormal.

• Page 23 Current Status Display

```

→PAGE23 (NEXT→▼ PREV→▲)

POWER      : 13.0V
TIS        : 250h
R GAIN     : 800h
B GAIN     : 800h
IRIS POS   : 800h
KWC        : 800h

EXIT MENU  (YES→▲)

```

Information for production.

• Page 24 TG ROM Operation

```

→PAGE24 (NEXT→▼ PREV→▲)

TG ROM

EXIT MENU  (YES→▲)

```

Not in use

• Page 25 Carrier Adjustment When DPR (Dual Pixel Readout) is on.

```

→PAGE25 (NEXT→▼ PREV→▲)

R D.DARK   : 128
G D.DARK   : 128
B D.DARK   : 128

EXIT MENU  (YES→▲)

```

R D.DARK	R Carrier balance adjustment at DPR ON
G D.DARK	G Carrier balance adjustment at DPR ON
B D.DARK	B Carrier balance adjustment at DPR ON

• Page 26 Option

```

→PAGE26 (NEXT→▼ PREV→▲)

OPTION1    : OFF
OPTION2    : OFF
          :
EXIT MENU  (YES→▲)

```

Normally this item setting is OFF.

2-12-2. File Menu

DXC-D35/D35P

Reset items and standard values to be set.

ITEM	Standard set value					
	NO.1	NO.2	NO.3	NO.4	NO.5	NO.6 to 8
ITEM	STD	HISAT	FL	FILMLIKE	SVHS/VHS	USER1 to 3
M.BLACK	±0	±0	±0	±0	±0	±0
STRETCH	±0	±0	±0	±0	±0	±0
M.GAMMA	±0	±0	±0	-33	±0	±0
DTL LEV	±0	+10	±0	-99	-40	±0
V DTL LEV	±0	±0	±0	±0	-10	±0
DTL FREQ	M	M	M	M	L	M
SAT	±0	±0	±0	±0	-5	±0
HUE	±0	±0	±0	±0	±0	±0
SKIN SAT	±0	±0	±0	±0	±0	±0
SKIN HUE	±0	±0	±0	±0	±0	±0
M.KNEE P	310	310	310	310	310	310
M.KNEE S	90	90	90	90	90	90
GAMMA TBL	B	B	B	A	B	B
COMB	OFF	OFF	OFF	OFF	OFF	OFF
R-G LEV	NTSC	65	80	99	12	65
	PAL	38	50	50	12	38
R-B LEV	NTSC	12	20	-15	9	12
	PAL	10	24	10	9	10
G-R LEV	NTSC	14	23	25	-6	14
	PAL	6	10	14	-6	6
G-B LEV	NTSC	32	46	-9	37	32
	PAL	15	30	12	37	15
B-R LEV	NTSC	10	11	0	-8	10
	PAL	6	10	10	-8	6
B-G LEV	NTSC	3	5	0	24	3
	PAL	7	12	-2	24	7
T-G WIDTH	40	40	40	40	40	40
R-B WIDTH	20	20	20	20	20	20
G-R WIDTH	20	20	20	20	20	20
G-B WIDTH	-40	-40	-40	-40	-40	-40
B-R WIDTH	-20	-20	-20	-20	-20	-20
B-G WIDTH	-20	-20	-20	-20	-20	-20
LEVEL DEP	52	52	52	52	52	52
V DTL LIM	20	20	20	20	20	20
CRISP	10	10	10	10	10	10
APERTURE	128	128	128	63	35	128
AFT DTL	10	10	10	10	40	10

	Standard set value					
	NO.1	NO.2	NO.3	NO.4	NO.5	NO.6 to 8
KNEE APT	24	24	24	63	24	24
HIGH DTL	63	63	63	63	63	63
CCS LEV	5	5	5	5	5	5
STRP1	20	20	20	20	20	20
STRP2	45	45	45	45	45	45
PRSP1	8	8	8	8	8	8
PRSP2	63	63	63	63	63	63

DXC-D35WS/D35WSP

Reset items and standard values to be set.

		Standard set value					
		NO.1	NO.2	NO.3	NO.4	NO.5	NO.6 to 8
ITEM		STD	HISAT	FL	FILMLIKE	SVHS/VHS	USER1 to 3
M.BLACK		±0	±0	±0	±0	±0	±0
STRETCH		±0	±0	±0	±0	±0	±0
M.GAMMA		±0	±0	±0	-33	±0	±0
DTL LEV		±0	10	±0	-80	-50	±0
V DTL LEV		±0	±0	±0	±0	-10	±0
DTL FREQ		M	M	M	M	L	M
SAT		±0	±0	±0	±0	-5	±0
HUE		±0	±0	±0	±0	±0	±0
SKIN SAT		±0	±0	±0	±0	±0	±0
SKIN HUE		±0	±0	±0	±0	±0	±0
M.KNEE P		310	310	310	310	310	310
M.KNEE S		90	90	90	90	90	90
GAMMA TBL		B	B	B	A	B	B
COMB		OFF	OFF	OFF	OFF	OFF	OFF
R-G LEV	NTSC	65	80	99	12	65	65
	PAL	38	50	50	12	38	38
R-B LEV	NTSC	12	20	-15	9	12	12
	PAL	10	24	10	9	10	10
G-R LEV	NTSC	14	23	25	-6	14	14
	PAL	6	10	14	-6	6	6
G-B LEV	NTSC	32	46	-9	37	32	32
	PAL	15	30	12	37	15	15
B-R LEV	NTSC	10	11	0	-8	10	10
	PAL	6	10	10	-8	6	6
B-G LEV	NTSC	3	5	0	24	3	3
	PAL	7	12	-2	24	7	7
R-G WIDTH		40	40	40	40	40	40
R-B WIDTH		20	20	20	20	20	20
G-R WIDTH		20	20	20	20	20	20
G-B WIDTH		-40	-40	-40	-40	-40	-40
B-R WIDTH		-20	-20	-20	-20	-20	-20
B-G WIDTH		-20	-20	-20	-20	-20	-20
LEVEL DEP		52	52	52	52	52	52
V DTL LIM		20	20	20	20	20	20
CRISP		10	10	10	10	10	10
APERTURE		145	145	145	128	128	145
AFT DTL		10	10	10	10	40	10

	Standard set value					
	NO.1	NO.2	NO.3	NO.4	NO.5	NO.6 to 8
KNEE APT	24	24	24	63	24	24
HIGH DTL	63	63	63	63	63	63
CCS LEV	5	5	5	5	5	5
STRP1	20	20	20	20	20	20
STRP2	45	45	45	45	45	45
PRSP1	8	8	8	8	8	8
PRSP2	63	63	63	63	63	63

• **Page 1 All Reset**
(For DXC-D35/D35WS)

→ PAGE1 (NEXT→▼ PREV→▲)

ALL RESET
(YES→▲)
DEST: UC

EXIT MENU (YES→▲)

Each item value in all FILE can be restored to their standard setting (factory setting).

(For DXC-D35P/D35WSP)

→ PAGE1 (NEXT→▼ PREV→▲)

ALL RESET
(YES→▲)

EXIT MENU (YES→▲)

• **Page 2 File Name Change/File Reset**

→ PAGE 2 (NEXT→▼ PREV→▲)

FILE NO. : 1
FILE NAME :

(STD)
FILE RESET
(YES→▲)

EXIT MENU (YES→▲)

FILE NO.	File No. of operation item
FILE NAME	File name of operation item file
FILE RESET	Performing of FILE RESET

• **Page 3 File Recall**

→ PAGE3 (NEXT→▼ PREV→▲)

FILE RECALL
FILE : *HISAT
SELECT FILE
STD
CHG FILE
(YES→▲)

EXIT MENU (YES→▲)

FILE	File name which is recalled
SELECT FILE	Select file to be recalled
CHG FILE	Performing of FILE RECALL

• Page 4 File Basic Setting

```

→ PAGE4 (NEXT→▼ PREV→▲)

M.BLACK  : ± 0
STRETCH  : ± 0
M.GAMMA  : ± 0
DTL LEV  : ± 0
V DTL LEV : -10
DTL FREQ  :  M

EXIT MENU (YES→▲)

```

M.BLACK Master black level setting
 STRETCH Black stretch level setting
 M.GAMMA Master GAMMA level setting
 DTL LEV Detail level setting
 V DTL LEV V detail level setting
 DTL FREQ Detail center frequency setting

FILE DATA selected with SET UP switch is displayed on the PAGE 4 to 11. When data value is changed, the data in the FILE DATA selected with SET UP switch is also rewritten.

When the SET UP switch is switched while any of PAGE 4 to 11 is displayed, the display is changed in response to the SET UP switch position.

• Page 5 File HUE Setting

```

→ PAGE5 (NEXT→▼ PREV→▲)

SAT      : ± 0
HUE      : ± 0
SKIN SAT : ± 0
SKIN HUE : ± 0

EXIT MENU (YES→▲)

```

SAT Chroma setting
 HUE HUE setting
 SKIN SAT Chroma setting for the skin tone area
 SKIN HUE HUE setting for the skin tone area

• Page 6 File Knee /GAMMA Setting

```

→ PAGE6 (NEXT→▼ PREV→▲)

M.KNEE P : 300
M.KNEE S : 90
GAMMA TBL : B
COMB      : OFF

EXIT MENU (YES→▲)

```

M.KNEE P Standard value setting of master knee point
 M.KNEE S Standard value setting of master knee slope
 GAMMA TBL Selection of GAMMA table A/B
 COMB A : Rising gain 3.5-fold
 B : Rising gain 4.0-fold
 COMB Filter selection
 (OFF/GR/R/G)

• Page 7 File Matrix Center Value Setting

```

→ PAGE7 (NEXT→▼ PREV→▲)

R-G LEV : 38
R-B LEV : 10
G-R LEV : 6
G-B LEV : 15
B-R LEV : 6
B-G LEV : 7

EXIT MENU (YES→▲)

```

R-G LEV R-G coefficient center value setting
 R-B LEV R-B coefficient center value setting
 G-R LEV G-R coefficient center value setting
 G-B LEV G-B coefficient center value setting
 B-R LEV B-R coefficient center value setting
 B-G LEV B-G coefficient center value setting

• **Page 8 File Matrix Variable Width Setting**

→ PAGE8 (NEXT→▼ PREV→▲)

R-G WIDTH	:	40
R-B WIDTH	:	20
G-R WIDTH	:	40
G-B WIDTH	:	-40
B-R WIDTH	:	-20
B-G WIDTH	:	-20

EXIT MENU (YES→▲)

R-G WIDTH	HUE variable width of R-G coefficient setting
R-B WIDTH	HUE variable width of R-B coefficient setting
G-R WIDTH	HUE variable width of G-R coefficient setting
G-B WIDTH	HUE variable width of G-B coefficient setting
B-R WIDTH	HUE variable width of B-R coefficient setting
B-G WIDTH	HUE variable width of B-G coefficient setting

• **Page 9 File Core Related Setting**

→ PAGE9 (NEXT→▼ PREV→▲)

LEVEL DEP	:	52
V DTL LIM	:	20
CRISP	:	6

EXIT MENU (YES→▲)

LEVEL DEP	Level depend level setting
V DTL LIM	V detail compression setting
CRISP	CRISPENING level setting

• **Page 10 File Detail Related Setting**

→ PAGE10 (NEXT→▼ PREV→▲)

APERTURE	:	145
AFT DTL	:	25
KNEE APT	:	48
HIGH DTL	:	63
CCS LEV	:	5

EXIT MENU (YES→▲)

APERTURE	Aperture level setting
AFT DTL	Setting of the detail amount to be added after the gamma circuit
KNEE APT	Setting of the detail amount higher than the knee point
HIGH DTL	Setting of the detail amount in the high light area
CCS LEV	Cross color supress level setting

• **Page 11 File Stretch Setting**

→ PAGE11 (NEXT→▼ PREV→▲)

STRP1	:	20
STRP2	:	45
PRSP1	:	8
PRSP2	:	63

EXIT MENU (YES→▲)

STRP1	BLACK STRETCH Point1 setting
STRP2	BLACK STRETCH Point2 setting
PRSP1	BLACK COMPRESS Point1 setting
PRSP2	BLACK COMPRESS Point2 setting

• Page 12 File Store

→ PAGE12 (NEXT→▼ PREV→▲)
 FILE STORE
 FILE :*HISAT
 DESTINATION FILE
 USER1
 STORE FILE
 (YES→▲)

 EXIT MENU (YES→▲)

FILE

File name to be recalled

DESTINATION FILE

Selection of FILE STORE destination

STORE FILE

Performing of FILE STORE





Section 3 Electrical Alignment


3-1. Preparation

3-1-2. Connection

3-1-1. Equipment Required

- Digital voltmeter
- Oscilloscope (100 MHz or more)
- Vectorscope
- Waveform monitor
- B/W monitor (Sony PVM-91/122 or equivalent)
- Color monitor (Sony PVM-1320 or equivalent)
- AC Adaptor (Sony CMA-8/8A/8CE/8ACE)
- Camera Adaptor (Sony CA-537/537P)
- Frequency counter
- SC-H Phase Equipment
- Tripod Adaptor VCT-U14

Pattern box PTB-500	extension board EX-490
Sony part number: J-6029-140-B • Light source for test chart 	Sony part number: J-6275-690-A 
Grayscale chart (4 : 3)	Grayscale chart (16 : 9)
(Translucent type) Sony part number: J-6026-130-B (Reflection type) Commercially available: Refer to Section 3-1-5. 	(Translucent type) Sony part number: J-6394-080-A 



3-1-3. Setting Before Adjustment

• Side Panel

GAIN switch:	LOW (0 dB)
OUTPUT/DL/DCC + switch:	CAM/DCC +
W. BAL switch:	PRESET
ZEBRA switch:	OFF
HYPER GAIN switch:	OFF
SET UP switch:	STD
EZ MODE button:	OFF
SKIN DTL switch:	OFF
ATW button:	OFF

• Front Panel

FILTER control:	1 (3200 K)
SHUTTER switch:	OFF

• Camera Adaptor

S1 switch (IF-313 board):	AUTO (Center position)
---------------------------	------------------------

• Viewfinder


DISPLAY switch:	ON
-----------------	----

• Lens


IRIS:	M (Manual)
ZOOM:	M (Manual)

3-1-4. Notes on Adjustment

- Before adjustment, be sure to perform 10-minute warm-up.
- When using the SERVICE menu and FILE menu, refer to "2-12. Service Mode Operation".
- To shoot the chart frame covering fully the underscanned monitor frame, perform the following procedures.
 1. Set the camera to the best focus, then adjust the lens zoom and the orientation of the camera.
 2. Adjust the chart frame to align with the underscanned monitor frame as shown in the figure below.



In case of the Grayscale chart:



(underscanned monitor screen)

- When replacing the CCD unit, be sure to perform the following adjustment items.
 - 3-3-13. Shading Adjustment
 - 3-3-14. Flare Adjustment
- If the waveform to be measured is blurred and the amplitude level is not clear, set the FILTER switch on the waveform monitor to "LUM" or "LPASS" mode.

3-1-5. Maintaining the Grayscale Chart

For the CCD OUT level adjustment and the Gamma correction adjustment, using an 89.9 %-reflective grayscale chart is preferable.

If a reflective chart is not available, use a well-maintained pattern box and a transparent grayscale chart for adjustment.

Before beginning adjustment, set the illumination of the light source (or the luminous intensity on the chart surface) properly proceeding as follows and set the color temperature to 3200 K exactly by adjusting light.

Information on the reflective grayscale chart

Recommended chart

The reflective grayscale chart is commercially available.

Recommended chart: Reflective grayscale chart (with a special case)
MURAKAMI COLOR RESEARCH LABORATORY GS-3
or equivalent

Supplier: MURAKAMI COLOR RESEARCH LABORATORY
Address: 3-11-3, Kachidoki, Chuo-ku, Tokyo, JAPAN
Postcode 104-0054
Phone: 81-3-3532-3011
Fax: 81-3-3532-2056

Handling precautions

- Do not touch the chart's surface.
- Do not subject the surface to dirt, scratches or prolonged exposure to sunlight.
- Protect the chart from excess moisture and harmful gas.
- Avoid resting articles against the case.
- Open the case and dry the chart more an hour for a month in no use long period.

Replacement period when the chart is used as the reference

The reflective grayscale chart should be replaced every two years if it used as the reference. Because the chart deteriorates with time and proper adjustment cannot be achieved.

Replacement period varies according to storage conditions of the chart.


Setting illumination (when the reflective chart is used)

Equipment: Illuminance meter (Calibrated)

1. Turn on the light source and warm up for about 30 minutes.
2. Place the illuminance meter on the chart surface.
Adjust the position and angle of the light source so that the whole surface of the chart is evenly 2000 lx.

Note

Light the chart from almost the same direction and height as the camera to shoot the chart.




Setting luminous intensity (when the transparent chart is used)

Equipment: Luminance meter (Minolta LS-110 or equivalent. Calibrated.)

1. Light the pattern box and warm up for about 30 minutes.
2. Place the pattern box where the chart is not exposed to light, such as a darkroom.
(Or cover the pattern box with a cover whose inside is painted in black.)
3. Place the luminance meter facing straight to the chart at a distance of 1 m from it.
4. Adjust the luminance control of the pattern box so that the white portion in the center of the chart is $573 \pm 6 \text{ cd/m}^2$.

Note


This corresponds to the luminous intensity on the 89.9 %-reflective chart at 2000 lx.




3-2. Before Adjustment

3-2-1. Color Bar Signal Confirmation

Equipment: Waveform monitor, Vectorscope
Preparation: OUTPUT/DL/DCC+ switch: BARS
Test point: VIDEO OUT connector
Specification:



- Chroma Level
 Confirm that the beam spots of each color (R, Y_L, G, C_y, G, B and M_G) are inside the area "田".



Notes

- Partial difference between scale and signal level is caused by photographic error.
- If the specifications are not met, carry out from "3-3-2. INT SC Phase Adjustment" through "3-3-9. Chroma (YC) Level Adjustment".
- Use the vectorscope conforming to setup "7.5 IRE". (for NTSC)

3-2-2. Sensitivity Measurement Confirmation

Object: Overall white
Light: 3200K, 2000 lux
 (If the pattern box is used, set the AUTO mode)

Equipment: Waveform monitor


Preparation:

- Shoot the overall white pattern covering fully the monitor frame.
- Lens iris → F11
- OUTPUT/DL/DCC + switch: CAM/DCC +
- W. BAL switch: PRESET

Note

If the zoom position is at the "TELE" edge, F value of the camera may decrease. When decreasing, adjust the distance between the pattern box and the camera and bring the zoom position slightly from the "TELE" edge to "WIDE".

Specification: 100 ± 10 IRE (for NTSC)
 700 ± 70 mV (for PAL)



Note

If the specification is not met, perform "3-3-11. CCD OUT Level Adjustment".

3-3. Camera Adjustment

Note

Before the adjustment, enter the "PAGE 1" of SERVICE menu, and perform the "RESET".

3-3-1. Sub-Carrier Frequency Adjustment


Equipment: Frequency counter

To be extended: ES-32 board (for DXC-D35/D35P)
ES-33 board (for DXC-D35WS/D35WSP)

Test point: TP501 (GND: E501)
/ES-32 board (for DXC-D35/D35P)
/ES-33 board (for DXC-D35WS/D35WSP)

Adjusting point: SERVICE menu "PAGE 8"
→ SC FREQ:
Adjust the sub-Carrier Frequency by
UP ▲ switch or DOWN ▼ switch to
meet the specification.

Specification: $3,579,545 \pm 10$ Hz (for NTSC)
 $4,433,618 \pm 10$ Hz (for PAL)



ES-32 board (A side) (DXC-D35/D35P)
ES-33 board (A side) (DXC-D35WS/D35WSP)

3-3-2. INT SC-H Phase Adjustment

Note

Stated below is a procedure with the SC-H phase measuring equipment (Tektronix Waveform monitor 1765).
If any other equipment is used, perform adjustment at the following adjustment point by reading the instruction manual attached.

Equipment: Waveform monitor (SC-H Phase mode)


Preparation:

- Put the Tektronix Waveform monitor 1765 to SC-H mode.

Test point: VIDEO OUT connector

Adjustment Procedure

1. SERVICE menu "PAGE 8"
→ SC-H
2. Adjust the phase relationship between SC (Burst) and H beam spot correctly by UP ▲ switch or DOWN ▼ switch.



Note

After this adjustment, set the mode of Tektronix Waveform monitor 1765 to "WFM" mode.

3-3-3. Y/R-Y/B-Y CLP Level Adjustment

Equipment: Oscilloscope
To be extended: IF-532 board (for DXC-D35/D35P)
 IF-700 board (for DXC-D35WS/D35WSP)
Preparation: OUTPUT/DL/DCC + switch: BARS
Test point: TP60, 61, 62 (GND: TP63)
 /EX-490 board
Trigger: HD (TP83/EX-490 board)


Adjustment Procedure

1. Select "PAGE 10" of SERVICE menu, make sure that R-Y and B-Y mode must be "ON".
2. SERVICE menu "PAGE 6"
 → Y CLP:
 R-Y CLP:
 B-Y CLP:
3. Adjust the following items by UP ▲ switch or DOWN ▼ switch to meet the specification.

Note

In case of Y CLP for NTSC model, perform the adjustment as follows.

- ① Select "PAGE 9" of SERVICE menu, and set the "SETUP" to "OFF".
- ② Select "PAGE 6" of SERVICE menu, and move the cursor to Y CLP.
- ③ Adjustment: $A = 0 \pm 5$ mV
- ④ Select "PAGE 9" of SERVICE menu, and set the "SETUP" to "ON".
- ⑤ And return to "PAGE 6".



DXC-D35/D35WS(UC)
 DXC-D35P/D35WSP(CE) V1

3-3-4. Y/SYNC/R-Y/B-Y Level Adjustment

Equipment: Oscilloscope
To be extended: IF-532 board (for DXC-D35/D35P)
 IF-700 board (for DXC-D35WS/D35WSP)
Preparation: OUTPUT/DL/DCC + switch: BARS
Test point: TP60, 61, 62 (GND: TP63)
 /EX-490 board
Trigger: HD (TP83/EX-490 board)

Adjustment Procedure

Note

Following procedures are for DXC-D35WS/D35WSP. For DXC-D35/D35P, perform steps 2 to 4 below.

1. Select "PAGE 9" of ADVANCE menu, set "16:9/4:3" to "4:3".
2. Select "PAGE 10" of SERVICE menu, make sure that R-Y and B-Y mode are "ON".
3. SERVICE menu "PAGE 5"
 → Y LEV:
 R-Y LEV:
 B-Y LEV:
 SYNC LEV:
 SETUP LEV:


Note

In case of Y LEV for NTSC model, perform the adjustment as follows.


- ① Move the cursor to Y LEV.
- ② Adjust the "A" of Y LEV level.
- ③ Move the cursor to SETUP LEV, and adjust the "F" of setup level.
- ④ Repeat step ① through ③ several times.
4. Adjust by UP ▲ switch or DOWN ▼ switch.
5. Select "PAGE 9" of ADVANCE menu, and set the "16:9/4:3" to "4:3".
6. SERVICE menu "PAGE 5"
 → W Y LEV:
 W R-Y LEV:
 W B-Y LEV:
7. Adjust by UP ▲ switch or DOWN ▼ switch to meet the specification.

(continued)


Item	Test Point	Specification
Y LEV	TP61	NTSC: $A = 714 \pm 10$ mV F = 54 ± 5 mV
*W Y LEV	TP61	PAL: $A = 700 \pm 10$ mV NTSC: $A = 714 \pm 10$ mV PAL: $A = 700 \pm 10$ mV
SYNC LEV	TP61	NTSC: $B = 286 \pm 5$ mV PAL: $B = 300 \pm 5$ mV



R-Y LEV	TP60	NTSC: $C = 700 \pm 20$ mV PAL: $C = 525 \pm 20$ mV
*W R-Y LEV	TP60	NTSC: $C = 700 \pm 20$ mV PAL: $C = 525 \pm 20$ mV



B-Y LEV	TP62	NTSC: $D = 700 \pm 20$ mV PAL: $D = 525 \pm 20$ mV
*W B-Y LEV	TP62	NTSC: $D = 700 \pm 20$ mV PAL: $D = 525 \pm 20$ mV



*: DXC-D35WS/35WSP only


3-3-5. Carrier Balance Adjustment

Equipment: Vectroscope (MAX GAIN)
Preparation: OUTPUT/DL/DCC + switch: BARS
Test point: VIDEO OUT connector


Adjusting point

- SERVICE menu "PAGE 7"
→ R-Y C/B
B-Y C/B
- Adjust by the UP ▲ switch or DOWN ▼ switch to bring the beam spot of the black level in the center of the vectorscope.

[for NTSC]



[for PAL]



3-3-6. Chroma (VBS) Level Adjustment

Note

Use the vectorscope conforming to setup "7.5 IRE". (for NTSC)

Equipment: Vectorscope

To be extended: ES-32 board (for DXC-D35/D35P)
ES-33 board (for DXC-D35WS/D35WSP)

Preparation:

- GAIN switch/Vectorscope: 75 % CAL
- Adjust the PHASE control on the vectorscope so that the burst spot is overlapped to the 75 % axis.
- OUTPUT/DL/DCC + switch: BARS

Test point: VIDEO OUT connector

- Adjust the adjusting volume controls below to enter the beam spot of each color within the area "田" specified for each color on the vectorscope screen.

● RV503 (B-Y LEV)

/ES-32 board (DXC-D35/D35P)

/ES-33 board (DXC-D35WS/D35WSP)

● FL502 (PHASE)

/ES-32 board (DXC-D35/D35P)

/ES-33 board (DXC-D35WS/D35WSP)

● RV504 (CHROMA VBS LEV)

/ES-32 board (DXC-D35/D35P)

/ES-33 board (DXC-D35WS/D35WSP)

- Then, perform above procedure item 1 again

Adjustment Procedure

- [for NTSC]

SERVICE menu "PAGE 7"

→ B-Y BST

Adjust by the UP ▲ switch or DOWN ▼ switch so that burst spot is located at 75 % scale mark on the vectorscope screen.

(In case of NTSC, make sure that "R-Y BST" must be "0".)

[for PAL]


SERVICE menu "PAGE 7"

→ R-Y BST



B-Y BST

Adjust "R-Y BST" and "B-Y BST" alternately by UP ▲ switch or DOWN ▼ switch so that burst spot is located at 75 % scale mark on the vectorscope screen.

[for NTSC]



[for PAL]



ES-32 board (A side) (DXC-D35/D35P)

ES-33 board (A side) (DXC-D35WS/D35WSP)

3-3-7. Y (VBS) Level Adjustment


Equipment: Waveform monitor
To be extended: ES-32 board (for DXC-D35/D35P)
 ES-33 board (for DXC-D35WS/D35WSP)
Preparation: OUTPUT/DL/DCC+ switch: BARS
Test point: VIDEO OUT connector

Adjustment Procedure

- [for NTSC]
 - SERVICE menu "PAGE 9"
 - SET UP : ON

[for PAL]
 • SERVICE menu "PAGE 9"
 → COMP LVL: 525 (not 700)

- Adjusting point:** ⦿RV501 (Y LEVEL)
 /ES-32 board (for DXC-D35/D35P)
 /ES-33 board (for DXC-D35WS/D35WSP)
Specification: B = 100 ± 2 IRE (for NTSC)
 B = 700 ± 10 mV (for PAL)



Note

In the NTSC model, check that the set up level is within $A = 7.5 \pm 5.0$ IRE.
 If without the range, perform the setup level adjustment in Section 3-3-4, "Y/SYNC/R-Y/B-Y Level Adjustment."



3-3-8. Y (YC) Level Adjustment

Note

Be sure that "3-3-7. Y (VBS) Level Adjustment" is completed.

Equipment: Oscilloscope
To be extended: ES-32 board (for DXC-D35/D35P)
 ES-33 board (for DXC-D35WS/D35WSP)
Preparation: OUTPUT/DL/DCC + switch: BARS
Test point: TP66 (GND: TP67)/EX-490 board
Trigger: HD (TP84/EX-490 board)

Adjusting point: ⦿RV502 (Y LEVEL)
 /ES-32 board (for DXC-D35/D35P)
 /ES-33 board (for DXC-D35WS/D35WSP)
Specification: A = 1.00 ± 0.02 V (for NTSC)
 A = 1.00 ± 0.02 V (for PAL)




ES-32 board (A side) (DXC-D35/D35P)
 ES-33 board (A side) (DXC-D35WS/D35WSP)

3-3-9. Chroma (YC) Level Adjustment



Equipment: Oscilloscope
To be extended: ES-32 board (for DXC-D35/D35P)
 ES-33 board (for DXC-D35WS/D35WSP)
Preparation: OUTPUT/DL/DCC + switch: BARS
Test point: TP64 (GND: TP65)/EX-490 board
Trigger: HD (TP84/EX-490 board)

Adjusting point: ⒶRV505 (CHROMA (YC) LEV)
 /ES-32 board (for DXC-D35/D35P)
 /ES-33 board (for DXC-D35WS/D35WSP)
Specification: A = 286 ± 5 mV (for NTSC)
 A = 300 ± 10 mV (for PAL)

[for NTSC]



[for PAL]



ES-32 board (A side) (DXC-D35/D35P)
 ES-33 board (A side) (DXC-D35WS/D35WSP)

3-3-10. VF SYNC/BLKG Level Adjustment

Equipment: Oscilloscope
To be extended: ES-32 board (for DXC-D35/D35P)
 ES-33 board (for DXC-D35WS/D35WSP)
Preparation: OUTPUT/DL/DCC + switch: BARS
Test point: TP82 (GND: TP83)/EX-490 board
Trigger: HD (TP84/EX-490 board)

Adjustment Procedure

- SERVICE menu "PAGE 7"
 VF SYNC
 → VF BLKG


Note

For the adjustment procedure, at the first "VF BLKG" adjustment is done, and next, "VF SYNC" adjustment is done.


- Adjust the following items by UP ▲ switch or DOWN ▼ switch to meet the specification.

Item	Test Point	Specification
VF BLKG	TP82	NTSC: A = 50 ± 10 mV PAL: A = 50 ± 10 mV
VF SYNC	TP82	NTSC: B = 290 ± 10 mV PAL: B = 300 ± 10 mV

[for NTSC]



[for PAL]



3-3-11. CCD Output Level Adjustment

Notes

- Usually, this adjustment is not required.
Only when the output level of CCD unit is largely different from the specification, make the adjustment.
- When the new CCD unit for spare parts is replaced, this adjustment is not required because of the correct adjustment at the factory.
- It is advisable to use a reflection type grayscale chart for this adjustment. Further more, before adjustment, setting of the luminance (or brightness) on the chart surface and the color temperature setting are required. For details, refer to Section 3-1-5, "Maintaining the Grayscale Chart".

Lightening: 3200K, 2000 lux
(When using the pattern box, set to Auto mode.)

Object: Grayscale chart

Equipment: Oscilloscope

To be extended: VA-165 board (for DXC-D35/D35P)
VA-185 board (for DXC-D35WS/D35WSP)



Preparation:

- OUTPUT/DL/DCC+ switch: CAM/DCC +
- W. BAL switch: PRESET
- Select a large lens iris to shoot the gray scale chart covering fully the underscanned frame.
(Refer to Section 3-1-4.)
- Adjust the lens iris so that the video level at TP27/extension board (VA-185 board) is 165 ± 5 mV.

Trigger: HD (TP72/EX-490 board)

Adjustment Procedure

1. **Test point:** TP15/EX-490 board
Adjusting point: ⓈRV1/PA-254 board
Specification: $A = 165 \pm 5$ mV
2. **Test point:** TP21/EX-490 board
Adjusting point: ⓈRV1/PA-256 board
Specification: $A = 165 \pm 5$ mV



3-3-12. Carrier Adjustment at DPR (Double Pixel Reading) ON

Equipment: Waveform monitor, Vectorscope
(MAX GAIN)

Preparation:


- HYPER GAIN switch: ON
- OUTPUT/DL/DCC + switch: CAM/DCC +

Test point: VIDEO OUT connector

Adjustment Procedure


1. SERVICE menu "PAGE25"
→ R D.DARK:
G D.DARK:
B D.DARK:
2. Set the lens iris to the close (C).
3. Adjust the settings of R D.DARK, G D.DARK and B D.DARK by UP ▲ switch or DOWN ▼ switch to meet the specifications 1 and 2 below.

Specification 1: $A = 10 \pm 1$ IRE (for NTSC)
 $A = 20 \pm 7$ mV (for PAL)




Specification 2: Beam spot of the black level comes to the center position of the vectorscope screen

[for NTSC]



[for PAL]



4. Check that the specifications 1 and 2 are satisfied at GAIN 0 dB.

3-3-13. Shading Adjustment

Note

When replacing the lens and CCD unit, perform this adjustment.

Object: Overall white

Equipment: Waveform monitor, Oscilloscope

To be extended: VA-169 board (DXC-D35/D35P)
VA-185 board (DXC-D35WS/D35WSP)
VD (TP73/EX-490 board)

Trigger:

Preparation:

[When replacing the CCD unit]

Attach the lens VCL-918BY or equivalent to this unit.
(Refer to the instruction manual, adjusting the Lens in Section 5, "Designating the lens".)

Set the LENS SEL of the ADVANCE menu "PAGE 4" to

1. Set the data following the adjustment procedure.

The R,G,B value of the number 1 takes as the reference to the values of LENS SEL 2, 3 and 4.

Reference

LENS SEL	EXTENDER OFF			EXTENDER ON		
	R	G	B	R	G	B
1 (Addition value)						
2	-15	10	-15	0	0	0
3	-25	20	-25	0	0	0
4	0	0	0	0	0	0

[When replacing the lens]

Set the LENS SEL of the ADVANCE menu "PAGE 4" to

4. Set the data following the adjustment procedure.


Adjustment Procedure

1. SERVICE menu "PAGE 2"
→ R W. SHAD:
G W. SHAD:
B W. SHAD:
2. Shoot the center portion of pattern box by zooming the lens to fully TELE position.
If the lens has an extender, set the extender OFF.

3-3. Camera Adjustment

- Adjust the lens iris to bring the white level "A" to 70 ± 2 IRE.

Test point: VIDEO OUT connector




- In the following items, by pressing the UP ▲ or DOWN ▼ switches, adjust the waveform of the oscilloscope to be flat.

GND: TP38/EX-490 board

Item	Test point	Specification
R W. SHAD	CL101	
G W. SHAD	CL201	
B W. SHAD	CL301	

- If the lens has an extender, set the extender ON and perform the adjustment of step 4.



VA-169 board (B side) (DXC-D35/D35P)
VA-185 board (B side) (DXC-D35WS/D35WSP)

3-3-14. Flare Adjustment

Object: Grayscale chart

Equipment: Waveform monitor

Preparation:

- OUTPUT/DL/DCC + switch: CAM/DCC +
- Select a large lens iris and shoot the grayscale chart covering fully the underscanned frame.
(Refer to Section 3-1-4.)

Test point: VIDEO OUT connector

Adjustment Procedure

- SERVICE menu "PAGE 3"

→ R FLARE: x


G FLARE: 5

B FLARE: x


Note

Make sure that "G FLARE" is "5".

- Push the WHT/BLK switch in the "BLK" direction to make a black balance.
- Adjust the lens iris to bring the white level to $A = 100$ IRE.
- With the W. BAL switch set to "A", push the WHT/BLK switch in the "WHT" direction to make a white balance.



- Make the lens iris large by two steps.
- Adjust the flare with UP ▲ and DOWN ▼ switches alternatively to minimize the carrier leakage level.



3-3-15. MIC Level/MIC Level IND Adjustment

Equipment: Oscilloscope

Preparation: OUTPUT/DL/DCC+ switch: BARS

Adjustment Procedure

MIC Level Adjustment

Test point: CL201 (GND: Capacitor C202 ⊕ side)

/MB-629 board (for DXC-D35/D35P)


/MB-785 board (for DXC-D35WS/D35WSP)

Adjusting point: ⓈRV201

/MB-629 board (for DXC-D35/D35P)



/MB-785 board (for DXC-D35WS/D35WSP)

Specification: $A = 110 \pm 5 \text{ mV}$



MIC Level IND Adjustment

1. SERVICE menu "PAGE 17"
→ MIC ADJ
2. Adjust by the DOWN ▼ switch, and stop at the point where the ♪ mark just appears on the monitor screen.
3. Adjust by the UP ▲ switch, and stop at the point where the ♪ mark just disappears on the monitor screen.
4. Set the DOWN ▼ switch at the five-descending position from the point the ♪ mark disappears.



MB-629 board (B side) (DXC-D35/D35P)
MB-785 board (B side) (DXC-D35WS/D35WSP)

3-3-16. Character Position Adjustment

Equipment: Color monitor (or, B/W monitor)
Preparation: OUTPUT/DL/DCC + switch: BARS
Test point: MONITOR OUT connector

Adjustment Procedure

1. Set the "MARKER" to "ON" on the BASIC menu.
2. Select "PAGE 9" on the ADVANCE menu, set "16:9/4:3" to "16:9" position.

Note

This step shall be performed for DXC-D35WS/D35WSP only.


3. Set the "MARKER" to "CENT/90 %" on the "PAGE 4" of ADVANCE menu.

4. Adjusting point:

- CV1/MB-629 board (for DXC-D35/D35P)
- CV3/MB-785 board (for DXC-D35WS/D35WSP)



Specification: "a" ≒ "b" (for NTSC)

[for NTSC]



Specification: Bring the characters to the safety zone as close as possible, yet prevent them from overlapping.
(for PAL)

[for PAL]



MB-629 board (B side) (DXC-D35/D35P)
MB-785 board (B side) (DXC-D35WS/D35WSP)

3-3-17. 4 : 3 Title Adjustment (Only for DXC-D35WS/D35WSP)


Equipment: Color monitor (or, B/W monitor)
Preparation: OUTPUT/DL/DCC + switch: BARS
Test point: MONITOR OUT connector

Adjustment Procedure

1. Select "PAGE 9" on the ADVANCE menu, set "16:9/4:3" to "4:3" position.
2. Select "PAGE 8" on the ADVANCE menu, set "CLOCK IND" to "BARS" position.
3. Set the cursor to "EXIT MENU" then press the UP ▲ switch to return to the menu selecting screen.
4. **Adjusting point:** ●CV1/MB-785 board



Specification: Align the center of the two-digit figure XX with the boundary between magenta and red of the color bar as shown in the following figure. (for NTSC)

[for NTSC]



Specification: Align the left end of the ":" with the boundary between magenta and red of the color bar as shown in the following figure. (for PAL)

[for PAL]



MB-785 board (B side) (DXC-D35WS/D35WSP)

3-4. Changing the Standard Setting Values (Video Level)

When changing the setting of black level, flare, gamma, manual knee and white clip by the user's desire, perform the procedures below.

3-4-1. Setting Status before Changing the Setting.

• Side Panel

GAIN switch:	LOW (0 dB)
OUTPUT/DL/DCC +:	CAM/DCC +
WHITE BAL switch:	A
ZEBRA switch:	OFF
HYPER GAIN switch:	OFF
SET UP switch:	STD
EZ MODE button:	OFF
A.IRIS MODE:	STD
ATW button:	OFF

• Front Panel

FILTER control:	1 (3200 K)
SHUTTER switch:	OFF

• Lens

IRIS:	M (Manual)
ZOOM:	M (Manual)


3-4-2. Changing the Setting Value of Black Level

Equipment: Waveform monitor
Test point: VIDEO OUT connector

Procedure for changing the setting

1. Set the lens iris to the close position (C).
2. Push the WHT/BLK switch in the "BLK" direction to make a black balance.
3. SERVICE menu "PAGE 15"
→ M.BLACK:
4. Set the black level A with the UP ▲ or DOWN ▼ switch.

M.BLACK Standard setting value = 2070 (for NTSC)
 2075 (for PAL)




3-4-3. Changing the Flare Compensation Setting Value

Object: Grayscale chart
Equipment: Waveform monitor
Preparation: Select a large lens iris and shoot the grayscale chart covering fully the underscanned frame.
Test point: VIDEO OUT connector

Procedure for changing the setting


- SERVICE menu "PAGE 3"
 → R FLARE: x
 G FLARE: 5
 B FLARE: x
- Adjust the lens iris to bring the white level A to A = 100 IRE.



Note

To make the flare compensation more effectively, set a big value to G FLARE.

G FLARE standard setting value = 5



- Make the lens iris large by more two steps.
- Adjust the "R FLARE" and "B FLARE" alternatively with the UP ▲ or DOWN ▼ switch in order to minimize the carrier leakage level.

3-4-4. Changing the Gamma Correction Setting Value

Note


It is advisable to use a reflection type grayscale chart for this adjustment. Further more, before adjustment, setting of the luminance (or brightness) on the chart surface and the color temperature setting are required. For details, refer to Section 3-1-5, "Maintaining the Grayscale Chart".

Object: Grayscale chart
Equipment: Waveform monitor
Preparation: Select a large lens iris and shoot the grayscale chart covering fully the underscanned frame.
Test point: VIDEO OUT connector

Procedure for changing the setting

- Push the WHT/BLK switch in the "WHT" direction to make a white balance.
- Adjust the lens iris to bring the white level to A = 100 IRE.
- SERVICE menu "PAGE15"
 → M.GAMMA
- Set the cross point B of the grayscale with the UP ▲ or DOWN ▼ switch.

M.GAMMA standard setting value = 132




3-4-5. Changing the Manual Knee/White Clip Setting Value


Equipment: Waveform monitor
Preparation: OUTPUT/DL/DCC + switch : CAM/DL
Test point: VIDEO OUT connector

Procedure for changing the setting

1. **Changing of the knee point setting value.**
 ADVANCE menu "PAGE 2"
 → DL: OFF
2. SERVICE menu "PAGE 10"
 → TEST SAW : 2
3. FILE menu "PAGE 6"
 → M.KNEE P:
4. Set the knee point with the UP ▲ or DOWN ▼ switch.



5. **Changing of the knee slope setting.**
 FILE menu "PAGE 6"
 → M.KNEE S :
6. Set the knee slope with the UP ▲ or DOWN ▼ switch.



Reference

In STD, HISAT, FL, FILMLIKE, SVHS/VHS and USER1 to 3 files, the manual knee setting is available in every file. To return the changed manual knee setting values to the standard setting values, perform the following procedures.

- (1) Set SETUP switch to STD.
- (2) FILE menu "PAGE 3"
 Recall FILE STD.
- (3) FILE menu "PAGE 6"
 Set M.KNEE P and M.KNEE S.
- (4) FILE menu "PAGE 12"
 Store *STD in FILE STD.
- (5) FILE menu "PAGE 3"
 Recall FILE STD to STD
- (6) Set SETUP switch to FILE.
- (7) FILE menu "PAGE3"
 Recall FILE HISAT.
- (8) FILE menu "PAGE 6"
 Set M.KNEE P and M.KNEE S.
- (9) FILE menu "PAGE 12"
 Store *HISAT in FILE HISAT.
- (10) For each of FL, FILMLIKE, SVHS/VHS and USER 1 to 3 files, perform the steps 7 to 9.
- (11) FILE menu "PAGE 3"
 Recall FILE HISAT to HISAT.
- (12) Return SETUP switch to STD.

7. Changing of the white clip level setting value.

The values at the factory setting are as follows.

NTSC Model = 107 IRE

PAL Model = 109%

SERVICE menu "PAGE 16"

→ WHT CLIP:

8. The white clip level can be decreased with the DOWN ▼ switch.

W.CLIP standard setting value = 255

Note

When reducing the white clip setting value, it is recommendable to change the former mentioned manual knee setting in order to keep the reproduction of the grayscale in the high luminance level part.